



UNIVERSITI PUTRA MALAYSIA

**COMPACT BANDPASS FILTERS USING DUAL-MODE MICROSTRIP
CLOSED-LOOP RING RESONATORS FOR WIRELESS
COMMUNICATION SYSTEMS**

BABAK KAZEMI ESFEH

FK 2009 79



**COMPACT BANDPASS FILTERS USING DUAL-MODE MICROSTRIP
CLOSED-LOOP RING RESONATORS FOR WIRELESS
COMMUNICATION SYSTEMS**

By

BABAK KAZEMI ESFEH

**Thesis Submitted to the School of Graduate Studies, Universiti Putra Malaysia, in Fulfilment of
the Requirement for the Degree of Master of Science**

August 2009



DEDICATION

TO

MY BELOVED PARENTS



ABSTRACT

Abstract of thesis presented to the Senate of University Putra Malaysia in fulfilment of the requirement for the degree of Master of Science

COMPACT BANDPASS FILTERS USING DUAL-MODE MICROSTRIP CLOSED-LOOP RING RESONATORS FOR WIRELESS COMMUNICATION SYSTEMS

By

BABAK KAZEMI ESFEH

August 2009

Chairman: Alyani Ismail, PhD

Faculty: Engineering

Microwave filters have important role in many wireless and communication systems such as satellite and cellular mobile organizations. In such kind of systems, factors such as compact size, low cost, light weight, high performance, and low loss in designing of microwave filters are of primary importance. In comparison with waveguide filters, microstrip filters are smaller and in such applications mentioned before there are needs to have smaller microstrip filters.

In this thesis, filters using dual-mode ring resonators is proposed, because they can be designed easier than the other kind of microwave filters and are more compact. In this thesis, a new compact form of dual-mode microstrip octagonal loop resonator filter is proposed in two forms; conventional and compact. These structures are designed to operate at WiMax frequency of 2.3 GHz with a 5% fractional bandwidth. The new dual-mode resonator will be produced by adding a rectangular patch inside the loop resonator. The experimental results and simulated values are presented and show good agreement.



The filter is fabricated on CER-10 substrate having a relative dielectric constant of 10 and 0.64 mm thickness. The primary dimension of the filter is 15.8 mm×15.8 mm and the measured minimum insertion loss is 1.68 dB and return loss is better than -20 dB. After minimization and compressing the filter structure, the final dimension is reduced to 9.1 mm×9.1 mm. The minimum insertion loss in this structure is 1.52 dB and the return loss is better than -20 dB. In the final design in addition to size reduction (about 42%), feed lines structure is changed from orthogonal to straight line form, which are more desirable in microwave networks. This new design is reduced in size by approximately 25% compared to the conventional square loop dual-mode filter. By using meander square loop structure more reduction in size (about 27%) can be achieved but this filter configuration has a weak frequency response including high passband insertion loss (more than 2.6 dB) and return loss less than -12dB at the same center frequency. Therefore its performance is less than the dual-mode filter proposed in this thesis.

Apart from WiMax, this model of filters is also useful for WLAN and mobile communication applications, because it is compact in size, low loss and has good performance due to its elliptic response with sharp rejection and adequate fractional bandwidth.

ABSTRAK

Abstrak tesis yang dikemukakan kepada Senat Universiti Putra Malaysia sebagai memenuhi keperluan untuk ijazah Master of Sains

PENURAS LULUS JALUR KOMPAK MENGGUNAKAN PENYALUN MIKROSTRIP GELUNG PUSINGAN TERTUTUP DUA MOD UNTUK SISTEM KOMUNIKASI TANPA WAYAR

Oleh

BABAK KAZEMI ESFEH

Ogos 2009

Pengerusi: Alyani Ismail, PhD

Fakulti: Kejuruteraan

Penapis mikrogelombang mempunyai banyak peranan dalam sistem wayarles dan sistem komunikasi seperti satelit dan sistem telefon mudah alih. Dalam sistem tersebut, faktor dalam sesuatu rekaan penapis mikrogelombang adalah sangat penting dan perlu diambilkira. Saiz yang bersesuaian, harga yang berpatutan, ringan, kualiti yang tinggi, dan hingar yang rendah adalah antara faktor yang diperlukan untuk meningkatkan mutu produk dan mengurangkan kos perlaksanaannya. Saiz penapis mikrogelombang adalah lebih kecil berbanding penapis waveguide. Tetapi, untuk aplikasi tersebut, penggunaan penapis mikrogelombang yang bersaiz kecil sangat bersesuaian. Terdapat banyak permintaan terhadap penapis yang menggunakan penyalun gelang dua mod. Rekaannya adalah lebih ringkas berbanding penapis mikrogelombang yang lain. Dalam tesis ini, satu bentuk penapis dual mode mikrostrip penyalun gelang berbentuk oktagon yang padat dicadangkan dalam dua bentuk iaitu; piawai biasa dan kompak. Struktur ini direka untuk beroperasi pada frekuensi 2.3 GHz sebagai frekuensi WiMax dengan 5% pecahan lebar jalur.

Penyalun dua mod akan dihasilkan dengan menambahkan bahagian berbentuk segi empat tepat di dalam gelung penyalun. Penapis ini telah direka , CER-10 menggunakan substrat yang mempunyai pekali dielektrik 10 dan ketebalan 0.64 mm. Struktur asal penapis ialah 15.8 mm x 15.8 mm dan nilai kehilangan sisipan ialah 1.68 dB dan nilai kehilangan pulangan ialah 20 dB. Selepas proses pemadatan dan pengurangan struktur penapis, dimensi penapis dikurangkan kepada 9.1mm x 9.1 mm. Jumlah minimum kehilangan sisipan dalam struktur ini adalah 2.6dB dan kehilangan pulangan lebih tinggi dari 22 dB. Dalam rekabentuk pengurangan saiz di peringkat akhir (dalam 42%), struktur garis masukan ditukar dari bentuk paksi yang bersudut tepat ke bentuk garis lurus, yang lebih diperlukan dalam rangkaian mikrogelombang. Rekabentuk ini juga dibandingkan dengan bentuk penapis piawai biasa gelung segiempat dua mod yang mempunyai pengurangan saiz sebanyak 25%. Dengan menggunakan struktur segiempat gegelung kekelokan , pengurangan saiz (dalam 27%) boleh dicapai. Tetapi penapis jenis ini mempunyai kelemahan dari segi sambutan frekuensi termasuklah kehilangan sisipan jalur lalu yang tinggi (lebih daripada 2.6 dB) dan return loss kurang daripada -12dB di frekuensi tengah yang sama. Oleh yang demikian, persembahannya adalah kurang memuaskan daripada penapis dual mode yang dicadangkan dalam tesis ini.

Model penapis ini sangat berguna untuk aplikasi WLAN dan sistem komunikasi, kerana saiz yang padat, kehilangan yang rendah, mempunyai keputusan yang baik dalam menapis dan pecahan lebar jalur yang memadai. Keputusan eksperimen dan simulasi yang dicadangkan telah menunjukkan mutu persembahan yang baik.

ACKNOWLEDGEMENT

Firstly, I wish to thank GOD, the merciful and kind for all the blessing upon me.

My deepest gratitude and appreciation goes to my supervisor, Dr. Alyani Ismail for all her valuable comments, suggestions, patience and encouragement in my study and the preparation of this thesis. Her professional review helped me to improve this thesis more.

Also, I would like to thank Dr. Raja Syamsul Azmir b. Raja Abdullah, my co supervisor for his constructive suggestions and helps.

My warmest gratitude goes to my family members especially my mother for her continuous support and encouragement and my father for being my strongest supporter.

Special thanks to my best friend Dr. Vahid Soluk for supporting me in my study from the start of my project until finalizing this thesis.

Finally, I wish to thank to all my friends especially, Adam, Helmi, Aris and Ayub for their help and support.



APPROVAL

I certify that a Thesis Examination Committee has met on (August 7, 2009) to conduct the final examination of (Babak Kazemi Esfeh) on his thesis entitled "**Compact Bandpass Filters Using Dual-Mode Microstrip Closed-Loop Ring Resonators for Wireless Communication Systems**" in accordance with the Universities and University Colleges Act 1971 and the Constitution of the Universiti Putra Malaysia [P.U. (A) 106] 15 March 1998. The Committee recommends that the student be awarded the (Master of Science degree).

Members of the Thesis Examination Committee were as follows:

Dr. Sabira Khatun, PhD

Associate Professor
Faculty of Engineering
Universiti Putra Malaysia
(Chairman)

Dr. Roslina Mohd Sidek, PhD

Associate Professor
Faculty of Engineering
Universiti Putra Malaysia
(Internal Examiner)

Dr. Nor Kamariah Noordin, PhD

Associate Professor
Faculty of Engineering
Universiti Putra Malaysia
(Internal Examiner)

Dr. Mohd Fadzil Ain, PhD

Engineering Campus
Universiti Sains Malaysia
Malaysia
(External Examiner)

Bujang Bin Kim Huat, PhD

Professor and Deputy Dean
School of Graduate Studies
Universiti Putra Malaysia

Date:



This thesis submitted to the Senate of Universiti Putra Malaysia and has been accepted as fulfillment of the requirement for the degree of Master of Science. The members of the Supervisory Committee are as follows:

Alyani Ismail, PhD

Lecturer
Faculty of Engineering
Universiti Putra Malaysia
(Chairman)

Raja Syamsul Azmir Raja Abdullah, PhD

Lecturer
Faculty of Engineering
Universiti Putra Malaysia
(Member)

HASANAH MOHD GHAZALI, PhD

Professor and Dean
School Of Graduate Studies
Universiti Putra Malaysia

Date: 16 October 2009



DECLARATION

I hereby declare that the thesis is based on my original work except for quotations and citations which have been duly acknowledged. I also declare that it has not been previously or concurrently submitted for any other degree at UPM or other institutions.

BABAK KAZEMI ESFEH

Date:

TABLE OF CONTENTS

DEDICATION	ii
ABSTRACT	iii
ABSTRAK	v
AKNOWLEDGMENT	vii
APROVAL	viii
DECLARATION	x
LIST OF TABLES	xiii
LIST OF FIGURES	xiv
LIST OF ABBREVIATIONS AND SYMBOL	xvii
LIST OF SYMBOLS	xviii
1 INTRODUCTION	1
1.1 Background	1
1.2 Problem Statement and Motivation	2
1.3 Research Aim and Objectives	5
1.4 Thesis Scope	5
1.5 Scope of Research	6
1.6 Thesis Organization	8
2 REVIEW AND ANALYSIS OF MICROSTRIP DUAL-MODE FILTERS	10
2.1 Background	10
2.2 Microstrip Lines	12
2.2.1 Characteristic Impedance and Effective Dielectric Constant	14
2.2.2 Guided Wavelength, Phase Velocity, Electric Length and Propagation Constant	15
2.2.3 Microstrip Losses	16
2.2.4 Designing Formulas for Microstrip	17
2.3 Dual-Mode Microstrip Resonators	19
2.4 Transmission-Line Model for Closed-Loop Ring Resonators	20
2.4.1 Transmission-Line Equivalent Circuit	22
2.4.2 Frequency Modes for Ring Resonators	24
2.4.3 Equivalent Lumped Element G, L, C Circuit for Closed-Loop Ring Resonators	27
2.4.4 Curvature Effect in Closed-Loop Resonators	33
2.4.5 Loaded and Unloaded Quality Factor in Closed-Loop Resonators	35
2.5 Microstrip Dual-Mode Resonator Filters	37



3	RESEARCH METHODOLOGY	48
3.1	Background	48
3.2	Design and Calculation of Microstrip Ring Resonator	51
3.3	Narrowband Bandpass Filter using Dual-Mode Octagonal Microstrip Ring Resonator	57
3.4	Compressed Dual-Mode Microstrip Octagonal Bandpass Filter using Meander Loop Resonator	60
4	RESULTS AND DISCUSSION	65
4.1	Background	65
4.2	Simulated Frequency Responses	65
4.3	Measured Frequency Responses	73
5	CONCLUSION	77
5.1	Conclusion	77
5.2	Thesis Contributions	77
5.3	Future Work	78
	REFERENCES	80
	APPENDICES	83
	BIODATA OF STUDENT	85
	LIST OF PUBLICATIONS	86



LIST OF TABLES

Table		Page
1.1	Filter and Resonator specifications for WiMax Application	4
3.1	Main Design Specifications of Dual-Mode Bandpass Filter	51
3.2	Calculated Parameters of the Resonator	52
3.3	Dimensions of the Single Mode Resonator	53
3.4	Dimensions of the Proposed Dual-Mode Octagonal Filter	58
4.1	Dimensions of Compressed Dual-Mode Octagonal Bandpass Filter Using Meander Loop Resonator Depicted in Figure 3.8	69
4.2	Specifications of Conventional Meander Dual-Mode Filter Design Adapted From (Gorur, 2007) and Proposed Meander Dual-Mode Filter Design in This Thesis.	72



LIST OF FIGURES

Figure	Page
1.1 Scope of Research	7
2.1 General Microstrip Structure	13
2.2 Magnetic and Electric Field Lines Structure of Microstrip Lines	14
2.3 TXLINE Software Windows to Obtain Physical Size of Transmission Lines	18
2.4 Lumped Element Equivalent Circuit of a Dual-Mode Resonator	20
2.5 Perturbed Square Ring Resonator	22
2.6 Transmission-Line Model	22
2.7 T-Network Equivalent Circuit	22
2.8 Transmission Line Equivalent Circuit	23
2.9 One-Port Square Ring Resonator	25
2.10 Two-Port Network Model of a Transmission-Line	28
2.11 Input Impedance of Ring Resonator and Its Equivalent Circuit	29
2.12 Input Impedance in Half-Wavelength Transmission Line	29
2.13 Total Input Impedance of Ring Resonator	30
2.14 G, L, C Parallel Circuit Input Impedance of Ring Resonator	32
2.15 The Equivalent Lumped Element Circuit for a Ring Resonator	32
2.16 a) Configuration of Microstrip Bend b) Equivalent Circuit	33
2.17 Curvature in Square and Octagonal Loops	34
2.18 Three Dual-Mode Microstrip Patch Resonators(Curtis, 1991)	38
2.19 New Miniaturized Microstrip Patch Bandpass Filter(Xiao, 2008)	38
2.20 Typical Dual-Mode Microstrip Loop Resonator (Hong, 2001)	39
2.21 Two-Pole Bandpass Filter using Single-Mode Meander Loop Resonator	40

2.22	Quadruple-Mode Coupled-Ring Resonator Bandpass Filter(Lok, 2008)	40
2.23	Dual-Mode Dual-Band Square Bandpass Filter (Chen. Z. X. 2007)	41
2.24	Dual-Mode Dual-Band Triangular Bandpass Filter (Zhao, 2007)	42
2.25	Reconfigurable Square Ring Filter (Sheta, 2008)	42
2.26	Dual-Mode Bandpass Filter with Two Patch Perturbations (Zhao, 2008)	43
2.27	Wide-Band Dual-Mode Loop Resonator Filter (Hsieh, 2003)	44
2.28	The Layout of the Filter with Two Internal Folded Stubs and DGSs	45
2.29	Miniature Dual-Mode Bandpass Filter with Enhanced Parasitic Coupling	46
2.30	Miniature Dual-Mode Bandpass Filter using Meander Loop Resonator	46
3.1	Methodology Block Diagram	50
3.2	Single Mode Square Ring Resonator	53
3.3	Simulation Results of the Single Mode Resonator	54
3.4	(a) Variation of Resonant Frequency versus Feedlines Widths, (b) Variation of Insertion Loss versus Feedlines Widths, For $G = 0.1\text{mm}$	55
3.5	(a) Variation of Resonant Frequency with Gapsizes, (b) Variation of Insertion Loss with Gapsizes, For $W_1 = 0.2\text{mm}$	56
3.6	Proposed Structure of Dual-Mode Octagonal Microstrip Ring Resonator Bandpass Filter	58
3.7	The Simulation Results of Dual-Mode Octagonal Microstrip Ring Resonator Bandpass Filter	59
3.8	Proposed Compressed Dual-mode Octagonal Microstrip Bandpass Filter Using Meander Loop Resonator	61
3.9	Extraction of Coupling Coefficient of Dual-Mode Resonator using the EM Simulator	63
3.10	Simulated S_{21} for Calculating Coupling Coefficient	63
4.1	Simulated S_{21} for Different Perturbation Sizes	66
4.2	Variation of the Filter Frequency Response for Different Tab Position of Feedlines	67
4.3	Simulated Coupling Coefficient versus the size of Perturbation	68



4.4	The Simulation Results for Proposed Dual-Mode Filter	70
4.5	(a) Configuration of the Conventional Meander Dual-Mode Filter Design Adapted From (Gorur, 2007) (b) The Simulation Results of the Conventional Meander Dual-Mode Filter	71
4.6	The Top View of Fabricated Dual-Mode Bandpass Filter	73
4.7	Obtaining the Measurement Results by Connecting the Filter to VNA	73
4.8	The Measured Frequency Response of the Proposed Dual-Mode Filter	74
4.9	(a) The Simulated and Measured S_{21} Frequency Responses of the Filter (b) The Simulated and Measured S_{11} Frequency Responses of the Filter	75

LIST OF ABBREVIATIONS AND SYMBOL

BPF	Bandpass Filter
CAD	Computer-Aided Design
CPW	Coplanar Waveguide
DBS	Direct Broadcast Satellite
DGS	Defected Ground Structure
EM	Electromagnetic Simulator
FBW	Fractional Bandwidth
GPS	Global Positioning Satellite
HTS	High Temperature Superconductor
LTCC	Low-Temperature Cofired Ceramic
MIC	Microwave Integrated Circuit
MEMS	Microelectromechanic Systems
MMIC	Monolithic Microwave Integrated Circuits
TEM	Transverse Electromagnetic Mode
VNA	Vector Network Analyzer
WLAN	Wireless Local Area Network



LIST OF SYMBOLS

ϵ_0	Permittivity of vacuum
ϵ_r	Relative dielectric constant
ϵ_{eff}	Effective dielectric constant
h	Impedance of free space
μ_0	Permeability of vacuum
c	Speed of light in vacuum
S_{11}	Reflection coefficient
S_{21}	Transmission coefficient
l_g	Guided wavelength
Z_0	Characteristic impedance
v_p	Phase velocity
b	Propagation constant
a	Attenuation constant
q	Electrical length
w	Angular frequency
s	Conductivity
g	Complex propagation constant
Q_u	Unloaded quality factor
Q_L	Loaded quality factor



CHAPTER 1

INTRODUCTION

1.1 Background

The majority of applications of today's microwave technology are in communication, radar, environmental remote sensing, military and medical systems. The most universal use of microwave technology is in cellular telephone systems proposed in the 1970s. Global Positioning Satellite (GPS) system and Direct Broadcast Satellite (DBS) system are such successful satellite systems.

After the birth of radar, communication systems using microwave technology began to be developed. Some advantages offered by microwave organizations, including wide bandwidths and line-of-sight propagation, have proved to be important for both satellite and terrestrial communications systems and also have provided the development of low-cost miniaturized microwave components (Pozar, 2005).

Since the electromagnetic spectrum is limited and has to be shared, filters attract so much concern due to their important roles in using the available spectrum efficiently. The main filter functions are to select or limit the RF/microwave signals within assigned spectral limits and to combine or separate different frequencies. Some applications of microwave filters are in wireless and communication systems such as satellite and cellular mobile systems. In these systems more stringent requirements such as higher performance, lighter weight, smaller size and lower cost are desirable. Depending on the requirements and applications, microwave filters may be designed in various transmission line structures such as waveguide, coaxial line and microstrip. In addition, they may be realized as distributed element or lumped element circuits.

1.2 Problem Statement and Motivation

Microwave filters have important role in many wireless and communication systems such as satellite and cellular mobile organizations. In such kind of systems some factors in designing of microwave filters are of primary importance. Compact size, low cost, light weight, high performance, and low loss are some of these factors that are essentially required to enhance the system performance and to reduce the fabrication cost (Pozar, 2005), (Hong, 2001). Parallel-coupled microstrip filters first proposed by Cohn have been used for many years since 1958 (Hasan, 2008). Although they have many advantages such as a wide range of filter fractional bandwidth (FBW) of 5% to 50 %, and simple design procedure, there are still some issues on this type of filters. Major disadvantages of this type of filter include the length of parallel coupled filter that is too long and it further increases with the order of filter. Some techniques have been developed to solve this problem. One of these techniques was using hairpin-line filters including folded $I/2$ resonator structures (Hasan, 2008). Afterwards, microstrip ring resonators in any shape were considered as the building blocks of microstrip bandpass filters and in which they are widely used, because they satisfy the mentioned demands that are essential for microwave filters.

On the other hand, microstrip ring resonators have many interesting characteristics including small size, low fabrication cost, and narrowband (Hsieh, 2000). In 1969, one technique for measuring wavelengths and dispersion characteristics of the relative permittivity of a microstrip line has been done by Troughton (Wolff, 1971) with the help of ring resonators. Microstrip ring resonators are also used for the measurement of phase velocity, and effective dielectric constant. Since no open-end

effects need to be considered in microstrip ring resonators, using them instead of the linear resonator for dispersion measurements is more desirable (Wolff, 1971 and Chang, 1987). In 1970 the theory of the ring resonator has been introduced by Wolff and Knoppik. In this theory, the ring resonator has been considered as a cavity resonator with electric walls on the top and bottom and magnetic walls on the side border. The curvature of the ring affects the resonance frequencies and this effect become larger by using lines with small impedances and substrate materials with small relative permittivity. Therefore, wider resonators are more affected in the higher-order resonances by the curvature, and as the width increases, this influence become larger. For resonators with impedances higher than 20Ω (for example 50, 90, and 110Ω) the effective relative permittivity is almost independent of the length of the resonator (Wolff, 1971). Another factor that affects the resonant frequency is the coupling gap. To calculate the coupling gap effects on the resonant frequency, the equivalent circuit of coupling gap that is modeled by a p - network is included in the equivalent circuit of the ring resonator (Chang, 1987). By using this model it can be found that as the coupling gap decreases, the resonant frequency become lower, but for most ranges of the coupling gap size, the influences on resonant frequency are small and negligible (Chang, 1987). The main discussing concept in this thesis is on dual-mode ring resonators. During recent years, they have been more considered and greatly used for microwave bandpass filter in wireless local area network (WLAN) applications and mobile communication systems (Chen, 2007).

Microstrip dual-mode filters have many interesting characteristics, such as narrowband, high Q, easy-to-design, and compact size. The main advantage of these types of filters is that in dual-mode each resonator operates as a doubled tuned resonant circuit and therefore, an n -degree filter can be achieved in more compact

configurations due to the halved number of resonators (Hong, 2001 and Chen, 2007). In addition to using dual-mode filters, there are some other useful methods to achieve a compact size in filter design. One of these techniques is to have different parts of filter bent. This could be the best solution to get more compact sizes especially for filters with stubs and long straight transmission lines.

Ultra-wideband filter reported in (Razalli, 2008) and wideband filter reported in (El-Shaarawy, 2008) are among the structures making use of method of bending the lines. Although miniaturizing of microwave filters can be done by using substrates with high dielectric constant, or lumped element or different transmission lines such as coplanar waveguide (CPW), reduction in size with changing the geometry of the filters using microstrip transmission lines is more desirable. This is because high dielectric permittivity will often introduce more surface waves and losses, and while filters using coplanar waveguide (CPW) can be found in quite compact sizes, however they also introduce more insertion losses. Hence, microwave filters using coplanar waveguide are seldom used in the millimetre-wave range, despite their wide applicability in monolithic microwave integrated circuits (MMICs) due to their ability in easily integrating series and shunt elements and simplicity of fabrication (Ismail, 2008).

In this thesis, by applying dual-mode microstrip closed-loop resonator, a compact narrowband bandpass filter applicable for WiMax and WLAN applications is introduced, designed, fabricated and tested.

Table 1.1: Filter and Resonator specifications for WiMax Application

Parameters	Specification
Fractional Bandwidth, BW_{3dB}	5 %
Center Frequency, f_0	2.3 GHz

Passband Insertion Loss	Less than 3 dB
Passband Return Loss	Better than – 20 dB

The main specifications of this proposed filter is shown in Table 1.1. It is shown that by using proper substrate material and filter structure in octagonal meander closed-loop shape a compact filter with good performance as mentioned in Table 1.1 can be achieved.

1.3 Research Aim and Objectives

This thesis presents a miniaturization technique of microwave filters by using dual-mode microstrip resonators and investigates their performance comparing with other kinds of filter structures. Even though dual-mode filters are essentially small and compact in size, but in many applications such as cellular mobile communication systems, much smaller size is more desirable, therefore some useful techniques can be applied to make the dual-mode filter structure even more compact. The aim of this thesis is to introduce and design a new configuration of compact narrowband bandpass filter with good performance including low insertion loss and return loss, sharp rejection and adequate bandwidth.

To achieve the aim, the main objectives of the thesis are as follows:

1. To design a compact and high performance dual-mode microstrip filter for WiMax applications.
2. To simulate and investigate the frequency response of the filters using an Electromagnetic Simulator software.
3. To fabricate and measure the frequency response of the filter.

1.4 Thesis Scope

As stated earlier, microwave filters are one of the most important parts of the cellular mobile and satellite systems and in this kind of circuits, compactness and high

performance are of primary importance. Of course, some other parameters such as low cost, light weight and low loss have also important role in enhancing the system performance. In the mean time, simplicity of the designing and fabricating of the filter structure is one of the other parameters that can be of an advantage for a filter design.

In this thesis, the narrowband bandpass filter is designed using microstrip dual-mode resonator. The microstrip dual-mode resonator will be constructed of a meander closed-loop in octagonal form. The compactness will be obtained by using dual-mode resonator and by using the dual-mode closed-loop resonator in meander form in which more compact structure can be achieved. Using the microstrip line as the transmission line in this filter design can make design calculation easy. By choosing the closed-loop resonator in octagonal form the curvature effects is decreased, compare with that in similar filter structures designed in square loop shape. The substrate material used has good characteristics that can support the mentioned demands such as low loss, light weight and low cost. Its high dielectric constant also helps to have more compact size. Of course by using better materials with lower loss tangent, lower insertion loss in passband can be achieved.

The operating frequency range of this filter makes it suitable to be used for WiMax applications.

1.5 Scope of Research

Figure 1.1 shows an overview of the scope in this thesis to achieve the desired compact filter structure. The solid lines in the chart exhibit the instruction followed in this thesis to obtain our objective and the dash lines propose other directions that are considered as different methods to minimize the filters size and make their structure more compact