



UNIVERSITI PUTRA MALAYSIA

***NUMERICAL ANALYSIS OF A SYSTEM OF WIRELESS ENERGY
TRANSFER VIA RESONANCE OF MAGNETIC INDUCTION***

RADIN ZA'IM BIN RADIN UMAR

FK 2013 102



UPM
UNIVERSITI PUTRA MALAYSIA
BERILMU BERBAKTI

**NUMERICAL ANALYSIS OF A SYSTEM OF WIRELESS ENERGY TRANSFER
VIA RESONANCE OF MAGNETIC INDUCTION**

By

RADIN ZA'IM BIN RADIN UMAR

**Thesis submitted to the School of Graduate Studies, Universiti Putra Malaysia, in
Fulfillment of Requirement for Degree of Master of Science**

November 2013

COPYRIGHT

All material contained within the thesis, including without limitation text, logos, icons, photographs and all other artwork, is copyright material of Universiti Putra Malaysia unless otherwise stated. Use may be made of any material contained within the thesis for non-commercial purposes from the copyright holder. Commercial use of material may only be made with the express, prior, written permission of Universiti Putra Malaysia.

Copyright © Universiti Putra Malaysia



Abstract of thesis presented to the Senate of Universiti Putra Malaysia in fulfillment of the requirement for the degree of Master of Science

**NUMERICAL ANALYSIS OF A SYSTEM OF WIRELESS ENERGY TRANSFER
VIA RESONANCE OF MAGNETIC INDUCTION**

By

RADIN ZA'IM RADIN UMAR

November 2013

Chairman: Professor Ishak Aris, PhD

Faculty: Engineering

In the early 19th century Nikola Tesla, the inventor well known for his contribution for the development of the present day alternating current system gave rise to the idea of wireless electricity, however it was short lived and sparks insignificant interest to the then society. In 2007, physicist at Massachusetts Institute of Technology (MIT) has demonstrated an efficient scheme of wireless energy transfer via magnetic induction at resonance frequency. The literature has reported several methods to optimize the power delivery and efficiency; as well as theories to explain the behavior of the wireless energy transfer system. However, most of them are based on the Coupled Mode Theory (which was put forward by the MIT physicist), and the Impedance Analysis Model. There are some limitations imposed by these theories, the Coupled Mode Theory despite being widely accepted in the literature are unfamiliar to electrical engineers, in that it introduces variables that does not directly correlate to variables accustomed to electrical engineers, as a result an ample time had to be spent to understand the theory. While the Impedance Analysis is more familiar and simpler, it only solves the system in the frequency domain and does not explain the system relationship to time; thus it only considers the steady state condition and does not provide the transient behavior. This thesis fills the gap by providing a set of numerical equations to solve the currents of a two-coil Wireless Energy Transfer via Resonance of Magnetic Induction in the time domain from an initial condition to a steady state condition by using variables familiar to electrical engineers; with the objective of obtaining the conditions for that maximizes the efficiency and power delivery. The behavior of the system is governed by variables defined by the values of the system's circuit components, and relationship between these variables is investigated by solving the ordinary differential equations of the system's current and providing both the analytical and the numerical solution to the differential equation problem. It was found that, analytical solution of the system's current in the time domain results in a very long algebraic expression, while the numerical solution produces equation much shorter in length. Analysis is done on the numerical solution by simulating the equation in MATLAB programming. The hardware was constructed to test the validity of the numerical solutions to the equations presented. The data presented shows an agreeable result between the hardware and the equation based simulation. Result of analyses performed found that there exist un-

symmetrically between the lower resonant frequency and the upper resonant frequency at high coupling coefficient. It was also found that there exist several load and frequency conditions that give peak power delivery in over-coupled mode. Moreover, a theoretical analysis performed suggest that efficiency at very low coupling coefficient could be maximize by optimizing the ratio self-inductance to the series capacitance in conjunction with a correct terminated load, as such it was shown that efficiency of 55% is obtainable at a very low coupling coefficient of 0.005. Finally, this thesis also provides a set of equations to calculate the mutual inductance and magnetic field of the system's coil; this is done by applying the Biot-Savart equation to perform finite element calculation.



Abstrak tesis yang dikemukakan kepada Senat Universiti Putra Malaysia sebagai memenuhi keperluan untuk ijazah Master Sains

**ANALISIS PENYELESAIAN BERANGKA KEPADA SISTEM PEMINDAHAN
TENAGA TANPA WAYAR MELALUI ARUHAN MAGNET PADA RESONAN**

Oleh

RADIN ZA'IM RADIN UMAR

November 2013

Pengerusi: Profesor Ishak Aris, PhD

Fakulti: Kejuruteraan

Pada awal abad ke-19 Nikola Tesla, pencipta terkenal dengan sumbangan beliau kepada pembangunan arus ulang alik telah membawa idea tentang elektrik tanpa wayar. Walau bagaimanapun, idea beliau tidak bertahan lama dan tidak mendapat minat daripada masyarakat zaman itu. Pada tahun 2007, ahli-ahli fizik di Massachusetts Institute of Technology (MIT) telah menunjukkan skim pemindahan tenaga tanpa wayar yang cekap melalui aruhan magnet pada frekuensi resonan. Sorotan ilmiah telah melaporkan beberapa kaedah untuk mengoptimumkan penghantaran kuasa dan kecekapan; serta teori-teori untuk menerangkan sifat-sifat sistem pemindahan tenaga tanpa wayar. Walau bagaimanapun, kebanyakannya adalah berdasarkan kepada Teori Mod Berpasangan (yang telah dikemukakan oleh ahli fizik MIT), dan Model Analisis Impedans. Terdapat beberapa batasan pada teori-teori ini, Teori Mod Berpasangan walaupun diterima secara meluas dalam sorotan ilmiah adalah asing kepada jurutera elektrik, ini kerana Teori Mod Berpasangan memperkenalkan pemboleh ubah yang tidak langsung ada kaitan dengan pemboleh ubah yang biasa digunakan jurutera elektrik, akibatnya masa yang banyak diperlukan untuk memahami teori ini. Walaupun Analisis Impedans adalah tidak asing dan lebih mudah, ia hanya menyelesaikan sistem dalam domain frekuensi dan tidak menjelaskan hubungan sistem di dalam domain masa; oleh itu ia hanya menunjukkan kelakuan akhir sistem dan tidak memberikan kelakuan antara permulaan dan pengakhiran. Tesis ini memenuhi jurang dengan menyediakan satu set persamaan berangka untuk menyelesaikan arus dalam sistem dua gegelung pemindahan tenaga tanpa wayar oleh induksi magnet pada frekuensi resonan dalam domain masa dari keadaan awal kepada keadaan akhir dengan menggunakan pemboleh ubah yang biasa digunakan jurutera elektrik; dengan objektif untuk mendapatkan kondisi yang memaksimumkan kecekapan dan penghantaran kuasa. Kelakuan sistem ini dikawal oleh pemboleh ubah yang ditakrifkan oleh nilai-nilai komponen litar sistem, dan hubungan antara pemboleh ubah ini disiasat dengan menyelesaikan persamaan pembezaan kepada arus sistem dan menyediakan kedua-dua penyelesaian analitikal dan penyelesaian berangka kepada masalah persamaan pembezaan. Didapati bahawa penyelesaian analitikal kepada arus sistem dalam domain masa dalam menghasilkan ungkapan algebra yang sangat panjang, manakala penyelesaian berangka menghasilkan ungkapan algebra yang lebih pendek.

Analisis penyelesaian berangka dilakukan oleh simulasi persamaan dalam pengaturcaraan MATLAB . Perkakasan telah dibina untuk menguji kesahihan penyelesaian berangka yang dibentangkan. Data menunjukkan persetujuan antara perkakasan dan simulasi persamaan berangka. Keputusan analisis mendapati bahawa terdapat ketidak-simetri antara frequency resonan yang lebih rendah dan frekuensi resonan yang lebih tinggi pada pekali gandingan yang tinggi. Ia juga mendapati bahawa wujud beberapa kondisi beban dan frekuensi yang memberikan penghantaran kuasa yang maksimum dalam mod 'over-coupled'. Selain itu, keputusan analisis mencadangkan bahawa kecekapan pada pekali gandingan yang sangat rendah boleh dimaksimumkan dengan mengoptimumkan nisbah kearuhan sendiri kepada pemuat siri, beserta beban ditamatkan yang betul. Keputusan telah menunjukkan bahawa kecekapan sebanyak 55% boleh diperolehi pada pekali gandingan yang sangat rendah iaitu 0.005. Akhir sekali , tesis ini juga menyediakan satu set persamaan untuk mengira kearuhan bersama dan medan magnet gegelung sistem; ini dilakukan dengan menggunakan persamaan Biot - Savart untuk melaksanakan pengiraan unsur terhingga.



ACKNOWLEDGEMENTS

All praise is due to Allah, the most Gracious and Merciful, and may peace be upon His Prophets Muhammad Sallallahu Alaihi Wasallam, I am most grateful to Allah for granting me the ability and strength to finish up this research successfully.

Being a post-graduate student is not an easy task, without the help, guidance, support and encouragement from my supervisor Professor Dr. Ishak Aris, it will not be possible for me to endure the difficulties of postgraduate life. I thank him most for his constructive criticisms, and advices given throughout the research duration.

I would like to also convey my gratitude and appreciation to my co-supervisor Ir. Dr. Mohammad Lutfi Othman, for his guidance, insightful questions and valuable comments.

I would like to also convey my thankfulness to Dr Ramizi from Universiti Kebangsaan Malaysia for his guidance, comments, kind assistance and helpful suggestion. The discussions with him had allowed me to obtain a background required for the research.

My highest gratitude to my Father, my Mother and my Wife, without their moral support and motivations it is impossible for me to conduct and complete this research.

Finally I would like to thank my very good friend Saber Elnour, my lab mate from Sudan. My everyday conversations with him has help me a lot to alleviate the stress, and pressure of being a post-graduate student. His suggestions have significantly assisted in drawing of my research plan.

I certify that a Thesis Examination Committee has met on 25 November 2013 to conduct the final examination of Radin Za'im bin Radin Umar on his thesis entitled "Numerical Analysis of a Wireless Energy Transfer System via Resonance of Magnetic Induction" in accordance with the Universities and University Colleges Act 1971 and the Constitution of the Universiti Putra Malaysia [P.U.(A) 106] 15 March 1998. The Committee recommends that the student be awarded the Master of Science.

Members of the Thesis Examination Committee were as follows:

Gorakanage Arosha Chandima Gomes, PhD

Associate Professor
Faculty of Engineering
Universiti Putra Malaysia
(Chairman)

Norhisam bin Misron, PhD

Associate Professor
Faculty of Engineering
Universiti Putra Malaysia
(Internal Examiner)

Mohd Amran bin Mohd Radzi, PhD

Senior Lecturer
Faculty of Engineering
Universiti Putra Malaysia
(Internal Examiner)

Soib Taib, PhD

Associate Professor
Universiti Sains Malaysia
Malaysia
(External Examiner)



NORITAH OMAR, PhD
Associate Professor and Deputy Dean
School of Graduate Studies
Universiti Putra Malaysia

Date: 21 January 2013


This thesis was submitted to the Senate of Universiti Putra Malaysia and has been accepted as fulfillment of the requirement for the degree of Master of Science. The members of the Supervisory Committee were as follows:

Ishak bin Aris, PhD

Professor
Faculty of Engineering
Universiti Putra Malaysia
(Chairman)

Mohammad Lutfi b. Othman, PhD, Ir.

Senior Lecturer
Faculty of Engineering
Universiti Putra Malaysia
(Member)




BUJANG BIN KIM HUAT, PhD

Professor and Dean
School of Graduates Studies
Universiti Putra Malaysia

Date:

DECLARATION

I declare that the thesis is my original work except for quotation and citations which have been duly acknowledged. I also declare that it has not been previously and is not concurrently, submitted for any other degree at Universiti Putra Malaysia or other institutions.



RADIN ZA'IM RADIN UMAR

Date: 25 November 2013



TABLE OF CONTENTS

	Page
ABSTRACT	ii
ABSTRAK	iv
ACKNOWLEDGEMENTS	vi
APPROVAL	vii
DECLARATION	ix
LIST OF TABLES	xiv
LIST OF FIGURES	xvi
LIST OF ABBREVIATIONS	xxii

CHAPTER

1	INTRODUCTION	1
	1.1 Background	1
	1.2 Problem Statement	1
	1.3 Importance of the Study	2
	1.4 Objectives of Research	2
	1.5 Scopes of Research	3
	1.6 Research Contributions	3
	1.7 Thesis Layout	4
2	LITERATURE REVIEW	5
	2.1 Introduction	5
	2.2 General Overview of Wireless Energy Transfer	5
	2.2.1 Tesla Work	5
	2.2.2 Radiative Power Transfer	6
	2.2.3 Capacitive Power Transfer	7
	2.2.4 Inductive Power Transfer	8
	2.3 Wireless Power Transfer via Resonance of Magnetic Induction	10
	2.3.1 Principle of Operation	10
	2.3.2 The Magnetic Resonance	13
	2.4 Identification of Knowledge Gaps based on Published Work in Literature	15
	2.4.1 The Coupled Mode Theory and Impedance Model	15
	2.4.2 Mode of Power Transmission	19
	2.4.3 Optimal Load and Losses due to AC Resistance	21
	2.4.4 Low Efficiency at Long Range Transmission	23
	2.5 Magnetic Field and Mutual Inductance	24
	2.6 Summary of Limitations of Published Work	26
	2.7 Summary	28

3	METHODOLOGY	29
	3.1 Introduction	29
	3.2 Research Process	29
	3.3 The System's Design	31
	3.4 Calculation of Magnetic Field and Mutual Inductance	31
	3.5 Solution for Currents of the System in the Time Domain	38
	3.5.1 Analytical Solution	38
	3.5.2 Numerical Solution	42
	3.5.3 Power, Efficiency, AC Resistance and Self-Inductance of Coil	46
	3.6 Analysis of Equations by MATLAB Programming	47
	3.6.1 Solving the Currents of the System	48
	3.6.2 Obtaining Resonance Frequency of Operation	49
	3.6.3 Obtaining the Optimal Load under variation of Frequency	50
	3.6.4 Maximizing Efficiency and Power Delivery at Variation of Coupling Coefficient and Frequency	51
	3.6.5 Maximizing Efficiency at Extremely Low Coupling Coefficient	52
	3.7 Hardware Implementation	53
	3.7.1 Hardware Design	53
	3.7.2 The Power Electronic Driver	55
	3.8 Summary	59
4	RESULTS AND DISCUSSION	60
	4.1 Introduction	60
	4.2 Magnetic Field of the System	60
	4.3 Measurement of Circuit Components	65
	4.3.1 Measurement of Transmitter Capacitance	65
	4.3.2 Equivalent Series Resistor (ESR) of Capacitor	66
	4.3.3 Self-Inductance of Transmitter Coil	69
	4.3.4 AC Resistance of the Circuit	70
	4.3.5 Receiver's Self-Inductance and Capacitance	71
	4.4 Experimental and Equation-Based Simulation	73
	4.4.1 Measured Waveforms in Time Domain	74
	4.4.2 Adding Real World Component to Equation-Based Simulation in MATLAB Programming	75
	4.4.3 Waveforms of Voltage and Current in the Time Domain	77
	4.4.4 The System under No Load	82
	4.4.5 Addressing the Issues Identified in the Literature Review	85
	4.5 Comparison of Experimental Data to Equation-Based Simulation	86
	4.5.1 The Relationship of Coupling Coefficient to Power Delivery and Efficiency	86
	4.5.2 Distance or Coupling Coefficient?	96

4.5.3 Full Frequency Response of the System under Varying Coupling Coefficient	97
4.5.4 Region of High Efficiency and High Power Delivery for a Given Coupling Coefficient	105
4.5.5 Discussion on Frequency Splitting Due To Coupling Coefficient	105
4.5.6 The Relationship of Output Load to the Power Delivery and Efficiency in Over-Coupled Mode	108
4.5.7 Full Frequency Response of the System under Varying Load	117
4.5.8 Determination of Optimal Load Region in Over-Coupled Mode	123
4.5.9 Discussion on Merging of the Frequency Splitting Due To Variation of Output Load in Over-Coupled Mode	123
4.5.10 Relationship of Output Load to the Power Delivery and Efficiency in Under-Coupled Mode	125
4.5.11 Optimal Load in Under-coupled Mode	134
4.6 Maximizing Efficiency at Extreme Low Coupling Coefficient by Varying the Ratio of Self-Inductance and Series Capacitance	134
4.7 Accuracy of the Numerical Solution	139
4.8 Benchmarking and Comparison with Previous Published Work in Literature	140
4.9 Summary	145
5 CONCLUSIONS AND FUTURE RECOMMENDATIONS	146
5.1 Conclusions	146
5.2 Suggestions for Future Work	146
REFERENCES	148
APPENDICES	
APPENDIX A: MATLAB Programming Code for Calculating Magnetic Field and Mutual Inductance	153
APPENDIX B: Algebraic Expression for Roots of D(s) for Analytical Solution	155
APPENDIX C: MATLAB Programming Code to Solve Current Numerically	165
APPENDIX D: MATLAB Programming Code to Obtain Resonance Frequency	168
APPENDIX E: MATLAB Programming Code to Obtain Load under variation of Frequency	171
APPENDIX G: MATLAB Programming Code to Maximize Efficiency at Extreme Low Coupling Coefficient	177

APPENDIX H	180
IRFZ44E Datasheet	
APPENDIX I	182
Full Schematic of Transmitter Driver	
BIODATA OF STUDENT	183
LIST OF PUBLICATIONS	184



LIST OF TABLES

Table		Page
2.1	Summary of Limitations of Published Work in the Literature	26
3.1	Hardware Design Parameter	54
4.1	Mutual Inductance of Single Turn Loop Centre to Centre Alignment	63
4.2	Calculated Mutual Inductance of 15cm Radius Coil of 15 Turns	65
4.3	Dissipation Factor at 100 kHz and 200 kHz	67
4.4	Equivalent Series Resistance and Dissipation Factor over Frequency	68
4.5	Measured Self-Inductance of Transmitter Coil using LCR Meter	69
4.6	Calculated AC Resistance of Circuit	70
4.7	Comparison of Experimental Data and Equation-Based Simulation for Figure (4.17) to (4.20)	82
4.8	Experimental Transmitter Current under No Load Condition	83
4.9	Experimental data at 10 cm distance and 6.8182 Ω load	87
4.10	Experimental data at separating distance of 15 cm and 6.8182 Ω load	91
4.11	Experimental data at separating distance of 25 cm and 6.8182 Ω of load	94
4.12	Difference between upper f_H and lower f_L optimal frequency in the function of coupling coefficient	101
4.13	Experimental data at 5 cm of coil separation and $R_L = 2.192 \Omega$	109
4.14	Experimental data at 5 cm of coil separation and $R_L = 30.064 \Omega$	112
4.15	Experimental data at 5 cm of coil separation and $R_L = 150.03 \Omega$	115

4.16	Experimental data for 6.8182 Ω at 40 cm coil separation	126
4.17	Experimental data at 14.969 Ω and 40 cm coil separation	129
4.18	Summary of Comparison to Published Work in the Literature	144



LIST OF FIGURES

Figure		Page
2.1	Tesla Wireless Energy Transfer System	6
2.2	Solar Power Satellite	7
2.3	Inductive Power Transfer System	9
2.4	Electric Vehicle Wireless Charging	9
2.5	Roadway Electrification	10
2.6	Magnetic Field Line of Current Conducting Wire	10
2.7	Current Carrying Loop in Close Proximity through a Wall	12
2.8	Equivalent Circuit of Conductor Loop and Capacitor in Series	13
2.9	Capacitor Loaded Loops in Close Proximity	14
2.10	Circuit of Wireless Energy Transfer System in Parallel L-C	17
2.11	Mode of Magnetic Resonance Power Transmission	19
2.12	Frequency Response in Over-coupled Mode	20
2.13	The Skin Effect of Round Conductor	21
2.14	Efficiency in the Function of Distance	23
2.15	Multiple Resonator of Wireless Energy Transfer	24
3.1	Flowchart of Research Process	30
3.2	Block Diagram of the Magnetic Resonance Wireless Energy Transfer System	31

3.3	Finite element of Biot Savart Calculation	32
3.4	Finite Current Element of Circular Conductor Loop	34
3.5	Mesh Elements of the Z-plane of Interest	35
3.6	Flowchart for Calculating Magnetic Field on a Z-plane from a Current Carrying Conductor	36
3.7	Mutual Inductance of between Transmitter and Receiver Coil of Multiple Turn	37
3.8	Equivalent circuit of Magnetic Resonance Wireless Energy Transfer System	38
3.9	Equivalent Un-isolated Circuit	39
3.10	Series Resistor-Inductor RL circuit	42
3.11	Equivalent Circuit with Mutual Inductance as Current Dependent Voltage Source	43
3.12	Flowchart to Solve Currents of the System	48
3.13	Flowchart to Obtain Resonance Frequency	49
3.14	Flowchart to Obtain Optimal Load at Variation of Frequency	50
3.15	Flowchart to Maximize Efficiency and Power under variation of Coupling Coefficient	51
3.16	Flowchart to Maximize Efficiency at Extreme Low Coupling Coefficient	52
3.17	Transmitting and Receiving Coils	53
3.18	Film Polyester Capacitor	53
3.19	Block Diagram of Full-Bridge Inverter- Transmitter Coil Driver	57
3.20	Full-Bridge Inverter-Transmitter Coil Driver with Microcontroller removed and Input Signal Replaced with Function Generator of Square-wave Signal	58
3.21	100Watt Light Bulb Powered Wirelessly at 40cm Distance	58

4.1	Magnetic Field Contour of a Single Turn Coil on Z-Plane 20cm apart	60
4.2	Magnetic Field Surface Plot on Z-Plane 20cm apart	61
4.3	Magnetic Field Enclosed within the Receiver Loop	62
4.4	Magnetic Field Enclosed within a Misaligned Loop	62
4.5	Mutual Inductance of Single Turn Loop	64
4.6	Plot of Mutual Inductance of 15cm Radius Coil of 15 Turns	65
4.7	Capacitance Variation over Frequency	66
4.8	Frequency dependence of dissipation factor $\tan \delta$ for $C=0.10 \mu\text{F}$	67
4.9	AC Resistance over Frequency	71
4.10	Experimental Setup for Data Measurement	73
4.11	Textronix AM503 Current probe and Current Probe Amplifier	73
4.12	MOSFET Gate Drive Voltage Waveform	74
4.13	Output voltage of Full Bridge Current Driver	74
4.14	Current of R-L-C Circuit with Resonant Drive	75
4.15	Equation-based Simulated Input Voltage $V(n)$ with Dead-time	75
4.16	Simulated Input Voltage $V(n)$ with Finite Rise Time and Dead-time	76
4.17	Experimental Transmitter Current and Receiver Current at 15cm Coil Separation With Load:1 ohm in Steady State	78
4.18	Equation based Simulation of Transmitter Current and Receiver Current at 15cm Coil Separation With Load:1 ohm in Steady State	78
4.19	Measurement setup for measuring voltage across receiver coil and capacitor	79

4.20	Experimental Waveform of Capacitor and Coil Voltage in Steady State	79
4.21	Equation-Based Simulation of Capacitor and Coil Voltage in Steady State	80
4.22	Experimental and Equation Based Current under No Load Condition	84
4.23	Experimental Data of Current under No-Load From Zero to Steady State (Current Probe: 0.5A / 10mV)	84
4.24	Equation-based Simulation of Current under No-Load from Zero to Steady State	85
4.25	Output Power versus Frequency at 10cm of Coil Separation	88
4.26	Efficiency at 10cm Separation	88
4.27	Output Power versus Frequency at 15cm of Coil Separation	92
4.28	Efficiency at 15cm of Coil Separation	92
4.29	Output Power versus Frequency at 25cm of Coil Separation	95
4.30	Efficiency at 25cm Coil Separation	95
4.31	Output power of the system at varying frequency and coupling coefficient with load of 6.8182 Ω	98
4.32	Full frequency response at varying frequency and coupling coefficient with load of 6.8182 Ω Top View	99
4.33	Difference between upper f_H and lower f_L optimal frequency in the function of coupling coefficient	102
4.34	Efficiency of the system at carrying coupling coefficient and frequency	103
4.35	Efficiency of the system at carrying coupling coefficient and frequency (top view)	104
4.36	Currents of the system at f_L at Steady State	106
4.37	Current of the system at f_H	107
4.38	Output Power in Over- Coupled Mode with Load: 2.192ohm	110

4.39	Efficiency in Over-Coupled Mode with Load: 2.192 ohm	110
4.40	Output Power in Over-Coupled Mode with Load: 30.064 ohm	113
4.41	Efficiency in Over-Coupled Mode with Load: 30.064 ohm	113
4.42	Output Power in Over-Coupled Mode with Load: 150.03 ohm	116
4.43	Efficiency in Over-Coupled Mode with Load: 150.03 ohm	116
4.44	Output power at varying frequency and varying load in over-coupled mode with $k = 0.255$	118
4.45	Output power at varying frequency and varying load in over-coupled mode with $k = 0.255$ (top view)	119
4.46	Efficiency at varying frequency and varying load in over-coupled mode with $k = 0.255$	121
4.47	Efficiency at varying frequency and varying load in over-coupled mode with $k = 0.255$ (top view)	122
4.48	Transmitter and receiver current at 1Ω	124
4.49	Transmitter and receiver current at 10Ω	124
4.50	Transmitter and receiver current at 20Ω	125
4.51	Output Power in Under-Coupled Mode with Load:6.8182 ohm	127
4.52	Efficiency in Under-Coupled Mode with Load:6.8182 ohm	127
4.53	Output Power in Under-Coupled Mode with Load: 14.969 ohm	130
4.54	Efficiency in Under-Coupled Mode with Load: 14.969 ohm	130
4.55	Efficiency in function of Frequency and Load in under-coupled mode $k=0.0166$	132
4.56	Efficiency in function of Frequency and Load in under-coupled mode $k=0.0166$ Top View	133
4.57	Efficiency at varying $\sqrt{L/C}$ and load (top view)	136
4.58	AC resistance in the function of $\sqrt{L/C}$	137
4.59	Quality factor in the function of $\sqrt{L/C}$	137

4.60	Accuracy of numerical solution	139
4.61	Power as a function of Frequency and Coupling Coefficient from based on Impedance Model	140
4.62	Currents of Repeater in different Transmission Mode	141
4.63	Output Voltage in the Function of Frequency and Distance	141
4.64	Efficiency and Frequency at varying Characteristic Impedance and Air Gap by Impedance Model	142
4.65	Efficiency in the Function of Coil Separation	143
4.66	Quality Factor in the Function of Frequency	143



LIST OF ABBREVIATIONS

A	Area of Overlapping Parallel Capacitor Plate
a	Index of Mesh Element in X-Axis
a_1	Energy Field Amplitude of Transmitting Coil
a_2	Energy Field Amplitude of Receiving Coil
AC	Alternating Current
a_m	Energy Field in Object m
B	Magnetic field Intensity
b	Index of Mesh Element in Y-Axis
C	Capacitance
C_1	Transmitter Series Capacitors
C_2	Receiver Series Capacitor
C_{gs}	MOSFET Gate-Source Capacitance
D	Separation Distance of Coil to Z-Plane
d	Separation of plate
dB	Partial Magnetic Field Intensity
DC	Direct Current
ds	Derivative of Current Source
dx	Finite Mesh Increment in X-Axis
dy	Finite Mesh Increment in Y-Axis
emf	Electromotive Force
EPCOS	Film Capacitor Manufacturer
ESR	Equivalent Series Resistor
f	Frequency
f_1	Natural Frequency of Transmitter Coil and Transmitter Capacitor
f_2	Natural Frequency of Receiver Coil and Transmitter Capacitor
f_3	Natural Frequency of Transmitter Coil and Receiver Capacitor
f_H	Upper Operational Frequency

f_L	Lower Optimal Frequency
F_m	Driving Term
f_{natural}	Natural frequency
HO	Output Voltage of How Side Gate Driver
\hat{i}	Vector in x-axis direction
I	Current
i_1	Current of the Transmitter Circuit in Time Domain
$i_{1 \text{ peak}}$	Peak Transmitter Current
$i_{2 \text{ peak}}$	Peak Receiver Current
i_2	Current of the Receiver Circuit in Time Domain
IC	Integrated Circuit
I_{peak}	Peak Current
$I_{\text{steady state}}$	Steady State Current
\hat{j}	Vector in y-axis direction
\hat{k}	Vector in z-axis direction
k	Coupling Coefficient
k_1	First Residue of Partial Fraction
k_2	Second Residue of Partial Fraction
k_3	Third Residue of Partial Fraction
k_4	Fourth Residue of Partial Fraction
k_n	n-th Residue of Partial Fraction
L	Self-Inductance
l	Length of Conductor
L_1	Self-inductance of Transmitter Coil
L_2	Self-inductance of Receiver Coil
L-C	Inductor-Capacitor
LCR	Inductor-Capacitor-Resistor
LO	Output Voltage of Low Side Gate Driver
M	Mutual Inductance

m	Total number of current element
MATH	Mathematic Function of Oscilloscope
MIT	Massachusetts Institute of Technology
MKP	Metallized Polypropylene Film Capacitor
MFP	Metallized Polypropylene Film Capacitor (similar to MKP)
MKN	Metallized Polyethylene Naphthalate Film Capacitor
MKT	Metallized Polyester Film Capacitor
MFT	Metallized Polyester Film Capacitor(similar to MKT)
MOSFET	Metal Oxide Semiconductor Field Effect Transistor
N	Number of Coil Turns
n	Index of Discrete Point
N_1	Number of Turns of Transmitter Coil
N_2	Number of Turns of Receiver Coil
n_c	Number of Discrete Points in One Period of Oscillation
nF	NanoFarad
P	Power
p	Number of Mesh Element in the X-Axis
P_{loss}	Power Loss
P_{out}	Power Delivery to Load
$P_{radiation}$	Radiation Power
Q	Quality Factor
q	Number of Mesh Element in the Y-Axis
Q_{max}	Maximum Quality Factor
\hat{r}	Unit Vector of Relative Distance to Current element
R	Resistance
r	Distance of point P to current element
r	Radius of Loop
R_1	AC Resistance of Transmitter Circuit
r_1	First Root of Equation D(s)

R_2	AC Resistance Receiver Circuit
r_2	Second Root of Equation D(s)
r_3	Third Root of Equation D(s)
r_4	Fourth Root of Equation D(s)
R_{ac}	AC Resistance
$R_{acQ_{max}}$	AC resistance at Q_{max}
RC	Resistor-Capacitor
R_g	Gate Resistance
$R_{L\text{ optimum}}$	Optimum Output Load
R_L	Output Resistive Load
RLC	Resistor-Inductor-Capacitor
$R_{LQ_{max}}$	Optimal load at Q_{max}
RMS	Root Mean Squared
R_r	Radiation resistance
R_{skin}	Skin Resistance
S_{21}	Power Delivery in S-Parameter
SPWM	Sinusoidal Pulse Width Modulation
T	Period
t	Time
$\tan \delta$	Dissipation Factor
$u(t)$	Step Function
V	Voltage
V_{gs}	MOSFET Gate-Source Voltage
V_{in}	Input Voltage to Full Bridge Inverter
V_{peak}	Peak Voltage
Z	Impedance
Γ	Intrinsic Decay Rate
θ	Angle of Current Element
Φ	Magnetic Flux

α	Constant of Optimized Load
δ	Skin depth
ϵ_0	Permittivity constant
η	Efficiency
η_{21}	Efficiency in S-Parameter
λ	Wavelength of Radiation
μ	Magnetic permeability of material
μ_0	Permeability of Free Space
ρ	Conductivity of material
ω	Angular frequency



CHAPTER 1

INTRODUCTION

1.1 Background

Wireless Energy Transfer is a method of electrical energy transmission from a source to a receiver without the use of any physical connectors (wire or conductor). Nikola Tesla [1] is probably the first to demonstrate the wireless energy transfer via large electrical fields. His idea was not well received to then society as it was perceived to be hazardous [2]. On the other hand, wireless energy transfer through electromagnetic induction has been widely implemented in devices such as the transformer and electrical motor. However, they are subjected to very tight magnetic coupling [3]; hence the distance of wireless energy transfer is limited to small distances. Only recently, wireless energy transfer regained the interest from academics as well as the industry, partly due to the advancement of portable electronics such as tablets, smartphones and laptops.

In 2007, physicists at Massachusetts Institute of Technology (MIT) has demonstrated a high efficiency wireless energy transfer scheme at a relatively large distance; implemented via magnetic induction at resonant frequency. It is consisted of a transmitting coil and a receiving coil connected wirelessly through mutual inductance. The wireless energy transfer is achieved by oscillating current through the pair of coil whose natural frequency are identical to each other. Due to the nature of resonance, energy is transferred at high efficiency. This system demonstrated by the physicist has open up a new concept; such that in the near future, it is possible to truly live in a world without wires.

1.2 Problem Statement

The field of Wireless Energy Transfer via Resonance of Magnetic Induction is a relatively new field. It was first introduced in 2007; as such the physics to explain the behavior of the system is still at its infancy. The physicist at MIT has put forward the Coupled Mode Theory to explain the energy sharing behavior of the system. While this theory is widely accepted, it is more preferred in the physics world and is unfamiliar to electrical engineers [4], [5]. The reason is because; the equation presented introduced variables that do not directly correlate to the variables familiar to electrical engineer. For example, the Coupled Mode Theory only explained the energy of the system, and does not explain how the components variables that the system is consisted of are in relationship to the current and voltages of the system. Therefore, it takes huge amount of time for electrical engineers to study the Coupled Mode Theory, to understand the concept and behavior of the system. Moreover, the Coupled Mode Theory only solves the system in steady state condition and it does not give the behavior of the system in transient time. While the alternative model, the Impedance Analysis Model is more familiar to engineers, it only explains the behavior of the system in the frequency domain, not in the time domain. Thus, analyses of power delivery are often reported in the form of s-parameters and not in watts. Additionally, this model has to assume that voltages and currents are purely sinusoidal, which might not be the case in real world implementation. For example, the time varying real world occurrence (such as dead time and rise time) is not simulate-able in the Impedance Analysis Model. Furthermore, similar to the Coupled Mode Theory, the Impedance Analysis Model only solves the system in steady state condition. Hence, this thesis shall bridge these gaps, by providing a set of equations to solve the system in the time domain from an initial state condition to the steady state condition; by using variables that are familiar to electrical engineers.

1.3 Importance of the Study

Apart from being able to better understand the underlying principle of operation of the system, studying the system's behavior, namely, the equation for current, power and efficiency of the system in the time domain is important because:

- It gives the behavior of the system's currents and voltages; the magnitude, and phase in relation to the time domain.
- It results in more precise simulation in comparison to actual hardware implementation by allowing real world occurrences such as dead time and rise time to be simulated. Moreover, the equation allows the system to be simulated under any type of input voltages defined by the user (as supposed to pure sinusoidal input voltage limited in other equation models).
- It allows the system's behavior to be simulated from an initial condition, transient condition and steady state condition.
- It allows for the optimal condition of the system to be determined based on the systems circuit's components and variables. These variables include:
 - Mutual Inductance (or Coupling Coefficient).
 - Frequency of Operation.
 - Series Tuning Capacitor.
 - Self-Inductance of the Coil.
 - Alternating Current Resistance of the Coil.
 - Output Load Resistance.

By solving the equations of the system under these different variables conditions, the resonance frequency of operation, optimal load condition, and optimal self-inductance to capacitance ratio could be determined. Moreover, since the behavior of the system could be obtained under different mutual inductance (or coupling coefficient) condition, it is possible to obtain the optimal condition under a very large distance of energy transfer (extreme low coupling coefficient), as such that it would maximize the power delivery and efficiency of the energy transfer.

1.4 Objectives of Research

In line with the aforementioned problem statement, the main objective of this research is to provide a set of numerical equations that model and explain the behavior of the system, namely the current of the system in the time domain, by using variables that are more familiar to electrical engineers. To justify the significance of the presented equations, analysis is done on the equation as such it is to achieve the following:

- It should produce an agreement between experimental result and the simulation based on the equations presented.
- Analysis of the equation results in the determination of resonance frequency of operation, and optimal load condition, as such that the system under the optimal condition the system would produce the highest efficiency and power delivery
- Analysis of the equation results in the determination of optimal self-inductance-capacitance ratio, and optimal load as such it maximizes the efficiency for a system under extreme low coupling coefficient, k , where $0 < k < 0.01$.

In order to provide a comparison between the experimental result and the equation-based-simulation, the mutual inductance and the magnetic field around the coils need to be determined. Thus a secondary objective of this research is to provide a set of equations to

calculate the magnetic field around the system's coils and hence calculation of the mutual inductance. This is done by applying the Biot-Savart equation to do finite elements calculations.

1.5 Scopes of Research

The scope of the research is limited to deriving the equation of the current of system in the time domain, using both analytical and numerical method. Then, the analysis of the equations is done by simulating the equations with MATLAB programming. The purpose of the simulation is to obtain the optimal conditions that maximize the efficiency and power delivery of the system. Upon obtaining the result of the analysis, experiment is designed where hardware is constructed. The result obtained from the hardware construction is compared to the result of the equations analysis; this is to justify the validity of the derived equations. Nonetheless, despite the fact that the thesis main contribution is the equation of the current of the system in the time domain, reader would find that most analysis is performed in the frequency domain. This is due to the fact that there is a lack of information in the literature regarding the current of the system in the time domain; in order to perform comparison analysis with the published work in the literature, the author has do the analysis in the frequency domain using the equation derived for the time domain; albeit reader would find that references shall be given in the time domain to explain the findings of the frequency domain results.

Moreover in order to do the comparison, the mutual inductance and magnetic field of the system has to be obtained; as such the equation governing the mutual inductance and magnetic field of the system shall also be derived. This research focuses on explaining the behavior and optimal conditions of the systems; thereby the health issues associated with the wireless energy transfer system shall not be investigated.

1.6 Research Contributions

This thesis claims the following to be its main contribution to the body of knowledge:

1. The equation of the transmitter current and receiver current of the Wireless Energy Transfer via Resonance of Magnetic Induction system in time domain solved using the technique of next discrete point approximation based on the circuit components and the input voltage to the system.

Moreover, the following are claimed to be the secondary contributions (contribution 2-4 are obtained by analysis of contribution 1):

2. A phenomenon unreported in the literature, obtained by analysis of the presented equation in contribution 1; as such that there exist un-symmetrically at high coupling coefficient, as such that the higher resonance frequency, f_H , and the lower resonance frequency, f_L are not centered at the natural frequency of the system, instead as the coupling coefficient increases, the difference of $\Delta f = f_H - f_L$ increases exponentially (as supposed to linear increment)
3. The maximization of efficiency obtained by analysis of the presented equation in contribution 1; as such that efficiency is maximized at the condition of optimal surd of self-inductance to capacitance ratio and the condition of optimal load for the system under extreme low coupling coefficient k , where $0 < k < 0.01$.
4. A phenomenon unreported in the literature, obtained by analysis of the presented equation in contribution 1; as such in contrast to the literature which only reports a

single optimal load condition, it was shown that in over-coupled mode there exist more than one load and frequency conditions that give peak power delivery and efficiency.

5. The equation for magnetic field calculation is obtained by applying the Biot-Savart equation for finite element calculation to determine the mutual inductance and magnetic field around the system's coil. As such the result of the presented equation gives better precision compared to the well-known Grover's Method.

1.7 Thesis Layout

This thesis is structured into 5 chapters. Chapter One introduces the Wireless Energy Transfer via Resonance of Magnetic Induction, outline the problems, the research objectives and contributions. Chapter Two encompasses the review of the literature pertaining to the field of wireless energy transfer, and the objective of this section is to identify the gaps in the literature, hence justifying the relevancy of this thesis. Chapter Three discusses the methodology used to achieve the stated research objective, in such that the derivation of the equation (as in contribution 1) is presented, as well as the derivation of equations for magnetic field calculation, obtained by applying Biot –Savart Equation (as in contribution 5), also presented are the programming flowcharts for analysis of the optimal conditions of the system (as in contribution 2-4). Chapter Four presents the result and discussion in which the result obtained from the equation based simulation is compared to the experimental result, this chapter discusses the research findings and addresses the issues identified in Chapter Two. Finally Chapter Five gives the summary of the findings, and draws the conclusion.

REFERENCES

- [1] N. Tesla, "Apparatus for Transmitting Electrical Energy." U.S. Patent No. 649,621. 15 May 1900.
- [2] A. Marincic, "Nikola Tesla and the Wireless Transmission of Energy," *IEEE Transactions on Power Apparatus and Systems*, vol.PAS-101, no.10, pp.4064,4068, Oct. 1982.
- [3] G. Elliott, J. Boys, and A. Green, "Magnetically coupled systems for power transfer to electric vehicles," *Proceedings of 1995 International Conference on Power Electronics and Drive Systems, 1995.*, pp.797,801 vol.2, 21-24 Feb 1995
- [4] T. Imura, and Y. Hori, "Maximizing Air Gap and Efficiency of Magnetic Resonant Coupling for Wireless Power Transfer Using Equivalent Circuit and Neumann Formula," *IEEE Transactions on Industrial Electronics*, vol.58, no.10, pp.4746,4752, Oct. 2011
- [5] Kiani, M.; Ghovanloo, M., "The Circuit Theory Behind Coupled-Mode Magnetic Resonance-Based Wireless Power Transmission," *Circuits and Systems I: Regular Papers, IEEE Transactions on* , vol.59, no.9, pp.2065,2074, Sept. 2011
- [6] N. Tesla, "System of Transmission of Electrical Energy." U.S. Patent No. 645576. 20 March 1900.
- [7] N. Tesla, "The transmission of electrical energy without wires as a means for furthering peace," *Electrical World and Engineer*, 1905. 7: p. 21
- [8] D. Schneider, "A critical look at wireless power," *IEEE Spectrum*, Retrieved 1 August 2013 from: <http://spectrum.ieee.org/green-tech/mass-transit/a-critical-look-at-wireless-power>," May 2010,
- [9] S. Williams, "Wind and solar aren't viable energy alternatives — and will never be," *The Baltimore Sun*, Retrieved 19 August 2013 from: http://articles.baltimoresun.com/2013-08-05/news/bs-ed-0802-greenhouse-gas-20130805_1_wind-power-solar-and-wind-solar-energy," 5 August 2013
- [10] R. Nansen, "Wireless power transmission: the key to solar power satellites," *IEEE Aerospace and Electronic Systems Magazine*, vol.11, no.1, pp.33,39, Jan 1996.
- [11] F. Steinsiek, K. Weber, W. Foth, H. Foth, and C. Schafer, "Wireless power transmission technology development and demonstrations," *Recent Advances in Space Technologies, 2005. RAST 2005. Proceedings of 2nd International Conference on* , vol., no., pp.140,149, 9-11 June 2005
- [12] J. Joannopoulos, A. Karalis, and M. Soljagic. "Wireless non-radiative energy transfer." U.S. Patent No. 7,741,734. 22 Jun. 2010.
- [13] H. Fnato, Y. Chiku, and K. Harakawa, "Wireless power distribution with capacitive coupling excited by switched mode active negative capacitor," *Electrical Machines and Systems (ICEMS), 2010 International Conference on* , vol., no., pp.117,122, 10-13 Oct. 2010.

- [14] M. Kline, I. Izyumin, B. Boser, and S. Sanders, "Capacitive power transfer for contactless charging," *Applied Power Electronics Conference and Exposition (APEC), 2011 Twenty-Sixth Annual IEEE*, pp.1398,1404, 6-11 March 2011
- [15] G. Rizzoni, and T. Hartley "Principles and applications of electrical engineering," Vol. 3. *McGraw Hill*, 2000.
- [16] C. Wang, G. Covic, and O. Stielau, "Power transfer capability and bifurcation phenomena of loosely coupled inductive power transfer systems," *IEEE Transactions on Industrial Electronics*, vol.51, no.1, pp.148,157, Feb. 2004.
- [17] N. Keeling, G. Covic, and J.Boys, "A Unity-Power-Factor IPT Pickup for High-Power Applications," *IEEE Transactions on Industrial Electronics*, vol.57, no.2, pp.744,751, Feb. 2010
- [18] A. Green, and J. Boys, "10 kHz inductively coupled power transfer-concept and control," *Fifth International Conference on Power Electronics and Variable-Speed Drives, 1994*. pp.694,699, 26-28 Oct 1994.
- [19] H. Wu, A Gilchrist, K. Sealy, P. Israelsen, and J. Muhs, "A review on inductive charging for electric vehicles," *IEEE International Electric Machines & Drives Conference (IEMDC), 2011*, pp.143,147, 15-18 May 2011.
- [20] S. Lee; J. Huh, C. Park, N. Choi, G. Cho, and C. Rim, "On-Line Electric Vehicle using inductive power transfer system," *IEEE Energy Conversion Congress and Exposition (ECCE), 2010*, pp.1598,1601, 12-16 Sept. 2010
- [21] H. Wu, J. Boys, and G. Covic, "An AC Processing Pickup for IPT Systems," *IEEE Transactions on Power Electronics*, vol.25, no.5, pp.1275,1284, May 2010.
- [22] C. Wang, O. Stielau, and G. Covic, "Design considerations for a contactless electric vehicle battery charger," *IEEE Transactions on Industrial Electronics*, vol.52, no.5, pp.1308,1314, Oct. 2005
- [23] S. Raabe, and G. Covic, "Practical Design Considerations for Contactless Power Transfer Quadrature Pick-Ups," *IEEE Transactions on Industrial Electronics*, vol.60, no.1, pp.400,409, Jan. 2013
- [24] M. Budhia, G. Covic, and J. Boys, "Design and Optimization of Circular Magnetic Structures for Lumped Inductive Power Transfer Systems," *IEEE Transactions on Power Electronics*, vol.26, no.11, pp.3096,3108, Nov. 2011
- [25] D. Giancoli, "Physics: principles with applications," *Pearson Education*, 2005.
- [26] Hyper Physics "Magnetic Field of Current Retrieved 1 August 2013 from: <http://hyperphysics.phy-astr.gsu.edu/hbase/magnetic/magcur.html>," 2005
- [27] Witricity, "WiTricity Technology: The Basics Retrieved 1 August 2013 from: <http://www.witricity.com/pages/technology.html>," 2009.
- [28] A. Karalis, J. Joannopoulos, and M. Soljagic, "Efficient wireless non-radiative midrange energy transfer," *Annals of Physics*, vol. 323, pp. 34-48, Jan. 2008

- [29] A. Kurs, A. Karalis, R. Moffatt, J. Joannopoulos, P. Fisher, and M. Soljacic, "Wireless Power Transfer via Strongly Coupled Magnetic Resonances", *Science*, Vol 317, 6 July 2007, pp. 83-86
- [30] J. Wang, S. Ho, W. Fu, and M. Sun, "Finite element analysis and corresponding experiments of resonant energy transmission for wireless transmission devices using witrlicity," *Electromagnetic Field Computation (CEFC), 2010 14th Biennial IEEE Conference on* , vol., no., pp.1,1, 9-12 May 2010
- [31] M. Kiani, U. Jow, and M. Ghovanloo, "Design and Optimization of a 3-Coil Inductive Link for Efficient Wireless Power Transmission," *IEEE Transactions on Biomedical Circuits and Systems*, vol.5, no.6, pp.579,591, Dec. 2011
- [32] Z. Fei, S. Hackwoth, X. Liu, C. Li and M. Sun, "Wireless power delivery for wearable sensors and implants in Body Sensor Networks," *Engineering in Medicine and Biology Society (EMBC), 2010 Annual International Conference of the IEEE* , vol., no., pp.692,695, Aug. 31 2010-Sept. 4 2010
- [33] H. Zhang, Y. Yao, Z. Geng, and Q. Fan, "Physical Pictures and Performance Analysis of Wireless Power Transfer via Evanescent Fields," *Electrical and Control Engineering (ICECE), 2010 International Conference on* , vol., no., pp.3985,3989, 25-27 June 2010
- [34] Z. Fei, S. Hackworth, W. Fu; C. Li, Z. Mao, and M. Sun, "Relay Effect of Wireless Power Transfer Using Strongly Coupled Magnetic Resonances," *IEEE Transactions on Magnetics*, vol.47, no.5, pp.1478,1481, May 2011
- [35] N. Yin, G. Xu, Q. Yang, J. Zhao, X. Yang; J. Jin, W. Fu, and M. Sun, "Analysis of Wireless Energy Transmission for Implantable Device Based on Coupled Magnetic Resonance," *IEEE Transactions on Magnetics*, vol.48, no.2, pp.723,726, Feb. 2012
- [36] C. Chen, T. Chu, C. Lin, and Z. Jou, "A Study of Loosely Coupled Coils for Wireless Power Transfer," *IEEE Transactions on Circuits and Systems II: Express Briefs*, vol.57, no.7, pp.536,540, July 2010
- [37] M. Zargham, and P. Gulak, "Maximum Achievable Efficiency in Near-Field Coupled Power-Transfer Systems," *IEEE Transactions on Biomedical Circuits and Systems*, vol.6, no.3, pp.228,245, June 2012
- [38] S. Cheon, Y. Kim, Kang, S. Youl, M. Lee; J. Lee, and Z. Taehyoung, "Circuit-Model-Based Analysis of a Wireless Energy-Transfer System via Coupled Magnetic Resonances," *IEEE Transactions on Industrial Electronics* , vol.58, no.7, pp.2906,2914, July 2011
- [39] S. Mao, R. Lee, C. Su, and C. Zhu, "Frequency characteristic of resonance- based wireless energy transfer," *Electromagnetic Launch Technology (EML), 2012 16th International Symposium on* , vol., no., pp.1,6, 15-19 May 2012.
- [40] A. Sample, A. Meyer, and J. Smith, "Analysis, Experimental Results, and Range Adaptation of Magnetically Coupled Resonators for Wireless Power Transfer," *IEEE Transactions on Industrial Electronics*, vol.58, no.2, pp.544,554, Feb. 2011

- [41] D. Ahn, and S. Hong, "Effect of Coupling Between Multiple Transmitters or Multiple Receivers on Wireless Power Transfer," *IEEE Transactions on Industrial Electronics* vol.60, no.7, pp.2602,2613, July 2013
- [42] J. Moshfegh, M. Shahabadi, and M. Rashed-Mohassel, "Conditions of maximum efficiency for wireless power transfer between two helical wires," *Microwaves, Antennas & Propagation, IET*, vol.5, no.5, pp.545,550, April 2011
- [43] J. Wang, J. Li; S. Ho, W. Fu, Y. Li; H. Yu; and M. Sun, "Lateral and Angular Misalignments Analysis of a New PCB Circular Spiral Resonant Wireless Charger," *IEEE Transactions on Magnetics*, vol.48, no.11, pp.4522,4525, Nov. 2012
- [44] D. Ahn, and S. Hong, "A Study on Magnetic Field Repeater in Wireless Power Transfer," *IEEE Transactions on Industrial Electronics*, vol.60, no.1, pp.360,371, Jan. 2013
- [45] B. Cannon, J. Hoburg, D. Stancil, and S. Goldstein, "Magnetic Resonant Coupling As a Potential Means for Wireless Power Transfer to Multiple Small Receivers," *IEEE Transactions on Power Electronics*, vol.24, no.7, pp.1819,1825, July 2009
- [46] C. Yu, R. Lu, Y. Mao, L. Ren, and C. Zhu, "Research on the model of magnetic-resonance based wireless energy transfer system," *Vehicle Power and Propulsion Conference, 2009. VPPC '09. IEEE*, vol., no., pp.414,418, 7-10 Sept. 2009
- [47] T. Imura, H. Okabe, and Y. Hori, "Basic experimental study on helical antennas of wireless power transfer for Electric Vehicles by using magnetic resonant couplings," *Vehicle Power and Propulsion Conference, 2009. VPPC '09. IEEE*, vol., no., pp.936,940, 7-10 Sept. 2009
- [48] All About Circuits, "More on Skin Effect Retrieved 1 August 2013 from http://www.allaboutcircuits.com/vol_2/chpt_3/6.html," 2003
- [49] Z. Popović, "Introductory electromagnetics," *Prentice Hall*, 2000
- [50] C. Balanis, "Antenna theory: analysis and design," *John Wiley & Sons*, 2012
- [51] Q. Yuan, Q. Chen, L. Li, and K. Sawaya, "Numerical Analysis on Transmission Efficiency of Evanescent Resonant Coupling Wireless Power Transfer System," *IEEE Transactions on Antennas and Propagation*, vol.58, no.5, pp.1751,1758, May 2010
- [52] C. Lee, W. Zhong, and S. Hui, "Effects of Magnetic Coupling of Nonadjacent Resonators on Wireless Power Domino-Resonator Systems," *IEEE Transactions on Power Electronic*, vol.27, no.4, pp.1905,1916, April 2012
- [53] T. Imura, and Y. Hori, "Optimization using transmitting circuit of multiple receiving antennas for wireless power transfer via magnetic resonance coupling," *Telecommunications Energy Conference (INTELEC), 2011 IEEE 33rd International*, vol., no., pp.1,4, 9-13 Oct. 2011

- [54] D. Niculae, M. Iordache, and L. Dumitriu, "Magnetic coupling analysis in wireless transfer energy," *7th International Symposium on Advanced Topics in Electrical Engineering (ATEE), 2011*, vol., no., pp.1,4, 12-14 May 2011
- [55] F. Grover, "Inductance Calculations," *Dover Publication* 2009
- [56] S. Karris, "Circuit Analysis II with Matlab Application," *Orchard Publications* 2003
- [57] W. Weisstein, "Quartic Equation Retrieved 1 August 2013 from: <http://mathworld.wolfram.com/QuarticEquation.html>," 1999
- [58] H. Wheeler, "Simple Inductance Formulas for Radio Coils," *Proceedings of the Institute of Radio Engineers*, vol.16, no.10, pp.1398,1400, Oct. 1928
- [59] EPCOS, "Film Capacitor General Technical Information," EPCOS Film Capacitor Datasheet, May 2009.
- [60] EPCOS, "Metallized Polypropylene Film Capacitors MKP," EPCOS Film Capacitor Datasheet, August 2004.
- [61] Z. Chao, G. Liu, X. Xu; Z. Xia and X. Hui, "Experimental Analysis on Wireless Energy Transfer System Based on Resonant Coupling," *Electromagnetic Field Problems and Applications (ICEF), 2012 Sixth International Conference on*, vol., no., pp.1,3, 19-21 June 2012.