



UNIVERSITI PUTRA MALAYSIA

**CHANNEL MODELING AND DIRECTION-OF-ARRIVAL ESTIMATION
IN MOBILE MULTIPLE-ANTENNA COMMUNICATION SYSTEMS**

ARASTOO ROSTAMI RAVARI.

FK 2005 2

**CHANNEL MODELING AND DIRECTION-OF-ARRIVAL ESTIMATION
IN MOBILE MULTIPLE-ANTENNA COMMUNICATION SYSTEMS**

By

ARASTOO ROSTAMI RAVARI

**Thesis Submitted to the School of Graduate Studies, Universiti Putra Malaysia,
in Fulfilment of the Requirement for the Degree of Doctor of Philosophy**

January 2006



DEDICATION

This Thesis is dedicated to

All I Love

Specially

My Mother's Sprite

and

My Father, Wife, Daughter and Son

and

My supervisor Professor Dr. Borhanuddin Mohd. Ali

for

his guidance, advice and endless supports



Abstract of thesis presented to the Senate of Universiti Putra Malaysia in fulfilment
of the requirement for the degree of Doctor of Philosophy

**CHANNEL MODELING AND DIRECTION-OF-ARRIVAL ESTIMATION
IN MOBILE MULTIPLE ANTENNA COMMUNICATION SYSTEMS**

By

ARASTOO ROSTAMI RAVARI

January 2006

Chairman: Professor Borhanuddin Bin Mohd. Ali, PhD

Faculty: Engineering

Antennas that are able to adaptively direct the transmitted (and received) energy are of great interest in future wireless communication systems. The directivity implies reduced transmit power and interference, and also a potential for increased capacity. This thesis treats some modeling and estimation problems in mobile communication systems that employ multiple antennas, primarily at the base stations. With multiple antennas at the receive side, the spatial dimension is added, and processing is performed in both the temporal and spatial domains. The potential benefits are increased range, fading diversity and spatially selective transmission. Specifically, the problems dealt in this thesis are mainly related to the uplink transmission from mobile to the base station. Two main topics are studied, channel modeling and estimation of channel parameters.

This thesis first describes the modeling of the reflected power distribution due to the scatterers close to the mobile stations, in terms of the received signal azimuth at the base station with multiple-antenna. As a more realistic channel modeling, a



multipath fading deterministic channel model is proposed to generate properly correlated faded waveforms with appropriate power distribution through azimuth spread of received signal. The purpose of the proposed channel model is to model fading received signal waveforms with Laplacian distribution of power through received signal azimuth spread.

This thesis is divided into two parts; in the first part multipath fading by local scattering are used to derive a channel model including the spatial dimension for non frequency-selective fading. This means that the mobile is not modeled as a point source but as a cluster of a large number of independent scatterers with small time delay spread to take into account angular spreading of the signal. Properly correlated fading waveforms are obtained by taking into account the angular spread of the scattered signals from a particular distribution of scatterers. By appropriate scaling of the array response vector (ARV) based on non-equal locations for various received signal components as a function of distance from the transmitter, the reflected power from a given scatterer is no longer constant but varies as a function of the distance from the transmitter. Our proposed channel model is able to produce fading signal waveform which agrees with the results of reflected angular power dispersions measured in the field, e.g. Laplacian distribution of power in azimuth. It is also shown that the channel response can be modeled as a complex Gaussian vector.

Although the channel will be frequency selective in the case of multipath propagation with considerable time spread, this can be modeled as having more than

one cluster of scatterers. By employing Walsh-Hadamard codewords an extension to

wideband multipath fading model is achieved.

It is shown that the statistical properties of proposed model such as signal waveform's correlation, autocorrelation and crosscorrelation between generated paths, are in good agreement with the theory in space and time domain. The model can be applied to evaluate smart antenna systems and beamforming algorithms in the uplink by generating uncorrelated multipaths Rayleigh fading waveforms with certain spatio-temporal correlation and spatial coordinates relative to base stations to simulate received signals from mobiles and interferers. Bit-error-rate (BER) performance analysis of uniform linear array antenna (ULA) based on correlation matrix is also presented as an application of our proposed model for multiple-antenna evaluations. Our simulated results show 5% improvement than other published related works.

One problem when modeling frequency selective fading is that each cluster has to be assigned spatial parameters. Since the joint spatial and temporal characteristics are unknown, non-parametric channel estimation approaches are required in this case in order to estimate the channel parameter, which is the subject of the second part.

The second part of the thesis deals with channel parameter estimation of distributed scattering sources. Because of local scattering around the transmitter the signal waveforms appears spatially distributed at the receiver. The characterization of the spatial channel, in particular mean direction of arrival and spatial spread, is of prime interest for system optimization and performance prediction. Low-complexity

spectral-based estimators are used for the estimation of direction and spatial spread of the distributed source by employing the proposed channel model for simulation. Estimated parameters from recent measurements ([PMF00]) are compared with estimated parameters from model generated waveforms as well as theoretical distribution of received signal's angular spread. Good agreement between them is observed which shows the correctness of our proposed channel model for simulating spatio-temporally correlated received signal at an antenna array. The estimated parameter error improved by 5% over the other published related works.

Abstrak tesis yang dikemukakan kepada Senat Universiti Putra Malaysia
sebagai memenuhi keperluan untuk ijazah Doktor Falsafah

**PEMODELAN SALURAN DAN PENGANGGARAN ARAH KETIBAAN
DALAM SISTEM KOMUNIKASI BERGERAK ANTENA BERBILANG**

Oleh

ARASTOO ROSTAMI RAVARI

Januari 2005

Pengerusi: Profesor Borhanuddin Bin Mohd Ali, PhD

Fakulti: Kejuruteraan

Antena yang mampu untuk menghala tenaga dihantar (dan diterima) secara mudahsuai adalah merupakan tarikan besar pada sistem komunikasi wayerles akan datang. Penghalaan menandakan kuasa penghantaran dan gangguan yang lebih kecil, dan potensi untuk penambahan kapasiti. Tesis ini mengolahkan beberapa masalah pemodelan dan penganggaran dalam sistem komunikasi bergerak yang menggunakan antena berbilang, terutamanya di stesyen tapak. Dengan antena berbilang pada bahagian penerimaan, dimensi ruangan adalah ditambahkan, dan pemerosesan dibuat dalam kedua dua domain masa dan ruangan. Potensi manfaat adalah peningkatan julat, kepelbagaian pemudaran, dan penghantaran pilihan ruangan. Secara khususnya, masalah yang diolahkan di dalam tesis ini adalah terutamanya berkaitan dengan penghantaran ke atas dari stesyen bergerak ke stesyen tapak. Dua topik utama adalah dikaji, pemodelan saluran dan penganggaran parameter saluran.

Tesis ini mula mulannya memerihalkan pemodelan kepada taburan kuasa terpantul disebabkan oleh penyelerak berhampiran dengan stesyen bergerak, dalam bentuk azimuth isyarat yang diterima di stesyen tapak dengan antenna berbilang. Untuk pemodelan saluran yang lebih realistik, suatu model saluran pudaran deterministik adalah dicadangkan untuk menjanakan bentukgelombang pudar yang benar benar berhubungkait dengan taburan kuasa bersesuaian melalui penyebaran azimuth isyarat yang diterima.

Tesis ini dibahagikan kepada dua bahagian; dalam bahagian pertama pemudaran laluan berbilang oleh penyelerakan lokal adalah digunakan untuk menerbitkan suatu model saluran temasuk dimensi ruangan untuk pemudaran frekuensi-pilihan. Ini bermaksud bahawa stesyen mobil ini tidak dimodelkan sebagai sumber titik tetapi sebagai suatu gugusan kepada suatu bilangan penyelerak bebas yang banyak, dengan penyebaran lengah yang kecil untuk mengambil kira penyebaran sudut isyarat tersebut. Gelombang pemudaran berhubungkait sempurna adalah diterima dengan mengambil kira penyebaran sudut isyarat terselerak dari suatu taburan penyelerak tertentu. Dengan penskalaan vektor sambutan tatasusunan (ARV) yang sesuai berdasarkan kepada lokasi tak sama beberapa komponen isyarat yang diterima sebagai fungsi kepada jarak dari pemancar, kuasa terpantul dari suatu penyelerak adalah tidak lagi malar malah berubah sebagai fungsi kepada jarak dari pemancar. Model saluran cadangan kami ini mampu untuk mengeluarkan gelombang isyarat pudaran yang bersetuju dengan hasil keputusan penyebaran kuasa sudut pantulan yang diukur di medan, cth, taburan Laplacian kuasa pada azimuth. Adalah ditunjukkan juga bahawa sambutan saluran boleh dimodelkan sebagai vektor Gaussian kompleks.

Walaupun saluran ini akan menjadi frekuensi pilihan dalam kes perambatan berbilang laluan dengan penyebaran masa yang banyak, ia boleh dimodelkan sebagai mempunyai lebih dari satu gugusan penyelerak. Dengan menggunakan kod perkataan Walsh-Hadamard satu tambahan model pudaran berbilang jalurluas adalah dicapai.

Adalah ditunjukkan bahawa sifat model yang dicadangkan seperti hubungkait gelombang isyarat, hubungkait sendiri, dan hubungkait bersilang di antara laluan yang dijanakan, adalah bersetuju dengan baik dengan teori domain ruangan dan masa. Model ini boleh diaplikasikan untuk menilaikan sistem antena pintar dan algoritma pembentukalur pada pautan ke atas dengan menjanakan gelombang pudaran Rayleigh berbilanglaluan dengan suatu hubungkait ruangan-masa dan koordinat ruangan relatif kepada stesyen tapak untuk menyimulasi isyarat terimaan dari stesyen bergerak dan pengganggu.

Satu masalah apabila memodelkan pemudaran frekuensi pilihan adalah setiap gugusan hendaklan diberikan parameter ruangan. Oleh kerana ciri ruangan dan masa bersama adalah tidak diketahui, pendekatan penganggaran saluran tak parametrik adalah diperlukan dalam kes ini untuk menganggarkan parameter saluran, ia itu tajuk bahagian kedua ini.

Bahagian kedua tesis ini membincangkan penganggaran parameter saluran kepada sumber penyelerak tertabur. Oleh kerana penyelerakan lokal sekitar pemancar, gelombang isyarat nampak tertabur secara ruangan pada penerima. Pencirian

saluran ruangan, terutamanya arah ketibaan min dan penyebaran ruangan, adalah menjadi minat utama untuk pengoptimuman sistem dan ramalan prestasi. Penganggar berasaskan spektrum yang tak berapa rumit adalah digunakan untuk penganggar arah dan penyebaran ruangan sumber tertabur dengan menggunakan model saluran yang dicadangkan untuk simulasi. Parameter anggaran dari pengukuran terkini adalah dibandingkan dengan parameter anggaran dari gelombang janaan model dan juga taburan teoretikal penyebaran sudut isyarat terimaan. Persetujuan yang baik di antara mereka adalah diperhatikan yang menunjukkan ketepatan model saluran cadangan kami untuk mensimulasiisyarat terimaan berhubungkait secara ruang-masa pada tatasusuan antena. Ralat parameter anggaran menjadi 5% lebih baik dari hasilkerja lain yang berkaitan yang telah diterbitkan.

ACKNOWLEDGEMENTS

Praise to God the Almighty, for his help and support during the Life's course and truth's moments.

I would like to extend my gratitude to the members of my supervisory committee; Prof. Dr. Borhanuddin Bin Mohd Ali, for his advice, kind and constant support, encouragement and help in all my difficulties, and for his supervision that never ends.

I wish to express my deepest thankfulness to my co-supervisors; Prof. Dr Sudhanshu Shekhar Jamuar, Prof. Dr Mohammad Umar Siddiqi, for their constructive guidance through out my study period.

I am also grateful to the Department of Computer and Communication Systems Engineering help to laboratories work.

I would like to thank my wife, daughter and son, that patiently support my away from home.

Last, I would like to thank too many others, who help me during my study.

TABLE OF CONTENTS

	Page
DEDICATION	ii
ABSTRACT	iii
ABSTRAK	vii
ACKNOWLEDGEMENTS	xi
APPROVAL	xii
DECLARATION	xiv
LIST OF TABLES	xviii
LIST OF FIGURES	xix
LIST OF ABBREVIATIONS	xxiv
LIST OF SYMBOLS	xxvi
 CHAPTER	
 1 INTRODUCTION	1
1.1 Multiple-Antenna in Cellular Communications	1
1.2 Motivation and Problem Statement	4
1.3 Aim and Objectives	8
1.4 Contributions of the Thesis	9
1.5 Organization of Thesis	9
 2 REVIEW OF CHANNEL MODELS, SPATIAL CORRELATION AND CHANNEL PARAMETER ESTIMATION	13
2.1 Propagation Models	16
2.1.1 Unstructured Models	17
2.1.1.1 The Additive Noise Channel	17
2.1.1.2 The Linear Filter Channel	18
2.1.1.3 The Linear Time-Variant Channel	19
2.1.2 Structured Models	20
2.1.3 Point Source Models	21
2.1.3.1 Complex Signal Representation	22
2.1.3.2 Small Time Delay	23
2.1.3.3 Electromagnetic Wave Propagation	25
2.1.3.4 The Narrowband Assumption	27
2.1.3.5 The Uniform Linear Array	28
2.1.3.6 Flat Rayleigh Fading and Antenna Array	29
2.1.3.7 Flat and Frequency Selective Fading	30
2.1.3.8 Flat Rayleigh Fading	31
2.1.3.9 Rice and Nakagami Models	34

2.1.3.10	The Received Signal to Antenna Array	36
2.1.4	Distributed Source Models	42
2.1.4.1	Flat Fast Fading and Adding the Spatial Dimension	43
2.1.4.2	Local Scatterers	44
2.1.4.3	The Vector Channel Response	46
2.1.4.4	Generalized Flat Rayleigh Fading for ULA	50
2.1.5	Arbitrary Sources and Multipath Propagation	58
2.1.5.1	Frequency Selective Fading	59
2.1.5.2	A General Distributed Source Model	60
2.1.5.3	Spatial Frequency Model	63
2.2	Channel Parameter Estimation	66
2.2.1	Sensor Array Processing	68
2.2.2	Beamforming	69
2.3	Summary and Discussion	73
3	SPACE-TIME CORRELATED MUTIPATH FADING CHANNEL MODEL	75
3.1	Deterministic Modeling and Second order statistics	75
3.2	Extended Lee's Model for Antenna Array	79
3.3	Analytical Correlation	86
3.4	Received Signal at Antenna Array	89
3.4.1	Scattering Clusters	91
3.4.2	Received Signal Waveform at Antenna Array with Laplacian PAS	93
3.5	Wideband Signal Waveform	95
3.6	BER Performance Analysis	98
3.7	Summary and Discussion	100
4	METHODOLOGY OF NUMERICAL STUDY AND RESULT	102
4.1	Second-order Statistics' Numerical Results	102
4.1.1	Channel Model Verification According to Spatial Correlation	103
4.1.2	Effect of Nominal AOA on Spatial Correlation	112
4.1.3	Effect of Transmitter's Direction of Motion on Spatial Correlation	117
4.1.4	Effect of Carrier Frequency on Spatial Correlation	119
4.1.5	Autocorrelation	120
4.1.6	Cross-Correlation	121
4.2	Comparison with Jakes Fading Model Incorporating Azimuth Spread	122
4.3	BER Performance	124
4.4	Discussion	127

5	DIRECTION OF ARRIVAL ESTIMATION AND NUMERICAL RESULTS	130
5.1	Parameter Estimation	130
5.1.1	Classical Beamforming	131
5.1.1.1	Conventional Beamformer (CBF)	131
5.1.1.2	Capon's Beamformer	133
5.1.1.3	Modified Capon's Spectrum	136
5.1.2	Spectral-based Parameter Estimation	138
5.2	High-Resolution Methods	144
5.2.1	Multiple Signal Classification (MUSIC)	145
5.2.2	Dispersed Signal Parametric Estimation (DISPARE)	145
5.2.3	Weighted Pseudo-Subspace Fitting (WPSF)	148
5.3	Numerical Results	149
5.4	Discussion	157
6	CONCLUSION AND FUTURE DIRECTIONS	159
6.1	Conclusion	159
6.2	Future Directions	162
REFERENCES		164
BIODATA OF THE AUTHOR		171
PUBLICATIONS		172

LIST OF TABLES

Table		Page
5.1	Eigenvalues of the true and noise-free covariance matrix of a uniformly distributed source for different spreads and an eight-element ULA	146
5.2	Eigenvalues of the true and noise-free covariance matrix of a Gaussian distributed source for different spreads and an eight-element ULA	147

LIST OF FIGURES

Figure	Page
1.1 The structure of thesis	12
2.1 Additive noise channel	18
2.2 Linear filter channel	19
2.3 Linear time-variant filter channel	19
2.4 The incident wave is approximately plane at the receiving array	28
2.5 Comparisons of PDFs of Rice and Nakagami- m . $\Omega=1$ and $m=1,\dots,5$	36
2.6 Multipath propagation leads to a spatially distributed signal with nominal arrival direction and angular spread $\{\theta_0, \sigma_\theta\}$	43
2.7 The model with local scatterers	45
2.8 The circle model places the scatterers uniformly on a circle	52
2.9 The magnitude of the correlation $\rho(x)$ using a Gaussian scatterer distribution with $\sigma_\theta = 3^\circ$ and different $\theta_0 = 30^\circ, 60^\circ, 90^\circ$	54
2.10 The magnitude of the correlation $\rho(x)$ using a Gaussian scatterer distribution with $\theta_0 = 90^\circ$ and different cluster spreads $\sigma_\theta = 0^\circ, 5^\circ, 10^\circ$	55
2.11 The magnitude and argument of the correlation $\rho(x)$ using the three different scatterer distributions. $N = 101$, $\theta_0 = 45^\circ$, $\sigma_\theta = 3^\circ$ and $\theta_{BW} = 6^\circ$	56
2.12 The magnitude of $\rho(x)$ using the three different scatterer distributions. $N = 101$, $\theta_0 = 90^\circ$, $\sigma_\theta = 6^\circ$ and $\theta_{BW} = 12^\circ$	57
2.13 The magnitude of the correlation using the three different scatterer distributions. $N = 101$, $\theta_0 = 90^\circ$ different cluster widths $\sigma_\theta = 10^\circ$ and $\theta_{BW} = 20^\circ$	57
2.14 Smart antenna system	67

2.15 Beamformer	69
3.1 Received signal to the mobile with angle η_i which is moving in direction ζ	82
3.2 Scattered received signal path to the BS	85
3.3 Power Azimuth Spread (PAS)	89
3.4 P scattereres on each radial line	92
3.5 Structure of simulator with $2N$ oscillators to generate N uncorrelated set of multipath waveforms	97
4.1 Correlation as a function of antenna separation with different values of N , number of scatterers that are placed on vertices of polygon, $q_p = 0$, $q_r = 0.5$, $d_0 = 50$ m, $d_r = 500$ m, $\tilde{\theta}_{\max} = 5.7^\circ$	104
4.2 Correlation as a function of antenna separation when $N=64$ scatterers are placed on vertices of polygon, $P=1$, $q_p = 0$, $q_r = 0.5$, with $\tilde{\theta}_{\max} = 5.7^\circ$ according to corresponded values of d_r & d_0	105
4.3 Correlation as a function of antenna separation when $N=64$ scatterers are placed on vertices of polygon, $P=1$, $q_p = 0$, $q_r = 0.5$, various values of $\tilde{\theta}_{\max} = 0.7^\circ, 1.4^\circ, 2.8^\circ, 5.7^\circ$ correspond to $d_0 = 50$ m & $d_r = 4000, 2000, 1000, 500$ m	106
4.4 Correlation as a function of antenna separation when $N=64$ scatterers are placed on vertices of polygon, $P=20$ on each radial line, $q_p = 0$, $q_r = 0.5$, $d_0 = 50$ m with $\tilde{\theta}_{\max} = 1.4^\circ, 2.8^\circ, 5.7^\circ$ corresponding to $d_r = 2000, 1000, 500$ m	107
4.5 Correlation as a function of antenna separation when $N=64$, $P=20$, $q_p = 0$, $q_r = 0.5$, $d_0 = 50$ m, $d_r = 500$ m ($\tilde{\theta}_{\max} = 5.7^\circ$) and various values of nominal angle of arrival, $\theta_0 = 0^\circ, 45^\circ, 90^\circ$	108
4.6 Correlation as a function of antenna separation when $N=64$ scatterers are placed on vertices of polygon, $P=1$ and 20 scatterers on each radial line, $q_p = 0$, $q_r = 0.5$, $\tilde{\theta}_{\max} = 5.7^\circ$	109
4.7 Correlation function with various values of q_p and q_r , $N=64$, $P=20$, $\sigma_\theta = 3.5^\circ$ corresponing to $d_0 = 115$ m & $d_r = 500$, m $\tilde{\theta}_{\max} = 3.8\sigma_\theta$	111

4.8 Correlation function with various values of q_p and q_r , $N=64$, $P=20$, $\sigma_\theta = 6.5^\circ$ corresponding to $d_0=208.9$ m & $d_r=500$ m, $\tilde{\theta}_{\max} = 3.8\sigma_\theta$	111
4.9 Spatial correlation as a function of antenna separation when $N=64$, $P=20$, $\sigma_\theta = 3.5^\circ$, 6.5° , $q_r = 0.7$, $q_p = 1.7$	112
4.10 Spatial correlation as a function of antenna separation when $N=64$, $P=20$, $\sigma_\theta = 3.5^\circ$, $d_0=115$ m, $d_r = 500$ m, $\theta_0 = 0^\circ, 45^\circ, 90^\circ$, $q_r = 0.7$, $q_p = 1.7$	113
4.11 Spatial correlation as a function of antenna separation when $N=64$, $P=20$, $\sigma_\theta = 3.5^\circ$, $d_r = 1000$ m, $\theta_0 = 0^\circ, 45^\circ, 90^\circ$, $q_r = 0.7$, $q_p = 1.7$	114
4.12 Spatial correlation as a function of antenna separation when $N=64$, $P=20$, $\sigma_\theta = 3.5^\circ$, $d_r = 2000$ m, $\theta_0 = 0^\circ, 45^\circ, 90^\circ$, $q_r = 0.7$, $q_p = 1.7$	114
4.13 Spatial correlation as a function of antenna separation when $N=64$, $P=20$, $\sigma_\theta = 3.5^\circ$, $d_r = 4000$ m, $\theta_0 = 0^\circ, 45^\circ, 90^\circ$, $q_r = 0.7$, $q_p = 1.7$	115
4.14 Spatial correlation as a function of antenna separation when $N=64$, $P=20$, $\sigma_\theta = 6.5^\circ$, $d_0=208.9$ m, $d_r = 500$ m, $\theta_0 = 0^\circ, 45^\circ, 90^\circ$, $q_r = 0.7$, $q_p = 1.7$	115
4.15 Spatial correlation as a function of antenna separation when $N=64$, $P=20$, $\sigma_\theta = 6.5^\circ$, $d_r = 1000$ m, $\theta = 0^\circ, 45^\circ, 90^\circ$, $q_r = 0.7$, $q_p = 1.7$	116
4.16: Spatial correlation as a function of antenna separation when $N=64$, $P=20$, $\sigma_\theta = 6.5^\circ$, $d_r = 2000$ m, $\theta_0 = 0^\circ, 45^\circ, 90^\circ$, $q_r = 0.7$, $q_p = 1.7$	116
4.17 Spatial correlation as a function of antenna separation when $N=64$, $P=20$, $\sigma_\theta = 6.5^\circ$, $d_r = 4000$ m, $\theta_0 = 0^\circ, 45^\circ, 90^\circ$, $q_r = 0.7$, $q_p = 1.7$	117
4.18 Correlation versus antenna separation when $N=64$, $P=20$, $q_p = 1.7$, $q_r = 0.7$, $\sigma_\theta = 3.5^\circ$ ($d_0=115$ m & $d_r=500$ m), for various values of ζ (the angle between the direction of the mobile transmitter motion and LOS)	118
4.19 Correlation versus antenna separation when $N=64$, $P=20$, $q_p = 1.7$, $q_r = 0.7$, $\sigma_\theta = 6.5^\circ$ ($d_0=208.9$ m & $d_r=500$ m), for various values of ζ (the angle between the direction of the mobile transmitter motion and LOS)	118

4.20 Correlation versus antenna separation with $N=64$, $P=20$, $q_p = 1.7$, $q_r = 0.7$, $\sigma_\theta = 3.5^\circ$ ($d_0 = 115$ m & $d_r = 500$ m), $\zeta = 0^\circ$, $f_c = 1.2$, 1.8 GHz	119
4.21 Correlation versus antenna separation with $N=64$, $P=20$, $q_p = 1.7$, $q_r = 0.7$, $\sigma_\theta = 6.5^\circ$ ($d_0 = 115$ m & $d_r = 500$ m), $\zeta = 0^\circ$, $f_c = 1.2$, 1.8 GHz	120
4.22 Temporal autocorrelation when $N=64, 128$	121
4.23 Cross-correlation between 1st and 2nd path, $N=64, 128$	122
4.24 Comparison of simulated waveforms correlation's generated by Jakes fading model and our proposed model. $N=64$, $P=20$, $q_p = 0$, $q_r = 0.5$, $d_0 = 50$ m with $\tilde{\theta}_{\max} = 1.4^\circ, 5.7^\circ$ corresponding to $d_r =$ 2000, 500 m in both models	124
4.25 BER performance flowchart	125
4.26 BER performance of ULA with Laplacian energy distribution, $\sigma_\theta = 3.5^\circ, 6.5^\circ$ as a function of SNR (γ_c)	126
4.27 BER performance of ULA as a function of β (nominal direction of arrival with respect to array's axis) for different angular spreads	127
5.1 RMSE of $\hat{\theta}_0$ for different SNRs. An antenna array with $M = 16$ elements (sensors), $N=64$ scatterers, Gaussian azimuth spread ($\tilde{\theta}$) with parameters $\theta_0 = 0^\circ$, $\sigma_\theta = 5^\circ$ (i.e. $p(\theta; \theta_0, \sigma_\theta)$ is the Gaussian PDF $\mathcal{N}(\theta_0, \sigma_\theta^2)$)	152
5.2 RMSE of $\hat{\sigma}_\theta$ for different SNRs. An antenna array with $M = 16$ elements (sensors), $N=64$ scatterers, Gaussian azimuth spread ($\tilde{\theta}$) with parameters $\theta_0 = 0^\circ$, $\sigma_\theta = 5^\circ$ (i.e. $p(\theta; \theta_0, \sigma_\theta)$ is the Gaussian PDF $\mathcal{N}(\theta_0, \sigma_\theta^2)$)	153
5.3 RMSE of $\hat{\theta}_0$ for different spreads . An antenna array with $M = 16$ elements (sensors), $N=64$ scatterers, Gaussian azimuth spread ($\tilde{\theta}$) with parameter $\theta_0 = 0^\circ$, 10 dB SNR	154
5.4 RMSE of $\hat{\sigma}_\theta$ for different spreads . An antenna array with $M = 16$ elements (sensors), $N=64$ scatterers, Gaussian azimuth spread ($\tilde{\theta}$) with parameter $\theta_0 = 0^\circ$, 10 dB SNR	154

- 5.5 RMSE of $\hat{\theta}_0$ for different number of antennas array elements (sensors) M . Gaussian azimuth spread ($\tilde{\theta}$) with parameters $\theta_0 = 0^\circ$, $\sigma_\theta = 5^\circ$ (i.e. $p(\theta; \theta_0, \sigma_\theta)$ is the Gaussian PDF $\mathcal{N}(\theta_0, \sigma_\theta^2)$), $N=64$ scatterers, 10 dB SNR 155
- 5.6 RMSE of $\hat{\sigma}_\theta$ for different number of antennas array elements (sensors) M . Gaussian azimuth spread ($\tilde{\theta}$) with parameters $\theta_0 = 0^\circ$, $\sigma_\theta = 5^\circ$ (i.e. $p(\theta; \theta_0, \sigma_\theta)$ is the Gaussian PDF $\mathcal{N}(\theta_0, \sigma_\theta^2)$), $N=64$ scatterers, 10 dB SNR 156
- 5.7 Estimated PDFs. Gaussian spread, $\theta_0 = 0^\circ$, $\sigma_\theta = 5^\circ$, 16 sensors, theoretical covariance matrix with $S/\sigma^2 = 10$ dB 157

LIST OF ABBREVIATIONS

3G	Third Generation
AOA	Angle-of-arrival
ARV	Array Response Vector
AS	Azimuth Spread (or Angle Spread)
BER	Bit-error-rate
BPSK	Binary Phase-Shift Keying
CBF	Conventional Beamformer
CLT	Central Limit Theorem
CM	Centre of Mass
CRLB	Cram'er-Rao Lower Bound
DISPARE	Dispersed Signal Parametric Estimation
DOA	Direction-of-arrival
DSPE	Distributed Signal Parameter Estimator
FDD	Frequency Division Duplex
FDMA	Frequency Division Multiple Access
GSM	Global System for Mobile communication
LOS	Line-of-sight
LTV	Linear Time-variant Filter
MMSE	Minimum Mean Square Error
MUSIC	Multiple Signal Classification
MVDR	Minimum Variance Distortionless Response
PAS	Power Azimuth Spectrum
PDF	Probability Density Function