



UNIVERSITI PUTRA MALAYSIA

***INTELLIGENT FAULT DIAGNOSIS FOR BROKEN ROTOR BAR USING
WAVELET PACKET SIGNATURE ANALYSIS***

SAHAR ZOLFAGHARI

FK 2016 80



**INTELLIGENT FAULT DIAGNOSIS FOR BROKEN ROTOR BAR USING
WAVELET PACKET SIGNATURE ANALYSIS**

By

SAHAR ZOLFAGHARI

**Thesis Submitted to the School of Graduate Studies, Universiti Putra Malaysia, in
Fulfillment of the Requirements for the Degree of Master of Science**

June 2016

COPYRIGHT

All material contained within the thesis, including without limitation text, logos, icons, photographs and all other artwork, is copyright material of Universiti Putra Malaysia unless otherwise stated. Use may be made of any material contained within the thesis for non-commercial purposes from the copyright holder. Commercial use of material may only be made with the express, prior, written permission of Universiti Putra Malaysia.

Copyright © Universiti Putra Malaysia



DEDICATIONS

This thesis is dedicated to my husband, Arash Fattahi, who has been a constant source of support and encouragement during the challenges of graduate school and life. I am truly thankful for having you in my life.

This work is also dedicated to my parents, Akbar and Ferdoos Zolfaghari, who have always loved me unconditionally.



Abstract of thesis presented to the Senate of Universiti Putra Malaysia in fulfillment of the requirement for the Degree of Master of Science

INTELLIGENT FAULT DIAGNOSIS FOR BROKEN ROTOR BAR USING WAVELET PACKET SIGNATURE ANALYSIS

By

SAHAR ZOLFAGHARI

June 2016

Chairman : Associate Professor. Samsul Bahari Mohd Noor, PhD
Faculty : Engineering

Induction motors are one of the extensively used machines in many industries due to their high reliability and simple structure. However, owing to the high stresses that happen during operation, induction motors are subjected to unavoidable failures. Among numerous inevitable burdens happening in different part of induction machines, rotor faults are considerable priority as they cause precipitate deterioration and, secondary failures that lead to an unexpected shutdown and result in time-consuming and expensive maintenance. Therefore, intelligent fault diagnosis of induction machines is an ongoing research topic because of the complexity of the issue as well as progress in signal processing. As a sensitive signal processing wavelet-based analysis is implemented and some difficulties like, lack of frequency localization, selection of best basis, and fault index are addressed in this study.

Intelligent methods have concerted on sensing precise failure modes and recommending intelligent maintenance decisions based on the signatures collected through signal processing. Therefore, an advanced signal processing must be considered to derive the fault signature accomplish with a powerful decision-making technique. In this thesis, intelligent fault detection and severity classification of broken rotor bars in induction motor is carried out using the secondary data of stator current. The stator current was decomposed using wavelet packet decomposition. Then, the most precious faulty sub bands were identified after spectrum analysis. Next step to assist the most relevant feature extraction was the definition of mother wavelet function. In order to alleviate the time-variant characteristics of the wavelet packet transform coefficients, statistical parameters of wavelet packet coefficients are calculated. Some combinations of features extracted from wavelet packet signature analysis could design neural network trained, cross validated and tested input vector to not only elucidate the faultless from faulty condition, but also classify the number of broken rotor bars.

As an effective signal processing, the time-scale characteristic of wavelet packet transform fused with the frequency resolution of Fast Fourier Transform named as wavelet packet signature analysis. This transformation technique is suitable for locating

certain frequency components of a signal superimposed to fundamental frequency and associated with broken rotor bars. Then, the practically identical mother wavelet, db44, was selected based on standard deviation of wavelet packet coefficients. To make an intelligent decision without the presence of expert, in this research simple multi-layer perceptron NN-based fault classifier is proposed for fault diagnosis which is inexpensive, reliable, and non-invasive by employing best combination of wavelet statistical parameter after a simple feature selection technique as the input vector. The fault detection and classification algorithm is carried out under the unknown dataset and the off-line testing results with 98.8% classification accuracy indicate good reliability of the proposed method in identifying broken rotor bars severity.



Abstrak tesis yang dikemukakan kepada Senat Universiti Putra Malaysia sebagai memenuhi keperluan untuk Ijazah Master Sains

**INTELLIGENT DIAGNOSIS KEROSAKAN UNTUK BAR ROTOR BROKEN
MENGUNAKAN OMBAK PACKET SIGNATURE ANALISIS
MENGUNAKAN**

Oleh

SAHAR ZOLFAGHARI

Jun 2016

Pengerusi : Profesor Madya Samsul Bahari Bin Mohd Noor, PhD
Fakulti : Kejuruteraan

Motor aruhan adalah salah satu mesin yang digunakan secara meluas dalam pelbagai industri kerana kebolehpercayaan yang tinggi dan strukturnya yang mudah. Walau bagaimanapun, oleh kerana tekanan yang tinggi yang berlaku semasa operasi, motor induksi mudah terdedah kepada kegagalan yang tidak dapat dielakkan. Dalam banyak kegagalan yang sering berlaku di bahagian yang berbeza dari mesin induksi, kerosakan pada pemutar adalah jenis kerosakan yang paling kritikal kerana ia menyebabkan mendakan kemerosotan dan kegagalan kedua yang boleh membawa kepada penutupan yang tidak dijangka dan kesannya memakan masa yang panjang untuk pembaikan pada masa sama kos penyelenggaraan yang tinggi. Oleh itu, 'intelligent fault' diagnosis mesin induksi adalah satu topik penyelidikan yang masih aktif kerana kerumitan kerosakan tersebut di samping kemajuan dalam pemprosesan isyarat. Isyarat sensitif berasaskan wavelet pemprosesan analisis dilaksanakan dan beberapa masalah seperti kekurangan kekerapan penyempatan, pemilihan terbaik asas, dan indeks kesalahan ditangani dalam kajian ini. Kaedah Pintar telah bersepadu terhadap penderiaan mod kegagalan tepat dan mencadangkan keputusan penyelenggaraan pintar berdasarkan tandatangan yang dikumpulkan melalui pemprosesan isyarat.

Oleh itu, kemajuan pada pemprosesan isyarat perlu dipertimbangkan agar dapat mengenalpasti kesalahan-kesalahan dengan menggunakan teknik khas dan terbaik. Di dalam tesis ini, kesalahan pintar pengesanan dan klasifikasi tahap kerosakan bar pemutar di dalam motor induksi dijalankan menggunakan data sekunder pemegun semasa. Pemegun semasa diekstrak menggunakan paket ombak penguraian. Seterusnya sub band rosak telah dikenal pasti selepas melalui analisis spektrum. Langkah seterusnya untuk membantu pengekstrakan ciri yang paling relevan ialah definisi ombak ibu fungsi. Dalam usaha untuk mengurangkan ciri-ciri masa-varian paket ombak mengubah pekali, parameter statistik pekali paket ombak dikira. Diantara gabungan ciri yang diekstrak daripada ombak analisis tandatangan paket ialah kebolehan mereka bentuk neural rangkaian yang terlatih, pengesanan dan vektor input diuji untuk bukan sahaja menjelaskan tahap kritikal kerosakan daripada keadaan rosak, tetapi juga

mengklasifikasikan bilangan bar pemutar yang patah.

Sebagai pemrosesan isyarat yang berkesan, ciri-ciri masa skala paket ubahan wavelet disatukan dengan dengan resolusi frekuensi Fourier Transform Fast dinamakan sebagai tandatangan paket ombak analisis. Teknik transformasi ini sesuai bagi mengesan komponen frekuensi tertentu isyarat yang ditekan kepada frekuensi asas dan yang berkaitan dengan bar pemutar patah. Kemudian, ombak ibu, db44, telah dipilih berdasarkan sisihan piawai ombak pekali paket. Untuk membuat keputusan yang bijak tanpa kehadiran pakar, kesalahan pengelasan berasaskan NN yang mudah adalah dicadangkan untuk diagnosis kerosakan yang dapat dilakukan dengan murah, kebolehpercayaan yang tinggi, dan tidak invasif dengan menggunakan kombinasi terbaik ombak parameter statistik selepas teknik pemilihan ciri semudah vektor input. Kesalahan pengesanan dan pengelasan algoritma yang dijalankan di bawah set data yang tidak diketahui dan di luar talian telah menghasilkan 98.8% ketepatan. Ini menunjukkan kebolehpercayaan yang tinggi bagi kaedah yang dicadangkan di dalam mengenalpasti tahap kerosakan pada bar patah pemutar.

ACKNOWLEDGEMENTS

I would like to thank my supervisor Associate Prof. Dr. Samsul Bahari Mohd Noor for his encouragement, unlimited support and providing a pleasant working environment in the department.

Also, I would like to express my appreciation to my committee members, Professor Ir. Dr. Norman b. Mariun and Prof. Dr. Mohammad Hamiruce b. Marhaban for their continuous help, the time they spent with me, the care they have shown and also for their valuable feedbacks, constructive comments and the contributions they made to the complement of this master work.

In addition, I want to thank my love, Arash Fattahi, for encouraging me to follow my education and pursuing this degree was a part of his dream which I tried to fulfill.

Finally, I want to dedicate this thesis to the dearest persons in my life, my mother and my father for their inspirable support and unconditional love.

Last but certainly not least, I would like to thank Mr. Mohammad Rezazadeh Mehrjou from UPM's power electrical laboratory for his support, encouragement and the contributions he made to this thesis in terms of providing experimental motor data.

I certify that a Thesis Examination Committee has met on 27 June 2016 to conduct the final examination of Sahar Zolfaghari on her thesis entitled "Intelligent Fault Diagnosis for Broken Rotor Bar using Wavelet Packet Signature Analysis" in accordance with the Universities and University Colleges Act 1971 and the Constitution of the Universiti Putra Malaysia [P.U.(A) 106] 15 March 1998. The Committee recommends that the student be awarded the Master of Science.

Members of the Thesis Examination Committee were as follows:

Azura binti Che Soh, PhD

Associate Professor
Faculty of Engineering
Universiti Putra Malaysia
(Chairman)

Asnor Juraiza binti Dato Hj. Ishak, PhD

Senior Lecturer
Faculty of Engineering
Universiti Putra Malaysia
(Internal Examiner)

Mohd Rizal Arshad, PhD

Professor
Universiti Sains Malaysia
Malaysia
(External Examiner)



ZULKARNAIN ZAINAL, PhD

Professor and Deputy Dean
School of Graduate Studies
Universiti Putra Malaysia

Date: 23 August 2016

This thesis was submitted to the Senate of the Universiti Putra Malaysia and has been accepted as fulfillment of the requirement for the degree of Master of Science. The members of the Supervisory Committee were as follows:

Samsul Bahari Mohd Noor, PhD

Associate Professor
Faculty of Engineering
Universiti Putra Malaysia
(Chairman)

Norman b. Mariun, PhD

Professor, Ir
Faculty of Engineering
Universiti Putra Malaysia
(Member)

Mohammad Hamiruce b. Marhaban, PhD

Professor
Faculty of Engineering
Universiti Putra Malaysia
(Member)

BUJANG BIN KIM HUAT, PhD

Professor and Dean
School of Graduate Studies
Universiti Putra Malaysia

Date:

Declaration by graduate student

I hereby confirm that:

- this thesis is my original work;
- quotations, illustrations and citations have been duly referenced;
- this thesis has not been submitted previously or concurrently for any other degree at any institutions;
- intellectual property from the thesis and copyright of thesis are fully-owned by Universiti Putra Malaysia, as according to the Universiti Putra Malaysia (Research) Rules 2012;
- written permission must be obtained from supervisor and the office of Deputy Vice-Chancellor (Research and innovation) before thesis is published (in the form of written, printed or in electronic form) including books, journals, modules, proceedings, popular writings, seminar papers, manuscripts, posters, reports, lecture notes, learning modules or any other materials as stated in the Universiti Putra Malaysia (Research) Rules 2012;
- there is no plagiarism or data falsification/fabrication in the thesis, and scholarly integrity is upheld as according to the Universiti Putra Malaysia (Graduate Studies) Rules 2003 (Revision 2012-2013) and the Universiti Putra Malaysia (Research) Rules 2012. The thesis has undergone plagiarism detection software

Signature: _____ Date: _____

Name and Matric No.: Sahar Zolfaghari (GS38140)

Declaration by Members of Supervisory Committee

This is to confirm that:

- the research conducted and the writing of this thesis was under our supervision;
- supervision responsibilities as stated in the Universiti Putra Malaysia (Graduate Studies) Rules 2003 (Revision 2012-2013) were adhered to.

Signature: _____

Name of Chairman
of Supervisory
Committee:

Associate Professor
Dr. Samsul Bahari Mohd Noor

Signature: _____

Name of Member
of Supervisory
Committee:

Professor
Dr. Norman b. Mariun

Signature: _____

Name of Member
of Supervisory
Committee:

Professor
Dr. Mohammad Hamiruce b. Marhaban

TABLE OF CONTENTS

	Page
ABSTRACT	i
ABSTRAK	iii
ACKNOWLEDGEMENTS	v
APPROVAL	vi
DECLARATION	viii
LIST OF TABLES	xii
LIST OF FIGURES	xiii
LIST OF ABBREVIATIONS	xv
LIST OF SYMBOLS	xvi
CHAPTER	
1 INTRODUCTION	1
1.1 Background	1
1.2 Problem Statement	3
1.3 Aim and Objectives	3
1.4 Thesis Scope	4
1.5 Research Contributions	4
1.6 Thesis Organization	5
2 LITERATURE REVIEW	6
2.1 Introduction	6
2.2 Squirrel-Cage Induction Motor	6
2.2.1 Induction Motor Broken Rotor Bars Fault	7
2.3 Condition-based Maintenance	8
2.3.1 Signal Processing Techniques	9
2.3.2 Frequency order of Wavelet Packet Decomposition	15
2.3.3 Mother Wavelet	16
2.4 Feature Index	17
2.5 Intelligent Decision Techniques	17
2.5.1 Theory of the Supervised MLP-NN	18
2.6 Summary	20
3 RESEARCH METHODOLOGY	21
3.1 Introduction	21
3.2 The Construction of Wavelet Packet Signature Analysis	23
3.2.1 Best Basis of Wavelet Packet Signature Analysis	26
3.3 Feature Extraction of Wavelet Packet Signature Analysis	28
3.4 Neural Network-based fault severity Classifier	30
3.4.1 Feature Vector of Neural Network	30
3.5 Summary	31
4 RESULTS AND DISCUSSION	33
4.1 Fault Detection Procedure	33
4.1.1 Wavelet Packet Signature Analysis	34
4.1.2 Selection of Mother Wavelet	37

4.2	Feature Index	41
4.3	Training and testing of NN	47
4.4	Performance Comparison	55
4.5	Summary	56
5	CONCLUSION AND RECOMMENDATIONS	58
5.1	Conclusion	58
5.2	Recommendations for Future Work	59
	REFERENCES	61
	APPENDICES	69
	BIODATA OF STUDENT	80
	LIST OF PUBLICATIONS	81



LIST OF TABLES

Table		Page
2.1	Review on Discrete Wavelet Transform	11
2.2	Review on Wavelet Packet Decomposition	14
3.1	The Fourteen Wavelet Statistical Parameters	29
4.1	Fault Frequency of BRBs	36
4.2	Studied Wavelet Families in this research	37
4.3	Mean Value of Statistical Features for Healthy and Faulty Motor in High Load	41
4.4	Mean Value of Statistical Features for Healthy and Faulty Motor in Medium Load	42
4.5	Mean Value of Statistical Features for Healthy and Faulty Motor in Low Load	42
4.6	Mean Value of Statistical Features for Healthy and Faulty Motor in No Load	43
4.7	Performance of MLP NN-based Classifier on Cross-Validation Data	50
4.8	Performance of MLP NN-Classifier on Test Dataset	50
4.9	High Load Sample Desired and Output Calculations	51
4.10	Desired and Actual Output in all Load Conditions	52
4.11	Comparison Specification of Proposed and Previous Work with Same Experiment Layout	57

LIST OF FIGURES

Figure		Page
2.1	The Construction of three Phase Squirrel-Cage Induction Motors	7
2.2	Effect of Broken Rotor Bar in Magnetic Flux [14]	8
2.3	Three Level of Discrete Wavelet Decomposition	12
2.4	Three Level of Wavelet Packet Decomposition	13
2.5	Three-layer Structure of WPD based on Frequency Order	16
3.1	The Proposed Fault Diagnostic Algorithm	22
3.2	Node Order and Frequency Sub-band of WPD	23
3.3	WPSA Flow Chart	24
3.4	Decomposition and Reconstruction Process	25
3.5	MW Selection Flow Chart	27
3.6	Schematic diagram of the MLP network Classifier	31
4.1	FFT on Wavelet Packet Tree	35
4.2	Most reliable wavelet tree based on WPSA	36
4.3	StD of WPSA vs. 82 mother wavelets in High Load Condition	38
4.4	Selected Mother Wavelets in Different Loads	39
4.5	Wavelet Packet Spectrum of Decomposed Signal Using Db44	40
4.6	Wavelet Packet Spectrum of Decomposed Signal Using Db45	40
4.7	High Order Daubechies	41
4.8	Decline in Kurtosis, P to RMS, and PAPR For High and No Load Condition	44
4.9	RMS of WPC	45
4.10	Increase in RSSQ, Energy, and StD in all Load Condition	46
4.11	Variation of Average Classification and MSE with a Number of Features as Inputs in High Load	48

4.12	Variation of Average Classification and MSE with a Number of Features as Inputs in Medium Load	48
4.13	Variation of Average Classification and MSE with a Number of Features as Inputs in Low Load	49
4.14	Variation of Average Classification and MSE with a Number of Features as Inputs in No Load	49
4.15	The Error between Real Output and Desired for Testing Data set in 80% of Full Load	53
4.16	The Error between Real Output and Desired for Testing Data set in 50% of Full Load	54
4.17	The Error between Real Output and Desired for Testing Data set in 35% of Full Load	54
4.18	The error between real output and desired for testing data set in 10% of full load	55

LIST OF ABBREVIATIONS

ANN	Artificial Neural Network
BP	Back-propagation
CBM	Condition-Based Monitoring
CI	Computational Intelligence
CV	Cross-Validation
DWT	Discrete Wavelet Transform
FFNN	Feed forward neural network
GUI	Graphical Unit Interface
IM	Induction Motor
LOO	Leave-One-Out
MCSA	Motor Current Signature Analysis
MLP-NN	Multi-layer Perceptron Neural Network
NEMA	National Electrical Manufacturers Association
MRA	Multi-resolution Analysis
RMS	Root Mean Square
RMSE	Root Mean Square Error
STFT	Short-Time Fourier Transform
SCIM	Squirrel-cage Induction Motor
StD	Standard Deviation
StD-WPC	Standard Deviation Of Wavelet Packet Coefficients
WPSA	Wavelet Packet Signature Analysis
WPT	Wavelet Packet Transform
WPD	Wavelet Packet Decomposition
WPR	Wavelet Packet Reconstruction
WPC-SCS	Wavelet Packet Coefficients of Synchronized Current Signal

LIST OF SYMBOLS

db	Daubechies
f_b	Broken Rotor Bar Frequency
f_s	Fundamental Frequency
n_s	Synchronous Speed
n	Rotor Speed
N_s	Number of Samples
S_f	Sampling frequency
s	Slip

CHAPTER 1

INTRODUCTION

1.1 Background

The initiation of induction motors by Galileo Ferraris in 1885 and further improvement by Nikola Tesla in 1888 provided industrial process engineers with a simple and rugged mechanism for electromechanical conversion [1]. Induction motors are basic segments in commercially accessible equipment and industrial procedures because of being cost effective and their robust performance. Among distinctive sorts of electric engines, more than 60% of the electrical energy produced is because of induction motors contribution [2]. In Europe, it has been reported that 87% of 96.2% AC motors shipment are devoted to three-phase induction motors [2]. Electric motors have transformed the form of human living and shaped in the convenient lifestyle. In every item that we consume or utilize these days or in any facilities that we profit, there is an electric motor involved [3]. Therefore, electrical machine condition monitoring assumes a critical part in modern industries.

An AC induction motor consists of two key parts: rotor and stator. The rotor core is affixed on a steel shaft to form a rotor congregation. The stator is mounted in the middle of the frame and the rotor turns interior the stator. There is a slight air gap separating rotor from the stator. The name induction motor is used because there is no direct physical and electric connection between stator and rotor and electricity is induced in the rotor by magnetic induction rather than electric connection [4]. Nevertheless, induction machines are subjected to the unavoidable burdens in the practical applications.

The rotor is subjected to different types of tensions that severely affect its normal condition and consequently create failures in it. In addition, localized rotor heating around the broken bars may progressively break the adjacent bars and the motor will be finally out of service. Rotor bar breakages rarely cause immediate failures. However, it can become quite a dangerous fault since no clear symptom is reflected over the machine behavior in the early stages. In the case with enough broken rotor bars, the motor possibly will not start as it could not develop sufficient accelerating torque [5]. Nonetheless, the presence of broken rotor bars precipitates deterioration in other components that can lead to an unexpected breakdown of the machine and result in time-consuming and expensive maintenance. Therefore, detection of broken bar faults is a crucial issue.

It is well known that fault detection in induction machine at an early stage may not only lessen maintenance time and minimize breakdowns but also prevent propagation of the fault or slow down its escalation to severe degrees. Therefore, a health monitoring or intelligent condition-based monitoring program which can diagnose such a failure of electrical machines has received extensive consideration for many years. Accordingly, a signal acquired from one of the prevalent condition monitoring techniques need to be

evaluated through an advanced signal processing method to generate fault-representative features for the purpose of decision making. Signal processing is a mathematical transformer used for fault detection and diagnostics, whose aim is to convert the raw complex signal to a more understandable signal which enhances the dominant features of fault signature for decision-making. The three major categories of the signature extraction techniques for the fault diagnosis are time domain, frequency domain and time-frequency domain techniques [6].

Time domain-feature extraction techniques include statistical methods, time synchronous averaging methods and other methods. The most frequently used time domain statistical features are root-mean-square, skewness, kurtosis, crest factor and so forth. Time domain features are useful for machinery fault diagnosis, especially for short-duration feature detecting. However, clear symptoms of the fault still may not be directly visible in the time domain. Literally, each fault is associated with the presence of a explicit harmonic in the spectrum. The frequency domain is another signal processing tool which describes the frequency information of a signal and extracts the energy of a particular frequency component. Motor Current Signature Analysis (MCSA) was extensively used based on the monitoring of the sideband components at $(1 \pm s)f$, where f_s is the fundamental frequency and s is the slip [7][8]. When the waveforms examined are stationary or periodical, feature extraction using Fourier transform produces good results, but they are not suitable for non-stationary signals.

In an effort to correct this insufficiency, as reported in Wavelet Toolbox™, Dennis Gabor adapted the Short-Time Fourier Transform (STFT). The difficulty with STFT is that the information obtained with limited precision is determined by the size of the window. This means the chosen time window with a particular size is same for all frequencies. Therefore, the time and frequency resolutions cannot increase simultaneously using STFT. Experimental diagnostic via spectral analysis is more complicated due to the subsequent reasons [9]:

- the precise measurement of slip and fundamental frequency,
- the simultaneous presence of numerous transitory and other various kinds of non-stationary characteristics such as noises, load torque fluctuations, voltage oscillations, and abrupt changes, and
- discrimination of several faults frequency span for different categories of faults may exist at the same time [10].

Hitherto, many non-stationary signal processing methods have been suggested in the literature to those published after the 1990s [11]. A straight forward solution for these difficulties is Discrete Wavelet Transform (DWT), because of zooming and adaptive windowing capability. Frequency resolution and time localization nature of time-scale analysis have been used to extract and describe a more precise behaviour of the stator current signal which is widely used for electrical machine diagnosis [10]. However, DWT iteratively decomposes the approximation signals of lower frequencies but does

not further work on the detail signals of higher frequencies. Therefore, due to the coarse decomposition of the high-frequency components in the signal, the resolution in the high-frequency region is quite poor. As a subtle multi-resolution analysis algorithm, Wavelet Packet Transform (WPT) can multi-decompose the signal into multi-levels and provide the different frequencies to obtain the localized impulse signals.

1.2 Problem Statement

According to the background, the specific issue is designing and developing a sensitive signal processing with a great concern of no-load condition. As a sensitive signal processing method, wavelet transform is a time-scale representation of a signal. Moreover, most time-varying machine operational conditions lead to non-stationary characteristics which contain rich information about machinery health condition. The way wavelet analysis localizes signal's information in the time-scale plane makes it especially more advisable in processing the non-stationary signals [12]. Therefore, conclusive fault features can be extracted from these signals for early identification of faults through the identification of time variant features superimposed at different scales. However, because wavelet transform is a time-scale domain technique, it does not provide frequency information on characteristic feature components. Consequently, one of the important point which needs to be affirmed in wavelet packet-based techniques is the fact that frequency order is not the same as the node order due to down sampling [13] [14]. Moreover, in order to choose the most appropriate subset instead of investigating all wavelet packet coefficients, care must be taken to manage the computational complexity, especially in practical circumstances. The next important point is to determine which mother wavelet has more distinctive wavelet coefficients for different conditions in fault identification as an ill-selected base may return false diagnosis result.

The next challenge is extracting the most appropriate feature indices which play an essential role in accomplishment of the performance of intelligent condition monitoring. In contrast to many researches in which only one feature extracted, this research mainly focuses on finding perfectly permissible features for broken rotor bar fault detection, in order to examine the arbitrary working conditions with focus on no-load case [15]. Different topologies of neural networks have been exploited to solve complex problems in various areas of almost all sophisticated fault classification tools. However, a tradeoff exists so that increasing the complexity the fault detection capability is also increased together with computational cost [16]. Therefore, one more step is taken toward an intelligent fault-severity classification with small set of data, by utilizing generalized, simple, small-sized and efficient multi-layer perceptron neural network.

1.3 Aim and Objectives

The aim of this study is focused on the application of an effectiveness signal processing through linking the strong points of both the time-scale and frequency domain techniques, a unified Wavelet Packet Signature Analysis (WPSA) technique that pinpoints the fault signature in special frequency bands with suitable sensitivity and a great concern of no load cases. Moreover, the necessity of sufficient and efficient

maintenance policies according to the literature review on intelligent decision-making algorithms for BRBs fault classification and severity identification in induction motor could be essential. Therefore, the following objectives were pursued in this research work.

- i. To define the exact localized fault frequency sub-bands based on WPSA associated with the most appropriate mother wavelet through investigating the ability of different types of wavelet functions for BRB detection.
- ii. To develop statistical features extracted from wavelet packet coefficients of stator current signal (WPC-SCS) for BRB fault detection with a great concern of no load condition.
- iii. To classify fault-severity of BRBs in arbitrary working conditions using simple multi-layer perceptron neural network (MLP-NN).

1.4 Thesis Scope

This thesis provides a comprehensive study on broken rotor bar detection and severity classification in assorted load in squirrel-cage induction machines. In the first step, the wavelet packet transform was applied to the stator current signal which has been acquired by previous research [17]. In order to enhance the effectiveness of defect feature extraction, FFT combines with WPT which can be called as WPSA in the current study. WPSA can accurately differentiate between healthy and faulty machines in more concentrated fault-related depths and nodes. Next step to assist the most relevant feature extraction was the definition of mother wavelet function. Finally, in order to examine the effect of load variations and fault severity on the fault signatures, the statistical parameters of wavelet packet coefficients along with the slip speed formed the input vector to the classifier. On the one hand, detection of fault-oriented sub bands and classification of fault severity on the other hand make the proposed algorithm clearly different with the base research in 2011 [17] with same database.

1.5 Research Contributions

The main contributions of this work are as follows:

1. In the signal processing step, exact localized fault frequency sub bands is determined based on the combination of WPD and FFT named as WPSA under arbitrary load conditions.
2. In the feature extraction step, wavelet statistical parameter of transformed stator current is applied after an advanced signal processing technique as an input vector to NN.

In the classification step, a straightforward, small-sized, low-cost multi-layer perceptron neural network (MLP-NN) is used in order to have an intelligent, reliable, and non-

invasive classifier.

1.6 Thesis Organization

The dissertation is organized as follow: In Chapter 2, the required background knowledge for the rest of the thesis is introduced briefly. The mechanical structure of an AC induction motor is described in particular also; the induction motor's performance which causes broken rotor fault has been discussed. To deal with this serious malfunction and the diagnosis of fault in an early stage, data processing along with the related difficulties and artificial intelligent decision-making will be highlighted as main subsections of intelligent condition-base monitoring, which have been used for induction motors fault detection and severity classification.

The gaps in the field of BRB fault detection and classification will be fulfilled by manipulated methodology in Chapter 3 to extract a reliable method that allows a better separation of anomaly cases from the normal operating condition modes of the motor and severity assessment. In Chapter 4, the findings of the research will be presented highlighting the role of broken rotor bar detection based on application of wavelet packet decomposition integrated with Fast Fourier transform to track the most appropriate depth and nodes. These results can be used to optimize the scheduling and clustering, and support the maintenance decision making, by implementing a simple cost-effective multi-layer perceptron neural network. Finally, the conclusion of the thesis and possible areas for future research will be presented in Chapter5.

REFERENCES

- [1] M. Eltabach, A. Charara, and I. Zein, "A Comparison of External and Internal Methods of Signal Spectral Analysis for Broken Rotor Bars Detection in Induction Motors," *IEEE Trans. Ind. Electron.*, vol. 51, no. 1, pp. 107–121, Feb. 2004.
- [2] M. Seera, Chee Peng Lim, D. Ishak, and H. Singh, "Fault Detection and Diagnosis of Induction Motors Using Motor Current Signature Analysis and a Hybrid FMM–CART Model," *IEEE Trans. Neural Networks Learn. Syst.*, vol. 23, no. 1, pp. 97–108, Jan. 2012.
- [3] M. Seera, C. P. Lim, D. Ishak, and H. Singh, "Application of the Fuzzy min–max Neural Network to Fault Detection and Diagnosis of Induction Motors," *Neural Comput. Appl.*, vol. 23, no. S1, pp. 191–200, Dec. 2013.
- [4] J.-C. Trigeassou, *Electrical Machines Diagnosis*. Hoboken, NJ, USA: John Wiley & Sons, Inc, 2011.
- [5] G. Didier, E. Ternisien, O. Caspary, and H. Razik, "A New Approach to Detect Broken Rotor Bars in Induction Machines by Current Spectrum Analysis," *Mech. Syst. Signal Process.*, vol. 21, no. 2, pp. 1127–1142, Feb. 2007.
- [6] A. Bellini, F. Filippetti, C. Tassoni, and G.-A. Capolino, "Advances in Diagnostic Techniques for Induction Machines," *IEEE Trans. Ind. Electron.*, vol. 55, no. 12, pp. 4109–4126, Dec. 2008.
- [7] I. Aydin, M. Karakose, and E. Akin, "A New Method for Early Fault Detection and Diagnosis of Broken Rotor Bars," *Energy Convers. Manag.*, vol. 52, no. 4, pp. 1790–1799, Apr. 2011.
- [8] B. Ayhan, H. J. Trussell, Mo-Yuen Chow, and Myung-Hyun Song, "On the Use of a Lower Sampling Rate for Broken Rotor Bar Detection With DTFT and AR-Based Spectrum Methods," *IEEE Trans. Ind. Electron.*, vol. 55, no. 3, pp. 1421–1434, Mar. 2008.
- [9] V. N. Ghate and S. V. Dudul, "Cascade Neural-Network-Based Fault Classifier for Three-Phase Induction Motor," *IEEE Trans. Ind. Electron.*, vol. 58, no. 5, pp. 1555–1563, May 2011.
- [10] J. Antonino-Daviu, P. Jover Rodriguez, M. Riera-Guasp, M. Pineda-Sánchez, and A. Arkkio, "Detection of Combined Faults in Induction Machines with Stator Parallel Branches through the DWT of the Startup Current," *Mech. Syst. Signal Process.*, vol. 23, no. 7, pp. 2336–2351, Oct. 2009.
- [11] Z. Feng, M. Liang, and F. Chu, "Recent Advances in time–frequency Analysis Methods for Machinery Fault Diagnosis: A Review with Application Examples," *Mech. Syst. Signal Process.*, vol. 38, no. 1, pp. 165–205, Jul. 2013.

- [12] Gerhard Henneberger, *Electrical Machines I*. 2002.
- [13] F. Filippetti, A. Bellini, and G. Capolino, "Condition Monitoring and Diagnosis of Rotor Faults in Induction Machines: State of Art and Future Perspectives," *IEEE Work. Electr. Mach. Des. Control Diagnosis*, pp. 196–209, Mar. 2013.
- [14] B. Ayhan, "Linguistic Rule Generation for Broken Rotor Bar Detection in Squirrelcage Induction Motors," North Carolina State University, 2005.
- [15] R. Ahmad and S. Kamaruddin, "An Overview of Time-based and Condition-based Maintenance in Industrial Application," *Comput. Ind. Eng.*, vol. 63, no. 1, pp. 135–149, Aug. 2012.
- [16] M. Seera, C. P. Lim, S. Nahavandi, and C. K. Loo, "Condition Monitoring of Induction Motors: A Review and an Application of an Ensemble of Hybrid Intelligent Models," *Expert Syst. Appl.*, vol. 41, no. 10, pp. 4891–4903, Aug. 2014.
- [17] A. K. S. Jardine, D. Lin, and D. Banjevic, "A Review on Machinery Diagnostics and Prognostics Implementing Condition-based Maintenance," *Mech. Syst. Signal Process.*, vol. 20, no. 7, pp. 1483–1510, Oct. 2006.
- [18] V. T. Tran and B.-S. Yang, "An intelligent condition-based maintenance platform for rotating machinery," *Expert Syst. Appl.*, vol. 39, no. 3, pp. 2977–2988, Feb. 2012.
- [19] M. R. Mehrjou, N. Mariun, M. Hamiruce Marhaban, and N. Misron, "Rotor Fault Condition Monitoring Techniques for Squirrel-Cage Induction Machine—A Review," *Mech. Syst. Signal Process.*, vol. 25, no. 8, pp. 2827–2848, Nov. 2011.
- [20] S. Bin Lee, D. Hyun, T. Kang, C. Yang, S. Shin, H. Kim, S. Park, T. Kong, and H. Kim, "on-Line Mcsa for Medium Voltage Induction Machines," no. 1, pp. 1–9, 2015.
- [21] H. Su and K. T. Chong, "Induction Machine Condition Monitoring Using Neural Network Modeling," *IEEE Trans. Ind. Electron.*, vol. 54, no. 1, pp. 241–249, Feb. 2007.
- [22] P. Konar and P. Chattopadhyay, "Bearing fault detection of induction motor using wavelet and Support Vector Machines (SVMs)," *Appl. Soft Comput.*, vol. 11, no. 6, pp. 4203–4211, Sep. 2011.
- [23] S. A. Taher, M. Malekpour, and M. Farshadnia, "Diagnosis of broken rotor bars in induction motors based on harmonic analysis of fault components using modified adaptive notch filter and discrete wavelet transform," *Simul. Model. Pract. Theory*, vol. 44, pp. 26–41, 2014.

- [24] J. Cusido, J. A. Rosero, L. Romeral, J. A. Ortega, and A. Garcia, "Fault Detection in Induction Machines by Using Power Spectral Density on the Wavelet Decompositions," in *37th IEEE Power Electronics Specialists Conference*, 2008, vol. 55, no. 2, pp. 1–6.
- [25] Z. K. Peng and F. L. Chu, "Application of the Wavelet Transform in Machine Condition Monitoring and Fault Diagnostics: A Review with Bibliography," *Mech. Syst. Signal Process.*, vol. 18, no. 2, pp. 199–221, Mar. 2004.
- [26] R. Yan, R. X. Gao, and X. Chen, "Wavelets for Fault Diagnosis of Rotary Machines: A Review with Applications," *Signal Processing*, vol. 96, no. PART A, pp. 1–15, Mar. 2014.
- [27] J. F. Watson and N. C. Paterson, "Improved Techniques for Rotor Fault Detection in Three-phase induction motors," in *Conference Record of 1998 IEEE Industry Applications Conference. Thirty-Third IAS Annual Meeting (Cat. No.98CH36242)*, 1998, vol. 1, pp. 271–277.
- [28] J. A. Antonino-Daviu, M. Riera-Guasp, J. R. Folch, and M. P. M. Palomares, "Validation of a New Method for the Diagnosis of Rotor Bar Failures via Wavelet Transform in Industrial Induction Machines," *IEEE Trans. Ind. Appl.*, vol. 42, no. 4, pp. 990–996, Jul. 2006.
- [29] S. H. Kia, H. Henao, and G. a. Capolino, "Diagnosis of Broken-Bar Fault in Induction Machines Using Discrete Wavelet Transform without Slip Estimation," *IEEE Trans. Ind. Appl.*, vol. 45, no. 4, pp. 1395–1404, 2009.
- [30] M. Eltabach, J. Antoni, G. Shanina, S. Sieg-Zieba, and X. Carniel, "Broken Rotor Bars Detection by a New Non-invasive Diagnostic Procedure," *Mech. Syst. Signal Process.*, vol. 23, no. 4, pp. 1398–1412, May 2009.
- [31] J. Faiz, B. M. Ebrahimi, B. Akin, and B. Asaie, "Criterion Function for Broken-Bar Fault Diagnosis in Induction Motor under Load Variation Using Wavelet Transform," *Electromagnetics*, vol. 29, no. 3, pp. 220–234, Mar. 2009.
- [32] P. Shi, Z. Chen, Y. Vagapov, and Z. Zouaoui, "A New Diagnosis of Broken Rotor Bar Fault Extent in Three phase Squirrel Cage Induction Motor," *Mech. Syst. Signal Process.*, vol. 42, no. 1–2, pp. 388–403, Jan. 2014.
- [33] M. R. Mehrjou, "Motor Current Signature Analysis of Incipient Broken Rotor Bar of Squirrel Cage Induction Motor," Universiti Putra Malaysia, 2011.
- [34] J. Antonino-Daviu, M. Riera-Guasp, J. Roger-Folch, F. Martínez-Giménez, and A. Peris, "Application and optimization of the discrete wavelet transform for the detection of broken rotor bars in induction machines," *Appl. Comput. Harmon. Anal.*, vol. 21, no. 2, pp. 268–279, Sep. 2006.
- [35] A. Bouzida, O. Touhami, R. Ibtouen, A. Belouchrani, M. Fadel, and a. Rezzoug, "Fault diagnosis in industrial induction machines through discrete

- wavelet transform,” *IEEE Trans. Ind. Electron.*, vol. 58, no. 9, pp. 4385–4395, 2011.
- [36] B. M. Ebrahimi, J. Faiz, S. Lotfi-fard, and P. Pillay, “Novel Indices for Broken Rotor Bars Fault Diagnosis in Induction Motors Using Wavelet Transform,” *Mech. Syst. Signal Process.*, vol. 30, pp. 131–145, Jul. 2012.
- [37] M. R. Mehrjou, N. Mariun, M. Karami, N. Misron, S. Toosi, and M. R. Zare, “Evaluation of Wavelet–Functions for Broken Rotor Bar Detection of Induction Machine Using Coefficient–Related Features,” *Int. J. Appl. Electron. Phys. Robot.*, vol. 1, no. 1, pp. 18–23, Jul. 2013.
- [38] E. Y. Hamid and Z. Kawasaki, “Wavelet-Based Data Compression of Power System Disturbances Using the Minimum Description Length Criterion,” vol. 17, no. 2, pp. 460–466, 2002.
- [39] Zhongming Ye, Bin Wu, and A. Sadeghian, “Current Signature Analysis of Induction Motor Mechanical Faults by Wavelet Ppacket Decomposition,” *IEEE Trans. Ind. Electron.*, vol. 50, no. 6, pp. 1217–1228, Dec. 2003.
- [40] L. Eren and M. J. Devaney, “Bearing Damage Detection via Wavelet Packet Decomposition of the Stator Current,” *IEEE Trans. Instrum. Meas.*, vol. 53, no. 2, pp. 431–436, 2004.
- [41] J. Zarei and J. Poshtan, “Bearing Fault Detection Using Wavelet Packet Transform of Induction Motor Stator Current,” *Tribol. Int.*, vol. 40, no. 5, pp. 763–769, May 2007.
- [42] S. Ekici, S. Yildirim, and M. Poyraz, “Energy and entropy-based feature extraction for locating fault on transmission lines by using neural network and wavelet packet decomposition,” *Expert Systems with Applications*, May-2008. .
- [43] G.-M. Xian and B.-Q. Zeng, “An intelligent fault diagnosis method based on wavelet packet analysis and hybrid support vector machines,” *Expert Syst. Appl.*, vol. 36, no. 10, pp. 12131–12136, Dec. 2009.
- [44] A. Sadeghian, Zhongming Ye, and Bin Wu, “Online Detection of Broken Rotor Bars in Induction Motors by Wavelet Packet Decomposition and Artificial Neural Networks,” *IEEE Trans. Instrum. Meas.*, vol. 58, no. 7, pp. 2253–2263, Jul. 2009.
- [45] H. Abu-Rub, A. Iqbal, S. Moin Ahmed, J. Guzinski, M. Adamowicz, and M. Rahiminia, “Rotor broken bar diagnostics in induction motor drive using Wavelet packet transform and ANFIS classification,” *2011 IEEE Int. Electr. Mach. Drives Conf. IEMDC 2011*, pp. 365–370, 2011.
- [46] G. F. Bin, J. J. Gao, X. J. Li, and B. S. Dhillon, “Early Fault Diagnosis of Rotating Machinery based on Wavelet Packets—Empirical Mode Decomposition Feature Extraction and Neural network,” *Mech. Syst. Signal Process.*, vol. 27, pp. 696–711, Feb. 2012.

- [47] J. C. G.-P. Maria Jesus Gomez, Cristina Castejon, "Incipient Fault Detection in Bearings Through the use of WPT Energy and Neural Networks," in *Advances in Condition Monitoring of Machinery in Non-Stationary Operations*, vol. 5, G. Dalpiaz, R. Rubini, G. D'Elia, M. Cocconcelli, F. Chaari, R. Zimroz, W. Bartelmus, and M. Haddar, Eds. Berlin, Heidelberg: Springer Berlin Heidelberg, 2014, pp. 535–544.
- [48] H. Keskes and A. Braham, "Recursive Undecimated Wavelet Packet Transform and DAG SVM for Induction Motor Diagnosis," *IEEE Trans. Ind. Informatics*, vol. 11, no. 5, pp. 1059–1066, Oct. 2015.
- [49] J. Rafiee, P. W. Tse, A. Harifi, and M. H. Sadeghi, "A Novel Technique for Selecting Mother Wavelet Function Using an Intelligent Fault Diagnosis System," *Expert Syst. Appl.*, vol. 36, no. 3, pp. 4862–4875, Apr. 2009.
- [50] M. A. S. K. Khan, S. Member, T. S. Radwan, S. Member, and M. A. Rahman, "Real-Time Implementation of Wavelet Packet Transform-Based Diagnosis and Protection of Three-Phase Induction Motors," vol. 22, no. 3, pp. 647–655, 2007.
- [51] X. Jiao, K. Ding, and G. He, "An Algorithm for Improving the Coefficient Accuracy of Wavelet Packet Analysis," *Measurement*, vol. 47, no. 1, pp. 207–220, Jan. 2014.
- [52] S. G. Mallat, "A Theory for Multiresolution Signal Decomposition: the Wavelet Representation," *IEEE Trans. Pattern Anal. Mach. Intell.*, vol. 11, no. 7, pp. 674–693, Jul. 1989.
- [53] R. R. Coifman and M. V. Wickerhauser, "Entropy Based Algorithms for Best Basis Selection," *IEEE Trans. Inf. Theory*, vol. 32, no. 2, pp. 712–718, 1992.
- [54] Enzo C. C. Lau and H.W. Ngan, "Detection of motor bearing outer raceway defect by wavelet packet transformed motor current signature analysis," *IEEE Trans. Instrum. Meas.*, vol. 59, no. 10, pp. 2683–2690, 2010.
- [55] C. Wang, R. X. Gao, and R. Yan, "Unified Time–Scale–Frequency Analysis for Machine Defect Signature Extraction: Theoretical Framework," *Mech. Syst. Signal Process.*, vol. 23, no. 1, pp. 226–235, Jan. 2009.
- [56] R. Yan, R. X. Gao, and C. Wang, "Experimental Evaluation of a Unified Time-Scale-Frequency Technique for Bearing Defect Feature Extraction," *J. Vib. Acoust.*, vol. 131, no. 4, p. 041012, 2009.
- [57] Z. Zhang, Y. Wang, and K. Wang, "Fault diagnosis and prognosis using wavelet packet decomposition, Fourier transform and artificial neural network," *J. Intell. Manuf.*, vol. 24, no. 6, pp. 1213–1227, Dec. 2013.
- [58] H. Douglas and P. Pillay, "The Impact of Wavelet Selection on Transient Motor

- Current Signature Analysis,” *IEEE Int. Conf. Electr. Mach. Drives, 2005.*, pp. 80–85, 2005.
- [59] J. Rafiee, M. A. Rafiee, and P. W. Tse, “Application of Mother Wavelet Functions for Automatic Gear and Bearing Fault Diagnosis,” *Expert Syst. Appl.*, vol. 37, no. 6, pp. 4568–4579, Jun. 2010.
- [60] J. Rafiee, F. Arvani, a. Harifi, and M. H. Sadeghi, “Intelligent condition monitoring of a gearbox using artificial neural network,” *Mech. Syst. Signal Process.*, vol. 21, no. 4, pp. 1746–1754, May 2007.
- [61] G. G. Yen and K.-C. Lin, “Wavelet Packet Feature Extraction for Vibration Monitoring,” *IEEE Trans. Ind. Electron.*, vol. 47, no. 3, pp. 650–667, Jun. 2000.
- [62] V. T. Tran, F. AlThobiani, A. Ball, and B. K. Choi, “An application to transient current signal based induction motor fault diagnosis of Fourier-Bessel expansion and simplified fuzzy ARTMAP,” *Expert Syst. Appl.*, vol. 40, no. 13, pp. 5372–5384, 2013.
- [63] C. S. Chen and J. S. Chen, “Rotor fault diagnosis system based on sGA-based individual neural networks,” *Expert Syst. Appl.*, vol. 38, no. 9, pp. 10822–10830, Sep. 2011.
- [64] A. Widodo and B.-S. Yang, “Support vector machine in machine condition monitoring and fault diagnosis,” *Mech. Syst. Signal Process.*, vol. 21, no. 6, pp. 2560–2574, Aug. 2007.
- [65] a. Tabrizi, L. Garibaldi, A. Fasana, and S. Marchesiello, “Early damage detection of roller bearings using wavelet packet decomposition, ensemble empirical mode decomposition and support vector machine,” *Meccanica*, vol. 50, no. 3, pp. 865–874, Mar. 2015.
- [66] D. A. Asfani, A. K. Muhammad, Syafaruddin, M. H. Purnomo, and T. Hiyama, “Temporary Short Circuit Detection in Induction Motor Winding Using Combination of Wavelet Transform and Neural Network,” *Expert Syst. Appl.*, vol. 39, no. 5, pp. 5367–5375, Apr. 2012.
- [67] S. Guedidi, S. E. Zouzou, W. Laala, K. Yahia, and M. Sahraoui, “Induction Motors Broken Rotor Bars Detection Using MCSA and Neural Network: Experimental Research,” *Int. J. Syst. Assur. Eng. Manag.*, vol. 4, no. 2, pp. 173–181, Jun. 2013.
- [68] K. Bacha, H. Henao, M. Gossa, and G. a. Capolino, “Induction machine fault detection using stray flux EMF measurement and neural network-based decision,” *Electr. Power Syst. Res.*, vol. 78, no. 7, pp. 1247–1255, Jul. 2008.
- [69] H. C. Cho, J. Knowles, M. S. Fadali, and K. S. Lee, “Fault Detection and Isolation of Induction Motors Using Recurrent Neural Networks and Dynamic Bayesian Modeling,” *IEEE Trans. Control Syst. Technol.*, vol. 18, no. 2, pp. 430–437, Mar. 2010.

- [70] C. T. Kowalski and T. Orłowska-Kowalska, "Neural Networks Application for Induction Motor Faults Diagnosis," *Math. Comput. Simul.*, vol. 63, no. 3–5, pp. 435–448, Nov. 2003.
- [71] V. N. Ghate and S. V. Dudul, "Optimal MLP neural network classifier for fault detection of three phase induction motor," *Expert Syst. Appl.*, vol. 37, no. 4, pp. 3468–3481, Apr. 2010.
- [72] E. Cabal-Yepez, M. Valtierra-Rodriguez, R. J. Romero-Troncoso, A. Garcia-Perez, R. A. Osornio-Rios, H. Miranda-Vidales, and R. Alvarez-Salas, "FPGA-based Entropy Neural Processor for Online Detection of Multiple Combined Faults on Induction Motors," *Mech. Syst. Signal Process.*, vol. 30, pp. 123–130, Jul. 2012.
- [73] F. M. C. Santos, I. Nunes, and M. Suetake, "Neural Network Classifier for Faults Detection in Induction Motors," 2013.
- [74] M. Rezazadeh Mehrjou, "Evaluation of Wavelet-Functions for Broken Rotor Bar Detection of Induction Machine Using Coefficient-Related Features," *Int. J. Appl. Electron. Phys. Robot.*, vol. 1, no. 1, pp. 18–23, 2013.
- [75] N. G. Nikolaou and I. a. Antoniadis, "Rolling Element Bearing Fault Diagnosis Using Wavelet Packets," *NDT E Int.*, vol. 35, no. 3, pp. 197–205, Apr. 2002.
- [76] S. Mallat, "Fourier kingdom," in *A Wavelet Tour of Signal Processing*, Elsevier, 1999, pp. 20–41.
- [77] H. Gopinath, Burrus and Gopinath, Ramesh and Guo, "Introduction to Wavelets and Wavelets Transforms." pp. 1–281, 1998.
- [78] J. Rafiee and P. W. Tse, "Use of Autocorrelation of Wavelet Coefficients for Fault Diagnosis," *Mech. Syst. Signal Process.*, vol. 23, no. 5, pp. 1554–1572, Jul. 2009.
- [79] A. Libraries, "Artificial Intelligence in Electrical Machine Condition Monitoring," 2009.
- [80] T. Han, B.-S. Yang, W.-H. Choi, and J.-S. Kim, "Fault Diagnosis System of Induction Motors Based on Neural Network and Genetic Algorithm Using Stator Current Signals," *Int. J. Rotating Mach.*, vol. 2006, pp. 1–13, 2006.
- [81] S. Zhang, J. Mathew, L. Ma, and Y. Sun, "Best Basis-based Intelligent Machine Fault Diagnosis," *Mech. Syst. Signal Process.*, vol. 19, no. 2, pp. 357–370, Mar. 2005.
- [82] M. R. Mehrjou, N. Mariun, M. Karami, S. B. M. Noor, S. Zolfaghari, N. Mison, M. Z. A. A. Kadir, M. A. M. Radzi, and M. H. Marhaban, "Wavelet-Based

Analysis of MCSA for Fault Detection in Electrical Machine,” in *Wavelet Transform and Some of Its Real-World Applications*, InTech, 2015.



APPENDICES

A. Wavelet Packet Signature Analysis MATLAB Command Line

```
clear all;close all;clc;

%% Simple sinusoids signal

f=50;

t=0:(1/2000):(1-(1/2000));

y=10*sin(2*pi*f*t);

%% Wavelet Packet Transform

Level=5;

wpt=wpdec(y,Level+1,'db44');% wavelet packet tree

for node = 0:2^Level;

    data = wprcoef(wpt,[Level node]);% wavelet packet

Reconstructed coefficients

    FFT;

    MAX= max(AMPLITUDEmat(:,2));

    [m n]=find( AMPLITUDEmat(:,2)==MAX);

    MaxFund(node+1,1)= AMPLITUDEmat(m,1);

    MaxFund(node+1,2)= AMPLITUDEmat(m,2);

End

MAX2= max(MaxFund(:,2));

[p q]=find(MaxFund(:,2)==MAX2);

clear node

node=p-1;

%% Plot
```

```

f=figure;
subplot(1,3,1)
plot(y);
title('Original Signal')
%% Wavelet Packet Transform
wpt = wptdec(y,Level+1,'db44');
data = wprcoef(wpt, [Level node]);
subplot(1,3,2)
plot(data);
title('Reconstructed Signal')
FFT %%%%%%%%%%%%%%%
samptime = (1/2000);
N2 = length(data);
[FFTData, amp, ang, freq, NFFT] = fft_signal(data,samptime);
x = NFFT/2+1;
amp=amp';
for j = 0:1;
for i = 1:x;
    AMPLITUDEmat(i,1) = freq(i,1);
    AMPLITUDEmat(i,j+1) = amp(i,1);
End
End
for k=1:x
    plotAm(k,1)=AMPLITUDEmat(k,1);
    plotAm(k,2)=AMPLITUDEmat(k,2);

```

End

```
subplot(1,3,3)
```

```
plot (plotAm(:,1),plotAm(:,2));
```

```
title('FFT')
```

```
xlabel('Frequency (Hz)')
```

```
ylabel('Amplitued (A)')
```

```
clear AMPLITUDEmat FFTD at a MAXMAX2 Max Fund N2 NFFT...
```

```
amp ang f data freq i j k m n p plot Amq samptimet wpt  
x
```

```
fft_signal%%%%%%%%%
```

```
function [FFTDData, amp, ang, freq, NFFT]=fft_signal(data,samptime)
```

```
options.sampFreq = 1/samptime;
```

```
N = 2^(nextpow2(length(data)));
```

```
N2 = length(data);
```

```
FFTDData = fft(data,N);
```

```
amp = abs(FFTDData) * 2/N2;
```

```
ang = angle(FFTDData);
```

```
NumUniquePts = ceil((N+1)/2);
```

```
amp = amp(1:NumUniquePts);
```

```
freq=(0:NumUniquePts-1) / (NumUniquePts)*(options.sampFreq/2) ;
```

```
NFFT=N;
```

End

B. Mother Wavelet MATLAB Command Line

```
close all;
```

```
clear all;
```

```

clc;

%% Load Data

% Stator current signal for different loads,as an example NoLoad condition

load Hnoload1 %Healthy No Load condition, it is also
tested for F1NoLoad, F2NoLoad, F3NoLoad

y = Hnoload1;

load MotherwaveletPacket

Level= 5; %(5,1)[31.25-62.5]

Depth= 1;

%Wavelet packet calculation based on different mother wavelet

for motherorder = 1:82;

    wpt=wpdec(y,Level,MotherwaveletPacket{1,motherorder}); % WPD of signal y with
level and mother wavelet

    cfs = wpcoef(wpt,[Level Depth]);

    StD=std(cfs);% Standard Deviation of WPD coefficients

    MW(motherorder,1) = MotherwaveletPacket(1,motherorder);

    MW{motherorder,2} = num2str(StD);

End

S1 = char(MW{:,2});

clear ft Frequency Sampling y mother order

```

C. Feature Extraction MATLAB Command Line

```

clear all;close all;clc;

%% Stator current signal for different loads,as an example NoLoad condition

load F1NoLoad;% 1BRB of No Load condition, it is also
tested for HNoLoad, F2NoLoad, F3NoLoad

```

```

for i=1:20;

    y = F1NoLoad(:,i);

    wpt = wpdec(y,11,'db44');

    cfs = wpccoef(wpt,[9 21]); %wavelet packet coefficients

    X = cfs;

%% Wavelet statistical parameters

RMS = rms(X);% Root-mean-squares

RSSQ = rssq(X);% Root-sum-of-squares

KURTOSIS = kurtosis(X);

SKEWNESS = skewness(X);

Mean = mean(X);

PtoP = peak2peak(X);

PtoRMS = peak2rms(X);% CrestFactor

LogDectect = exp(mean(log(abs(X))));

PAPR = ((max(X))^2)/((rms(X))^2);% peak-to-average power ratio(dB)

ShapeFactor = rms(X)/mean(X);

ImpulseFactor = max(abs(X))/mean(X);

Energy = sum(X.^2);

StD = std(X); %Standard Deviation

Moment = moment(X,6); %sixth order centrl moment

ResultTime(i,1) = RMS;

ResultTime(i,2) = RSSQ;

ResultTime(i,3) = KURTOSIS;

ResultTime(i,4) = SKEWNESS;

ResultTime(i,5) = Mean;

```

```

ResultTime(i,6) = PtoP;
ResultTime(i,7) = PtoRMS;
ResultTime(i,8) = LogDectect;
ResultTime(i,9) = PAPR;
ResultTime(i,10) = ShapeFactor;
ResultTime(i,11) = ImpulseFactor;
ResultTime(i,12) = Energy;
ResultTime(i,13) = StD;
ResultTime(i,14) = Moment;

```

```
i=i+1
```

Ed

```

clear RMS RSSQ KURTOSIS SKEWNESS Mean...
PtoP PtoRMS PAPR ShapeFactor ImpulseFactor...
Root X Margin Factor LogDectect Energy StD Moment

```

D. MultiLayer Perceptron NN-based Classifier MATLAB Command Line

```

clear all;close all;clc;

%% Load Data
load NN_Input; %is defined based on the best combination of features in various loads
Inputs = NN_Input';
load fault_type;

%% Define training set
in=[];

for i=1:15

    temp=[Inputs(i,:);Inputs(20+i,:);Inputs(40+i,:);Inputs(60+i,:)];

```

```

in=[in temp];

End

%% Define targets
A =[0.1 0.1 0.1 0.9];
B =[0.1 0.1 0.9 0.1];
C =[0.1 0.9 0.1 0.1];
D =[0.9 0.1 0.1 0.1];
temp = [repmat(A,1,1) repmat(B,1,1) repmat(C,1,1) repmat(D,1,1)];
Target=repmat(temp,[1 15]);

%% Create a Fitting Network
hiddenLayerSize = 13;
TF={'tansig','purelin'};
trainFcn='trainlm'; %Levenberg-Marquardt backpropagation.
net.performFcn = 'msereg'; %'msereg' improve generalization
net = feedforwardnet(hiddenLayerSize,trainFcn);

CVO = cvpartition(fault_type,'Leaveout');%Create cross validation partition for data
err = zeros(CVO.NumTestSets,1);
cp = classperf(fault_type);%Evaluate performance of classifier
single_error = zeros(1,CVO.NumTestSets);

numNN = 10;%Multiple Neural Network
nets = cell(1,numNN);

for i = 1:numNN

    disp(['Training ' num2str(i) '/' num2str(numNN)])

for j = 1:CVO.NumTestSets

```



```
%% Train the Network
```

```
trIdx = CVO.training(j); % training Index
```

```
trIdx = trIdx';
```

```
trainInputs = in(:,trIdx);
```

```
trainTargets = Target(:,trIdx);
```

```
nets{i} = train (net, trainInputs,trainTargets);
```

```
%% Test the Network
```

```
teIdx = CVO.test(j); % test Index
```

```
teIdx = teIdx';
```

```
testInputs = in(:,teIdx);
```

```
%% Classification
```

```
class = classify(in(:,teIdx)',in(:,trIdx)',fault_type(trIdx,:));
```

```
classperf(cp,class,teIdx);% To modify properties
```

```
err(j) = sum(~strcmp(class,fault_type(teIdx,:)));
```

```
single_error(1,j) = cp.ErrorRate;
```

```
single_correct(1,j)= cp.CorrectRate;
```

```
end
```

```
end
```

```
get(cp);
```

```
cp.ErrorRate;
```

```
cp.CorrectRate;
```

```
mean_error = mean(single_error);
```

```
mean_correct = mean(single_correct);
```

```
STD_correct = sqrt(var(single_correct));
```

```
%% TEST and Evaluate the Network with TEST DATA
```

```
%Load Test Data
```

```
in_ts=[];
```

```
perfs = zeros(1,numNN);
```

```
y2Total = 0;
```

```
for i=1:5
```

```
    temp_ts=[Inputs(15+i,:);Inputs(35+i,:);Inputs(55+i,:);Inputs(75+i,:)]';  
    in_ts=[in_ts temp_ts];
```

```
End
```

```
targets= repmat(temp,[1 5]);
```

```
for i=1:numNN
```

```
    neti = nets{i};
```

```
    Tsoutputs = neti(in_ts);
```

```
    perfs(i) = mse(neti,targets,Tsoutputs);
```

```
    y2Total = y2Total + Tsoutputs;
```

```
    PlotResults(targets(:),Tsoutputs(:),'Test Data');
```

```
    saveas(subplot(2,2,4),'Test Data.png')
```

```
End
```

```
y2AverageOutput = y2Total / numNN;
```

```
perfAveragedOutputs = mse(nets{1},targets,y2AverageOutput);
```

```
Mean_iter=[cp.ErrorRate cp.CorrectRate mean_error mean_correct STD_error  
perfAveragedOutputs];
```

```
save Mean_iter;
```

```
result=[targets; y2AverageOutput]';
```

```
save result
```

```

%% Test Correct class

testCor = 100 * length(find(targets.*y2AverageOutput > 0)) / length(targets);

fprintf('TestCorrect class = %.1f %%\n',testCor/4)

%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%%

PlotResults

function PlotResults(t,y,name)

figure;

% t and y
subplot(2,2,1);
plot(y,'k');
hold on;
plot(t,'r');
legend('Outputs','Targets');
title(name);

% Correlation Plot
subplot(2,2,2);
plot(t,y,'ko');
hold on;

xmin=min(min(t),min(y));
xmax=max(max(t),max(y));
plot([xmin xmax],[xmin xmax],'b','LineWidth',2);

R=corr(t,'y');

%title(['R = ' num2str(R)]);

% e
subplot(2,2,3);

```

```
e=t-y;
plot(e,'b');
legend('Error');
MSE=mean(e.^2);
RMSE=sqrt(MSE);
title(['MSE = ' num2str(MSE) ', RMSE = ' num2str(RMSE)]);

subplot(2,2,4);
histfit(e,50);
eMean=mean(e);
eStd=std(e);
title(['\mu = ' num2str(eMean) ', \sigma = ' num2str(eStd)]);
```

End

BIODATA OF STUDENT

Sahar Zolfaghari was born in Isfahan, Iran. She got his B.S. degree in Electrical and Electronic Engineering from Islamic Azad University, Najaf Abad branch. After graduating, she started to work as Instrumentation Engineering on Oil and Gas field projects of the PetroSanat Company, Iran for about 5 years. In 2013, she joined Universiti Putra Malaysia to continue her study and she is currently pursuing Master of Science in Department of Electrical and Electronic Engineering.



LIST OF PUBLICATIONS

- Zolfaghari, Sahar, S.B.Mohd Noor, Norman Mariun, Mohammad Hamiruce Marhaban, Mohammad Rezazadeh Mehrjou, and Mahdi Karami. "Broken rotor bar detection of induction machine using wavelet packet coefficient-related features." *In Research and Development (SCORed), 2014 IEEE Student Conference on*, pp. 1-5. IEEE, 2014.
- S. Zolfaghari, et al, "Wavelet-Based Analysis of MCSA for Fault Detection in Electrical Machine," *in Wavelet Transform and Some of Its Real-World Applications, InTech, 2015*





UNIVERSITI PUTRA MALAYSIA

STATUS CONFIRMATION FOR THESIS / PROJECT REPORT AND COPYRIGHT

ACADEMIC SESSION: _____

TITLE OF THESIS / PROJECT REPORT:

INTELLIGENT FAULT DIAGNOSIS FOR BROKEN ROTOR BAR USING WAVELET PACKET SIGNATURE ANALYSIS

NAME OF STUDENT : SAHAR ZOLFAGHARI

I acknowledge that the copyright and other intellectual property in the thesis/project report belonged to Universiti Putra Malaysia and I agree to allow this thesis/project report to be placed at the library under the following terms:

1. This thesis/project report is the property of Universiti Putra Malaysia.
2. The library of Universiti Putra Malaysia has the right to make copies for educational purposes only.
3. The library of Universiti Putra Malaysia is allowed to make copies of this thesis for academic exchange.

I declare that this thesis is classified as :

*Please tick (✓)

CONFIDENTIAL

(Contain confidential information under Official Secret Act 1972).

RESTRICTED

(Contains restricted information as specified by the organization/institution where research was done).

OPEN ACCESS

I agree that my thesis/project report to be published as hard copy or online open access.

This thesis is submitted for :

PATENT

Embargo from _____ until _____
(date) (date)

Approved by:

(Signature of Student)
New IC No/ Passport No.:

Date :

(Signature of Chairman of Supervisory Committee)
Name:

Date :

[Note : If the thesis is CONFIDENTIAL or RESTRICTED, please attach with the letter from the organization/institution with period and reasons for confidentially or restricted.]