

UNIVERSITI PUTRA MALAYSIA

THREE-LEVEL UNIVERSAL ELECTRIC VEHICLE CHARGER BASED ON VOLTAGE-ORIENTED CONTROL AND SINUSOIDAL PULSE-WIDTH MODULATION

ALI SAADON MTAIR AL-OGAILI

FK 2018 36



THREE-LEVEL UNIVERSAL ELECTRIC VEHICLE CHARGER BASED ON VOLTAGE-ORIENTED CONTROL AND SINUSOIDAL PULSE-WIDTH MODULATION



ALI SAADON MTAIR AL-OGAILI

Thesis Submitted to the School of Graduate Studies, Universiti Putra Malaysia, in Fulfillment of the Requirements for the Degree of Doctor of Philosophy

December 2017

COPYRIGHT

All material contained within the thesis, including without limitation text, logos, icons, photographs and all other artwork, is copyright material of Universiti Putra Malaysia unless otherwise stated. Use may be made of any material contained within the thesis for non-commercial purposes from the copyright holder. Commercial use of material may only be made with the express, prior, written permission of Universiti Putra Malaysia.

Copyright © Universiti Putra Malaysia.



DEDICATION

I would like to dedicate this thesis to my father and my mother for their endless love, support, and encouragement. Thank you both for giving me the strength to reach for the stars and chase my dreams. My uncle, Abduljabbar, My brother, Mohammed Saadon, My sister, Menar, and my best friend, Hashim; are worthy of deserving my wholehearted thanks as well.



Abstract of thesis presented to the Senate of Universiti Putra Malaysia in fulfillment of the requirement for the degree of Doctor of Philosophy

THREE-LEVEL UNIVERSAL ELECTRIC VEHICLE CHARGER BASED ON VOLTAGE-ORIENTED CONTROL AND SINUSOIDAL PULSE-WIDTH MODULATION

By

ALI SAADON MTAIR AL-OGAILI

December 2017

Chairman: Ishak Bin Aris, PhDFaculty: Engineering

The electric vehicle (EV) could be one of the solutions to address the issues of the environmental pollution and the depletion problems of non-renewable energy resources. EVs, which are energized by a battery storage system, are becoming attractive because it keeps the environment clean and friendly. The battery charger of EV needs to have a sufficient performance by a unity power factor and zero harmonic distortion.

This work presents the design process of a universal EV charger. The proposed charger is able to provide a controllable and constant charging voltage for a variety of EVs. It is composed of three levels of charging: (1) 650 V/100 A DC for bus or lorry, (2) single-phase 120 V/16 A AC for motorcycle, and (3) three-phase 240 V/60 A for saloon car battery charging.

The power system of this work consists of two converters: (1) the three-phase pulsewidth modulated (PWM) of a bridge rectifier with an output of 650 V DC unregulated voltage, and (2) the converter is for the three-phase DC–DC converter.

To satisfy the voltage control and the isolation between Grid To Vehicle (G2V), a three-phase transformer has been exploited within the DC–DC converter. The primary output circuit achieved the charge Levels 1 and 2, while the whole circuit output can charge Level 3 or the DC charge. For efficient and secure battery charging, voltage-oriented control (VOC) technique is proposed.

A study is conducted to investigate the use of a three-phase converter unidirectional EV battery charger. In the proposed design, the reactive and unstable active currents can be counteracted by the PWM rectifier via the input and output filters and PFC.

The current controller and DC-link voltage controller have been designed using a technique called internal model control. The unity power factor for the PWM-based rectifier and SPWM are designed and evaluated using MATLAB/Simulink 2010a block sets. The total harmonic distortion (THD) for the input current is recorded as less than 0.85 %. A prototype and simulation results are used to validate the proposed EV charger to ensure its robustness, accuracy, and application.



Abstrak tesis yang dikemukakan kepada Senat Universiti Putra Malaysia sebagai memenuhi keperluan untuk ijazah Doktor Falsafah

PENGECAS KENDERAAN ELEKTRIK SEMESTA TIGA ARAS BERDASARKAN KAWALAN BERHALAAN VOLTAN DAN MODULASI LEBAR DENYUT BENTUK SINUS

Oleh

ALI SAADON MTAIR AL-OGAILI

Disember 2017

Pengerusi : Ishak Bin Aris, PhD Fakulti : Kejuruteraan

Kenderaan elektrik (EV) boleh menjadi salah satu penyelesaian untuk menangani isu-isu pencemaran alam sekitar dan masalah kesusutan tenaga. EV yang ditenagakan oleh sistem storan bateri, menjadi menarik kerana ia menjadikan alam sekitar bersih. Pengecas bateri EV perlu mempunyai prestasi yang mencukupi dengan faktor kuasa unit dan gangguan sifar herotan harmonik.

Kerja ini membentangkan proses reka bentuk pengecas EV semesta, Pengecas yang dicadangkan dapat menyediakan voltan pengecasan terkawal dan berterusan untuk pelbagai EV, yang terdiri daripada tiga tahap pengisian iaitu 650 V/100 A DC untuk bas atau lori, fasa tunggal 120 V/16 A AC untuk motosikal, dan tiga fasa 240 V / 60 A untuk pengecasan bateri kereta saloon.

Sistem kuasa kerja ini terdiri daripada dua penukar; pertama, adalah untuk modul penerus jambatan termodulat lebar denyut (PWM) tiga fasa dengan keluaran 650 V voltan DC tak diatur, manakala penukar kedua adalah untuk penukar DC-DC tiga fasa.

Untuk memenuhi kawalan voltan dan pengasingan antara Grid ke Kenderaan (G2V), pengubah tiga fasa telah dieksploitasi dalam penukar DC-DC. Litar keluaran utama mencapai cas Tahap 1 dan 2, manakala keluaran keseluruhan litar boleh mengecas Tahap 3 atau cas DC. Untuk pengecasan bateri yang cekap dan selamat, teknik kawalan berorientasikan voltan (VOC) telah dicadangkan.Satu kajian telah dijalankan dengan menyiasat penggunaan penukar tiga fasa pengecas bateri EV satu

arah tiga fasa untuk digunakan di stesen pengecasan. Dalam reka bentuk yang dicadangkan, arus regangan dan arus aktif yang tidak stabil boleh diatasi oleh penerus PWM melalui penapis masukan dan keluaran dan PFC.

Pengawal arus dan pengawal voltan DC-link telah direka menggunakan teknik yang dikenali sebagai Kawalan Model Dalaman. Faktor kuasa unit untuk penerus berasaskan PWM dan SPWM direka dan dinilai menggunakan set blok MATLAB/Simulink 2010a. Jumlah herotan harmonik (THD) untuk arus masukan adalah kurang daripada 0.85 %. Keputusan prototaip dan simulasi mengesahkan bahawa pengecas EV yang dicadangkan adalah kukuh, tepat dan boleh guna.



ACKNOWLEDGEMENTS

First and foremost, praises and thanks to the God, for his showers of blessings throughout my research work to complete the research successfully.

I would like to sincerely thank my supervisor, Prof. Dr. Ishak Bin Aris, for his guidance and support throughout this study period, and especially for his confidence in me. I have been extremely lucky to have a supervisor who cared so much about my work, and who responded to my questions and queries so promptly. Without his inspirational guidance, his enthusiasm, encouragements, and selfless help, I could never finish my doctoral work. For me, he is not only a teacher, but also a lifetime friend and an advisor.

I would like to extend my special thanks to the members of my advisory committee, Assoc. Prof. Ir. Dr. Mohammad Lutfi Bin Othman, Dr. Norhafiz Bin Azis, and Prof. Dr. Dino Isa for their guidance and helpful discussions.

I would like to thank all lecturers at the Department of Electrical and Electronic Engineering, Universiti Putra Malaysia (UPM) who supported and helped me during my studies. I greatly appreciate the Department of Electrical and Electronic Engineering, Faculty of Engineering Universiti Putra Malaysia, for their contribution in facilitating smoothly successful completion of the research work alongside with other co-researchers in the Centre. This thesis was submitted to the Senate of University Putra Malaysia and has been accepted as fulfillment of the requirement for the degree of Doctor of Philosophy. The members of the Supervisory Committee were as follows:

Ishak Bin Aris, PhD Professor

Faculty of Engineering Universiti Putra Malaysia (Chairman)

Mohammad Lutfi Bin Othman, PhD

Associate Professor, Ir Faculty of Engineering Universiti Putra Malaysia (Member)

Norhafiz Bin Azis, PhD

Senior Lecturer Faculty of Engineering Universiti Putra Malaysia (Member)

Dino Isa, PhD

Professor Faculty of Engineering University of Nottingham Malaysia Campus (Member)

ROBIAH BINTI YUNUS, PhD

Professor and Dean School of Graduate Studies Universiti Putra Malaysia

Date:

Declaration by graduate student

I hereby confirm that:

- this thesis is my original work;
- quotations, illustrations and citations have been duly referenced;
- this thesis has not been submitted previously or concurrently for any other degree at any other institutions;
- intellectual properties from the thesis and copyright of the thesis are fully owned by Universiti Putra Malaysia, as according to the University Putra Malaysia (Research) Rules 2012;
- written permission must be obtained from supervisor and the office of Deputy Vice-Chancellor (Research and Innovation) before thesis is published (in form of written, printed or in electronic form) including books, journals, modules, proceedings, popular writings, seminar papers, manuscripts, posters, reports, lecture notes, learning modules or any other materials as stated in Universiti Putra Malaysia (Research) Rules 2012;
- there is no plagiarism or data falsification in the thesis, and scholarly integrity is upheld as according to the University Putra Malaysia (Graduate Studies) Rules 2003 (Revision 2012-2013) and the University Putra Malaysia (Research) Rules 2012. The thesis has undergone plagiarism detection software.

Signature :	Date :	
0		

Name and Matric No: Ali Saadon Mtair Al-Ogaili, GS34259

Declaration by Members of Supervisory Committee

This is to confirm that:

- the research conducted and the writing of the thesis was under our supervision;
- supervision responsibilities as stated in the Universiti Putra Malaysia (Graduate Studies) Rules 2003 (Revision 2012 2013) are adhered to.



Professor Dr. Dino Isa

Committee:

TABLE OF CONTENTS

			-			
ABSTI	RACT		i			
ABSTH	RAK		iii			
ACKN	OWL	EDGEMENTS	v			
APPROVAL						
DECLARATION						
LIST (OF TA	BLES	xiii			
LIST (OF FIC	JURES	xiv			
LIST (OF SY	MBOLS	xviii			
LIST (OF AB	BREVIATIONS	xix			
СНАР	TER					
1	INTR	ODUCTION	1			
	1.1	Background	1			
		1.1.1 Types of Vehicles in Use Today	3			
		1.1.2 On / Off Board Charging System	4			
		1.1.3 Overview about the Planning of EV Charging Facilitates	5			
		1.1.4 Charger Power Levels and Infrastructure	6			
		1.1.5 Level 1 Charging	6			
		1.1.6 Level 2 Charging	7			
		1.1.7 Level 3 Charging	7			
		1.1.8 Charging Features and Infrastructures of Some				
		Manufactured PHEVs AND EVs	7			
		1.1.9 Typical Battery Charging Profile	10			
	1.2	Problem statement	11			
	1.3	Aim and Objectives	12			
	1.4	Scope and Limitations of Work	12			
	1.5	Thesis Layout	13			
2	LITEI	RATURE REVIEW	14			
	2.1	Introduction	14			
	2.2	Electric Vehicle Supply Equipment (EVSE) Technology	16			
		2.2.1 Basic EVSE Components	16			
		2.2.2 Electric Vehicle Connector	16			
		2.2.3 Electric Vehicle Inlet	16			
		2.2.4 Battery Charger	16			
	2.3	Charger Requirements	17			
	2.4	Charging Times	19			
	2.5	Power Converter of Electric Vehicle Charger	22			
		2.5.1 Hysteresis control	22			
		2.5.1.1 Current Control	23			
		2.5.1.2 Hysteric Direct Torque Control (DTC)	23			
		2.5.1.3 Direct Power Control (DPC)	25			

	2.5.2	Linear Control	27
		2.5.2.1 Field–Oriented Control	27
		2.5.2.2 Voltage-Oriented Control	30
	2.5.3	Sliding Mode Control	33
		2.5.3.1 Sliding Mode Current Controller	34
		2.5.3.2 Sliding Mode Voltage Control	35
	2.5.4	Predictive Deadbeat Control	36
	2.011	2.5.4.1 Deadbeat Control	36
		2.5.4.2 Model Predictive Control	36
		2.5.4.3 Generalized Predictive Control	37
	255	Artificial Intelligence	38
	2.3.5	2 5 5 1 Fuzzy Logic Controller	38
		2.5.5.1 Neural Network (NN) and Fuzzy Control Method	ds 40
26	Volta	ve-Oriented Control (VOC)	40
2.0	Pervic	us Important Work on Electric Vehicle Charger	41
2.1	271	Unidirectional Chargers	<u>4</u> 1
	2.7.1	Bidirectional Chargers	$\frac{1}{12}$
28	Summ	Didirectional Chargers	
2.8	Summ		+/
3 MF'	гноро	LOCA	18
3 1	Introd	uction	-10 /18
3.1	Mode	lling of Electric Vehicle Charger	51
3.2	Mode	Modeling the System by Using Voltage-oriented Control (VOC)	
5.5		Algorithm 54	
	3 3 1	Modeling of Charging System	55
	3.3.1	Decoupled Controller Using VOC	56
	3.3.2	Current Controllers of the Inner Current	56
2.4	Dhasa	Locked Loop (PLL)	50 61
3.4	Simul	Simulation Work	
3.6 Experime		imontal Implementation	70
5.0	2.6.1	Step by Step of Inductors Eabrication	76
	5.0.1	3.6.1.1 Exprises	76
		3.6.1.2 Copper Coil	70
		3.6.1.2 Copper Coll 3.6.1.2 Formite Toroid Coloulation	70
	262	Three phase DWM Destifier and Three phase SDWM	11
	5.0.2	Inter-phase F wive Recurrent and Three-phase SF wive	70
	363	IGBT Transistors	70 80
	3.0.3	Gate Driver Circuits	80
	265	Softing of Dood Time	00 Q1
	266	Veltage and Current Sensors	01 02
	3.0.0	Implementation of Control Algorithms in Digital Signal	02
	5.0.7	Drocessor (DSD)	02
27	Summ	FIOCESSOI (DSF)	03 05
5.7	Summ	iai y	05
/ DEG	ТП ТС А	ND DISCUSSION	86
	Introd		00 86
4.1 4.2	4.1 Introduction		
4.2		Lavel 1 Charging	00 97
	4.4.1		07

		4.2.2 Level 2 Charging	89
		4.2.3 Level 3 Charging	95
	4.3	Experimental Results	101
		4.3.1 Stage One: Laboratory prototype of low power charger	101
		4.3.2 Stage Two: Laboratory prototype of medium power	
		charger	112
	4.4	Results Verification and Comparison	118
	4.5	Benchmarking	119
	4.6	Summary	120
5	CON	CLUSION AND RECOMMENDATIONS FOR FUTURE	
	WOI	RK	122
	5.1	Overall Conclusion	122
	5.2	Contributions of Work	123
	5.3	Recommendations for Future Work	123
REF	EREN		124
APP	ENDIC	ES	138
BIO	DATA	OF STUDENT	150
LIST	Г OF Pl	JBLICATIONS	151

C

LIST OF TABLES

Table		Page
1.1	Charging characteristic and infrastructures of some manufactured PHEV and EVS	rs 9
2.1	Typical EV battery capacities and normalized charging times	17
2.2	The classifications of charging time	20
2.3	Switching table	25
2.4	Bidirectional and unidirectional charger topologies and comparisons	44
2.5	Comparison of bidirectional and unidirectional charger infrastructure	45
4.1	Parameter specifications for Level 1 charging	87
4.2	Parameter specifications for Level 2 charging	90
4.3	Parameter specifications for Level 3 charging	96
4.4	THD results of simulation and experimental work	119
4.5	The performances of proposed work with pervious work of charging systems	120

LIST OF FIGURES

	Figure		
	1.1	Global CO2 emission reduction	1
	1.2	Malaysia automotive technology projection (2013-2025)	2
	1.3	Block diagram of off-board charger	4
	1.4	Figure 1.4: Block diagram of on-board charger	5
	 Typical charging profile of Li-ion cell Typical battery charger (AC-DC Converter) 		11
			14
	2.2	Commonly applied control method	22
	2.3	Basic structure configuration of DTC	24
	2.4	Typical control structure of DPC	27
	2.5 The vector diagram of FOC principle2.6 Fundamental design of FOC for AC motor		29
			30
	2.7 Voltage-oriented control of PWM rectifier: (a) Vector layout (b) Overall control structure		
	2.8	Phase plot for (a) ideal SM (b) actual SM	33
	2.9	2.9 Control scheme of sliding mode controller	
	2.10	Control structure of GPC	38
	2.11	Overview of fuzzy logic control process	39
	2.12	General topology of unidirectional and bidirectional charger	41
	2.13	EV charger: (a) Non-isolated bidirectional two-quadrant charger and (b) Isolated bidirectional dual active bridge charger	43
	2.14	Integrated charger using multi-mode electric vehicle charging station	46
	3.1	Flowchart of the proposed methodology	49
	3.2	Three-phase PWM bridge rectifier of proposed charger for electric bus with VOC control algorithm	52
	3.3	Circuit configuration of three levels battery charging circuit	53

	3.4	Three PI controllers in VOC algorithm	55
	3.5	Modeling circuit of the grid-connected rectifier	57
	3.6	Park transformation	58
	3.7	Phasor diagram of Park transformation	59
	3.8	The equivalent Laplace transform of rectifier connected to grid	60
	3.9	Block configuration for active power P and reactive power Q computations based on Clarke and Park transform	61
	3.10	Simulation model of battery charger (a) overall control configuration, (b) details of Supply Voltage and VOC Rectifier (c) details of SPWM Inverter, LC filter, Isolation transformer, Bridge Rectifier and Battery, and (d) control algorithms	67
	3.11	Overall circuit configuration of battery charging circuit with the control system	68
	3.12	Control signal generator for SPWM controller	69
	3.13	Three-phase sinusoidal PWM inverter	69
	3.14	Control process flow of VOC and SPWM controller	71
	3.15	Experimental setup for low voltage test (a) three-phase programmable AC source, VOC rectifier and SPWM inverter, (b) SPWM inverter, resistor load and battery, (c) DC supply, three-phase VOC rectifier, DSP and sensors, (d) three-phase SPWM inverter, LC filter and rectifier, and (e) overall charger circuit	74
	3.16	Experimental setup for medium voltage test (a) overall circuit of VOC rectifier and SPWM inverter, (b) details of three levels charger circuits, and (c) 12 V Lead-acid Battery	76
	3.17	The dimension of inductor	78
	3.18	Simulink model for DSP implementation (a) VOC control algorithm and (b) SPWM control algorithm	79
	3.19	Gate driver circuit: (a) block diagram of gate driver circuit and (b) Hardware design of gate driver circuit	81
	3.20	One arm scheme diagram of VOC rectifier / SPWM inverter	81
	3.21	Current sensor: (a) schematic diagram and (b) hardware circuit	82
	3.22	Voltage sensor: (a) schematic diagram and (b) hardware circuit	83

	3.23	Pin configuration of DSP for control algorithm implementation	
	4.1	Reference voltage of phase A	86
4.2 The output current of the charger for Level 1 charging		The output current of the charger for Level 1 charging	88
	4.3 The output voltage of the charger for Level 1 charging		89
	4.4	The input voltage waveform phase AThe input current waveform phase A	
	4.5		
	4.6	The simulation output current waveform of the SPWM inverter before auto transformer and the corresponding FFT analysis: (a) phase A (b) phase B and (c) phase C	92
	4.7	The simulation result and the FFT analysis of three-phase input current after transformer : (a) phase A, (b) phase B, and (c) phase C	93
	4.8	The simulation waveform and the FFT analysis of phase A output voltage	94
	 4.9 The simulation waveform of the input current for (a) phase A, (b) phase B, and (c) phase C 4.10 The simulation result of the input voltage for (a) phase A, (b) phase and (c) phase C 		97
			98
	4.11	 The output DC-link voltage of Level 3 charging for (a) Nickel Metal battery, (b) Lithium-ion battery, and (c) Lead Acid batteries The output DC current of Level 3 charging for (a) Nickel Metal battery, (b) Lithium-ion battery, and (c) Lead Acid batteries 	
	4.12		
	4.13 Input AC voltage and output DC voltage of VOC rectifier: (a) reference voltage is 5 V and (b) reference voltage is 10 V (c) THD for input current		102
	4.14	Measurement result in different view for the three-phase voltage of SPWM inverter with input voltage of 20 V	103
	4.15	Measurement three-phase SPWM voltage waveform and the waveform of phase A current before LC filtering (captured using Average function of oscilloscope)	105
	4.16	Output DC current and DC voltage of the charger with resistive load and without capacitive filter	106
	4.17	Output current and voltage of the charger with resistive load and without LC filter	106

4.18	Measurements of output voltages and currents of SPWM inverter without LC filtering (captured using Average function of oscilloscope) for (a) phase A, (b) phase B and (c) phase C	108
4.19	Measurements of the output voltages and currents of SPWM inverter with LC filtering for (a) phase A, (b) phase B and (c) phase C	109
4.20	THD measurements of the output currents of SPWM inverter with LC filtering for (a) phase A, (b) phase B and (c) phase C	110
4.21	Measurements of the voltages and the currents for the low power prototype charger: (a) phase A input voltage, current and output DC voltage and current, (b) phase A input voltage, reference voltage and input current (c) THD value of input current	111
4.22	Experimental waveforms (a) Phase A input voltage, input current and (b) THD of input current for the charger	113
4.23	Input phase voltage, output phase voltage and output phase-to-phase voltage of SPWM inverter without LC filter	114
4.24	The input phase current, input phase voltage of the charger of phase A and output DC-link voltage	114
4.25	The input phase current, input phase voltage of the charger, output DC current and output DC-link voltage of the charger: (a) Phase A, (b) Phase B and (c) Phase C	115
4.26	Phase A input voltage, input current and THD of input current for the charger	116
4.27	Phase A input voltage, output voltage and current of the charger after LC filter	117
A1	Current control with inner decoupling loop	140
A2	Block diagram of IMC structure	141
A3	The IMC rearranged as the "classical" control system structure	143
A4	Voltage controller for regulating dc link voltage	145

LIST OF SYMBOLS

	а	Phase A
	b	Phase B
	С	Phase C
	d	D Frame Representation
	C _{dc}	DC-link Capacitor
	i _s	Source Current
		Inductor
	P	Active Power
	Q	Reactive Power
	q	Q Frame Representation
	R	Resistor
	S	Switching Signal
	Т	Torque
	V _{dc}	DC-link Capacitor Voltage
	vs	Source Voltage
	θ	Reference Angle
	α	Alpha Domain Representation
	β	Beta Domain Representation
	0	Zero Domain / Frame Representation
	ψ_R	Amplitude of rotor flux
	$\overline{\Psi_r}$	Rotor flux
	$\omega_{\lambda r}$	Rotor flux angular velocity

LIST OF ABBREVIATIONS

AC	Alternating Current
ADC	Analog-to-Digital Converter
BEV	Battery Electric Vehicle
BMS	Battery Management System
CC	Constant Current
CCS	Code Composer Studio
CV	Constant Voltage
DC	Direct current
DSP	Digital Signal Processor
DPC	Direct Power Control
DTC	Direct Torque Control
EV	Electric Vehicle
EVSE	Electric Vehicle Supply Equipment
FLC	Fuzzy Logic Controller
FOC	Field-oriented Control
GPC	Generalized Predictive Control
GPIO	General Purpose Input / Output
G2V	Grid to Vehicle
IC	Integrated Circuit
ICE	Internal Combustion Engine
IGBT	Insulated Gate Bipolar Transistor
IMC	Internal Model Control
IPM	Intelligent Power Model
KVL	Kirchhoff's Voltage Law

	MIMO	Multi-input Multi-output
	MPC	Model Predictive Control
	NN	Neural Network
	NNGVE	Neural Network Grid-Voltage Estimator
	NNIPI	Neural Network Interfacing Parameters Identifier
	SISO	Single Input Single Output
	SM	Sliding Mode
:	SPWM	Sinusoidal Pulse-width Modulation
:	SVPWM	Space Vector Pulse-width Modulation
,	THD	Total Harmonic Distortion
	PEV	Plug-in Electric Vehicle
	PFC	Power Factor Correction
	PHEV	Plug-in Hybrid Electric Vehicle
	Р	Proportional
	PI	Proportional-Integral
	PID	Proportional-Integral-Derivative
	PLL	Phase-locked loop
	PWM	Pulse-width Modulation
	VOC	Voltage-oriented Control
(VSS	Variable Structured Systems
	VSI	Voltage Source Inverter
G	V2G	Vehicle to Grid

CHAPTER 1

INTRODUCTION

1.1 Background

There is a growing concern on the issues of the non-renewable energy resources depletion and other environmental issues all over the world. The concerns are largely focusing on replacing the fuel based automobiles with electric vehicles (EVs) with no emission and low noise. Motorbike vehicles - salon cars and vans - generate about 15% of the EU's emissions of CO_2 as shown in Figure 1.1. Consequently, various countries have taken their own initiatives in developing their own EV industry, aiming to de-carbonize their transport sectors. In setting the timeframe for the Malaysia Automotive Technology Roadmap (MART), the most appropriate policy adopted is the forecasted advancement of the Energy Efficient Vehicle (EEV) from Internal Combustion Engine (ICE) to Electric Vehicles (EV) as description in Figure 1.2. For instance, China has brought forward a conservative development plan that aimed to increase number of EVs ownership to five millions by 2020 [1]. However, the availability and convenient of EVs charging infrastructure are the key factors that affects the future development and popularization of the EVs. In addition, EV charging infrastructure insufficiency will hinder the widespread use of EVs. Therefore, all necessary advice and guidance have been provided to develop a convenient EV charging infrastructure network, especially, fast charging stations on the freeways, which can significantly enhance travel distance of EV [2].



Figure 1.1 : Global CO2 emission reduction



Figure 1.2 : Malaysia automotive technology projection (2013-2025)

Regardless of the environmental and economic benefits, the substantial scales of grid-connected EVs impose incredible difficulties to the power grid. The main issues that are caused by EV charging on the power grid include harmonics, voltage drop, system instability, system losses, and grid overloading [3, 4]. Particularly, the effect of EV charging which leads to voltage drop of power grid has broadly been investigated and reported in the previous literatures [5-7]. In spite of the fact that EV charging has caused many difficulties to the operation of power grid, the development of EV can actually convey another prospect to the power grid. This is due to the fact that EV is considered as mobile energy storage. The energy in EV battery can be used to support the grid in different circumstances. With the bidirectional communication framework integrated in the power grid, the exchange of energy between the power grid and EV battery can plausibly be managed.

EVs are operated by an electric motor which receives power from a rechargeable battery. The performance qualities required for some EVs specifications greatly surpass the capabilities of traditional battery systems. Unfortunately, when the battery technology advances, the charging of these batteries turns out to be exceptionally complicated. This is due to the involvement of high voltage and currents flow in the system; as well as the necessity of complex charging techniques. This imposes great distortions in the connected ac power system, and thus, an efficient and low-distortion charger is highly required. With respect to the issues stated above, battery varies in different ways. The commonly applied charging technology of battery varies in different ways. The commonly applied charging techniques are the constant-current and constant-pressure charging techniques. Since AC voltage of the charger fluctuates most of the time, it requires a tributary constant-current power supply for the charging process; which is known as constant-current charger.



1.1.1 Types of Vehicles in Use Today

Ideas that were developed during the 19th century are now being utilized to develop a new collection of vehicles. Vehicles can be classified into four basic types. First type is the internal combustion engine (ICE) vehicle. It runs on liquid fuels such as, gasoline, diesel, ethanol or biodiesel. The ICE vehicle is the most common type and majority of the vehicles on the road today belong to this category.

The second type is the traditional battery electric vehicle (BEV). This battery relies fully on batteries to obtain their energy. The BEV can be charged either by being plugged into a charger, or by exchanging or replacing the depleted battery with a charged one. BEVs do not have the usual conventional engine or a tailpipe or even a fuel tank. This is because of the type of vehicle is fully operated on battery energy, whereas the commercial vehicles run on fossil fuels. The distance range and performance of the BEVs is fairly limited, however, they are adequate for their planned purpose. It is essential to remember that the electric car is a major performer in this field, and there is still room for an improvement. Nevertheless, the technology of electric cars is developing and improving continuously in order to compete with their biggest competitors; the internal combustion engine cars.

A hybrid vehicle uses a combination of electric power and fossil fuel; it has two energy systems for the engines to operate. The furthermost public type of hybrid vehicle is comprised of: an internal combustion engine with a battery, and an electrical motor and generator. The two basic measures for hybrid vehicles consist of the series called the hybrid vehicle and the parallel hybrid. A hybrid vehicle series is driven by one or more electric motors, which is provided either from the ICE driven generator unit (EVT book) or the battery or both. In either system, the electric motor fully supplies the driving force. However, in the parallel hybrid series, both the electric motor and internal combustion engine provide the driving force. In this system, the generator and engine recharges the battery itself while moving. Both types possess a regenerative braking mechanism, whereby, the drive motor works as a generator while slowing down the vehicle and simultaneously recharging the battery.

The fueled electric vehicle comprises of the same basic principles of an electric vehicle, where the battery is the power source. However, instead of a rechargeable battery, a metal air battery or fuel cell is used. Hydrogen gas is used to power an electric motor, which is kept in liquid system. Even though it can be kept on the board, it is not an easy task. Alternatively, hydrogen is produced from a fuel such as methanol. A variation of fuel cells is the metal air batteries that are refueled by substituting the metal electrodes, which can be easily recycled. The most common type metal that can be categorized to this class are the zinc air batteries.

1.1.2 On / Off Board Charging System

Presently, there are two charging techniques for electric vehicles (EVs) namely AC and DC charging [8, 9]. For AC charging, single-phase and three-phase AC power is supplied via on-board AC–DC converter of the EV. Meanwhile, DC charging is performed by direct supplying DC power to the battery of EV via off-board AC–DC converter supplies. There are three types of chargers that are widely applied [10-14]:

- 1. Type 1 SAE J1772 single-phase charger applied in US
- 2. Type 2 Mennekes single-phase and three-phase charger applied in Europe,
- 3. Tesla dual charger single-phase AC and DC.

The use of on-board chargers definitely will increase charging accessibility of the vehicle and meanwhile, off-board chargers allow the use of higher rating circuits. Thus, it completes charging in shorter period of time.

Figure 1.3 shows the off-board charger [15]. It is actually available as an outside unit, rather than being a part of the EV. A typical off-board charger is able to produce a higher DC voltage. As a result, the internal battery management system (BMS) should have the ability to charge the battery by supplying this voltage. Nevertheless, the main weakness of this type of design is that the charger is not installed as a part of the EV. Therefore, charging of EV battery can only be done with a specific charger that is capable of providing the required higher amount of DC voltage.



Figure 1.3 : Block diagram of off-board charger [15]



Figure 1.4 : Figure 1.4: Block diagram of on-board charger [16]

On the other hand, Figure 1.4 depicts the on-board charger [16]. In contrast to offboard charger, on-board charger is made as a part of EV, which allows charging at almost every location possible. As long as there is a single-phase and three-phase supply is available. However, the main disadvantage of this design is that an additional DC-AC inverter is essential.

1.1.3 Overview about the Planning of EV Charging Facilitates

Lately, plug-in electric vehicles (PEVs) have acquired a noteworthy awareness as they provide significant advantages both economically and financially. From environmental point of view, effective utilization of PEVs can greatly reduce the consumption of conventional energy sources especially gasoline. This is because PEVs powered by battery that can be completely recharged by electricity. Thus, fewer discharges are generated. From the literature [17], battery powered PEVs has reported to have a reduced discharge from transport sector, with up to 70 %, hence, it essentially minimizes environmental contamination. Financially, from previous literature [18], a TESLA PEV prices only 30\$/km, meanwhile, a gasoline-fueled premium sedan prices 173\$/km, respectively.

Due to the results of benefits mentioned above, there is a large number of PEVs operating in various nations among the world [19]. Additionally, high PEV infiltration levels are estimated to reach about 35 % by the year 2020, 51 % by the year 2030, and 62 % by year 2050 [20]. Generally, PEVs can be recharged by electricity while they are being parked at industrial, residential, and commercial as well as parking areas [21]. Moreover, mobile PEVs can fully be recharged within the time duration of 30 minutes at fast charging stations [22].

Generally, there are two main directions of research which are linked to these charging facilities (fast charging stations and parking lots). Firstly, it focuses on the process techniques of these charging services to prevent problems of overload charging [23, 25-30]. Secondly, diverse development models are examined for these charging facilities [31, 32]. Therefore, this work focuses on the future research



direction. Charging facility planning for PEV [33] must include the charger numbers to be installed in the charging facility. This corresponds to the degree of power drawn from the grid, and the space of waiting area for the uncharged PEVs. Literature has rarely discussed on the main factors that influence waiting duration of PEVs at the charging services and the proportion of PEVs with forbidden charging orders, which happens once all chargers and waiting areas are fully occupied for a new PEV [34, 35].

Besides, the research on charging facilities is limited to few factors that are One factor is that an optimization for performance discussed in literature. improvement only involves the number of chargers installed. Nevertheless, the space of waiting area for uncharged PEVs is also important due to the fact that fast charging stations are more commonly installed in areas that are based in real estate such as business districts and city centers. Thus, it becomes expansive at cost. However, oversized waiting area may reduce the profit of operator for charging facility because of the associated high investment cost. In contrast, an insufficient size of waiting area may reduce the request probability in term of PEV charging, and it will eventually contribute to loss in profit. Moreover, the current planning models only target to enhance a single criterion such as rejected requests, charger utilization, and waiting time. However, an effective charging facilities plan must consider implementing a multiple criteria, which includes the electricity cost, price of charging service, waiting queue length of PEVs, and percentage of rejected PEV charging requests. This is because these are all the critical aspects that greatly influence the amount of profit earned.

1.1.4 Charger Power Levels and Infrastructure

The power level of charger reflects towards its power, location and charging time, equipment, the impact on the grid, and cost. Charging infrastructure and EV supply equipment (EVSE) installation requires critical considerations due to many issues that should be considered: the regulatory procedures, demand policies, distribution, extent, charging time, and charging stations standardization. The availability of charging infrastructure can be utilized to lessen the requirements. Thus, the cost of on-board energy storage is applied. The significant segments of EVSE include EV charge cords, attachment plugs, power outlets, vehicle connectors, charge stands (public or residential), and protective [36, 37]. Generally, they are available in two distinct designs: (1) a dedicated cord set, and (2) a pedestal or wall mounted box. The detailed setup is differs in different locations and countries subjected to electrical grid connection, voltage, frequency, and the applied standards [38].



1.1.5 Level 1 Charging

Level 1 charging is installed for slow charging. In United States (US), a standard 120 V/15 A single-phase grounded outlet is dedicated for Level 1 charging. For example, a NEMA 5-15 R. A typical J1772 connector may be applied into the AC port of EV

[39]. Meanwhile, no addition substructure is compulsory for sites such as home and business. Low off-peak rates are probably accessible during the night time.

1.1.6 Level 2 Charging

Level 2 charging is preferred to be used for public and home facilities. This type of charging infrastructure can likewise be installed on-board to prevent excessive power through electronic devices. The current Level 2 devices provide charging from 208 V or 240 V (at up to 80 A, 19.2 kW). It could need specific tool and a joining installation for home or public units [42]. In spite of the fact that vehicles especially Tesla has on-board power electronics, it requires just the outlet. Most homes in the US have 240 V service accessibilities, and Level 2 equipment can charge a typical EV battery overnight. Level 2 technologies are very much preferred by consumers as they provide standardized connection between the vehicle and charger, and a fast charging time. However, billing meter is installed differently.

1.1.7 Level 3 Charging

Level 3 charging system is installed for fast charging (within 60 minutes) and it is suitable to be installed at city refueling areas, corresponding to petrol stations, and also in highway rest areas. Normally, the charging system works with three-phase circuit of 480 V or higher [46] and it would require an off-board charger to ensure effective AC–DC rectification procedure. DC joining may directly be applied to the vehicle.

1.1.8 Charging Features and Infrastructures of Some Manufactured PHEVs AND EVs

Charging via Level 3 is less appropriate for residential areas. CHAdeMO is a Japanese protocol that has received an international acknowledgment [47]. It is reported to have an issue on the installation cost. However, it has been reported in [48, 49], that the installation costs between \$30 000 and \$160 000 is required for Level 3 charging infrastructure. Meanwhile, an additional cost is needed for maintenance of the charging stations, respectively [50]. It is stated in standard SAE J1772 [51] that Levels 1 and 2 EVSE must be situated on the vehicle, while Level 3 should be situated at the external to the vehicle [52, 53]. Generally, it is expected that public stations apply either Levels 2 or 3 charging in order to achieve fast charging in public places [72]. A lower charge power is beneficial for functions seeking to reduce on-peak effect [54]. High-power fast charging can build request and possibly over-burden local distribution equipment at peak times [55, 56]. Level 2 and 3 charging contributes greatly to harmonic distortion, increment to transformer losses, peak demand, voltage deviations, and thermal loading on the power system. These difficulties encountered may affect the transformer's operational life, efficiency, security, reliability, and the market of smart grids development caused by

degraded transformer operation life [57]. Nevertheless, a controlled smart charging scheme [58] can be applied to minimize the likelihood of typical distribution equipment from degrading. Subsequently, a robust communication network and public charging control system is expected to successfully ensure the large-scale development of EVs [59]. Charging features and infrastructure aspects for five types of vehicles is summarized in Table 1.1.



Table 1.1 : Charging characteristic and infrastructures of some manufactured PHEVS and EVS

C

	Level 2 Charging	Charge Time	2 – 3 hours	14 hours	2.5 hours	6-8 hours	4-12 hours
		Demand	3.8 kW	3 kW	3.8 kW (240 V)	3.3 kW	9.6–16.8 kW
	Level 1 Charging	Charge Time	5-8 hours	7 hours	3 hours	12 – 16 hours	30 + hours
		Demand	0.96 – 1.4 kW	1.5 kW	1.4 kW (120 V)	1.8 kW	1.8 kW
	DC Fast Charging	Charge Time	N/A	30 Minutes	N/A	15 - 30 minutes	N/A
		Demand	N / A	50 kW	N/A	50 + kW	N/A
	All-Electric Range		40 miles	96 miles	14 miles	100 miles	245 miles
	Connector Type		SAE J1772	SAE J1772 JARI/TEPCO	SAE J1772	SAE J1772 JARI/TEPCO	SAE J1772
	Battery	Type and Energy	Li-Ion 16 kWh	Li-Ion 16 kWh	Li-Ion 4.4 kWh	Li-Ion 24 kWh	Li-Ion 53 kWh
			Chevrolet Volt PHEV	Mitsubishi i-MiEV EV	Toyota Prius PHEV (2012)	Nissan Leaf EV	Tesla Roadster EV

6

1.1.9 Typical Battery Charging Profile

Battery is simply an electrochemical galvanic cell or a combination of these cells, which is capable of storage chemical energy. It is commonly referred to as an invention that converts chemical energy into electrical energy in a direct manner. Battery is highly preferred to be utilized in vehicles, and most EV manufacturers apply specific traction batteries such as Nickel, Nickel and Cadmium, Lead Acid, Sodium and Nickel Chloride, Lithium ion/polymer, and Zinc. Besides that, the design of batteries must fulfill certain requirements in expressions of power density and energy, safety matters, and operational life with a specific end goal; so that they can be applied in EVs and PHEVs. Hence, in 2006, the United States Advanced Battery Consortium (USABC) and Electrochemical Energy Storage Tech Team (EESTT) have worked together to create requirements for PHEV end of life battery [60]. The EV's battery should perfectly afford a high independence (refer to the distance coverage of vehicle in one whole discharge of the battery) to any vehicle and have the necessary specific amount of energy and power. In other words, the batteries should be compact, lightweight, and accomplished of storage and providing extraordinary amounts of energy and power correspondingly. Moreover, they should also have a extended operational life, where they should be able to fully discharge to an empty state and fully recharge again as many times as possible. This also needs to ensure that there is no exhibiting of any obvious performance degradation and it can be fully recharged in shortest time. Furthermore, they must also be able to function properly over a substantial temperature range and safely handle and recycle with a minimum costs. In contrast to batteries that are applied in conventional low power/energy applications, batteries apply in EV require additional care regarding safety issues. This is due to a continuous fast charging or discharging cycles and a high power transfer may generate excessive heat. The choices of a proper chemistry, cell balancing and advanced thermal management are the factors that influence losses in the cell. One passive solution to those losses is by using phase alteration materials to eliminate large amounts of heat by means of latent heat of fusion [61].

A common charging profile of Li-ion battery cell [62] is shown in Figure 1.5. In industry, constant voltage (CV) and constant current (CC) charging are the two typical charging profiles applied for Li-ion batteries. Throughout CC charging, the current is controlled, whilst maintaining a constant fix value until the voltage of battery cell scopes the desired level. Consequently, the charging will switch to CV charging, and the battery will be charged with the applied trickle current supplied by constant output voltage of the charger.



Figure 1.5 : Typical charging profile of Li-ion cell [62]

1.2 Problem statement

Electric vehicle (EV) development is one of the effective approaches in reducing fuel consumption and greenhouse emissions, and battery charging system is the most critical part of its development. Owing to the advancement in EV technologies, the design of a reliable, efficient and high power density charger has become a great challenge. Its operation is fully dependent on components, control, and switching technique.

As described in Sections 1.1.5 - 1.1.7, there are three levels of charging mode. However, the existing battery chargers are designed only to charge one level of charging mode [19], and thus lack of flexibility to provide charging for the other modes. Besides, the chargers also suffer from high ripples of DC-link voltage which can damage the battery.

The input current of the EV charger with high total harmonic distortion (THD) can subsequently cause many problems to the other electronic devices that are used in the charger station. Hence, it is crucial to maintain the THD of the input current within the acceptable limits of 5 % as stated in IEEE 519 standard.

Numbers of control algorithms have been introduced to reduce the harmonic distortion of the current drawn from the input power line by the rectifiers, such as Direct Power Control (DPC) and Virtual Flux Oriented Control (VFOC). The application of control systems is accomplished through the following components: (1)

analog controllers, (2) microcontrollers, (3) digital signal processors, and (4) integrated circuits particularly reliant on the rating, and (5) category of converters.

Studies recommended that DPC control algorithm provides an improved power factor when compared with other algorithms [7, 22]. Although, there is a greater power factor can be achieved with Variable Flux Direct Power Current (VF-DPC), the drawback is that it requires microprocessors and A/D converters. To avoid this, voltage oriented control VOC should be selected.

1.3 Aim and Objectives

This work aims to present the design and fabrication process of a three levels universal electric vehicle charger. The proposed charger is capable of providing a controllable and constant charging voltage for various EVs. The objectives of this work are as follows:

- 1. To develop three levels of electric vehicle charging system, it composes 650V/100A DC for bus or lorry, three-phase 240V/60A AC for saloon car and single-phase 120V/16A AC for motorbike.
- 2. To propose and design a new control algorithm for three-phase PWM rectifier, based on concepts of voltage oriented control (VOC), and three-phase PWM inverter based on SPWM technique.
- 3. To validate and compare experimental results of the charging system with the simulation results by developing a laboratory prototype of the charging system with integration of VOC and SPWM algorithms.

1.4 Scope and Limitations of Work

This work is divided into two sections, namely, software and hardware sections. In the software section, the work begins with the design of three levels charger followed by simulation of the proposed design in MATLAB/Simulink software program. The three levels charger covers both the on board and off board charging: Levels 1 and 2 for on board charging, while, Level 3 is for off board charging. The input source voltage is set to be 600 Vrms (line to line) for Level 1 charger testing, and 850 Vrms (line to line) for Level 2 charger testing. Both Levels 1 and 2 chargers are tested with resistor load. On the other hand, for Level 3 charger, the input source voltage is set to be 1700 Vrms (line to line) and it is tested with three types of batteries (Li – ion, Lead – acid and Nickel Cadmium).

Performance evaluation with the actual EV is not within the scope of this work, as this work only focuses on power system. In order to work with EV, BMS and PLC or CAN communication system must be installed. Furthermore, this work does not consider unbalanced and distorted input voltage in the evaluation process. The input



voltage serves as a reference to ensure proper synchronization between voltages and current, hence, an effective charging can be achieved. Therefore, this work only considers balanced three-phase three-wire system with sinusoidal source voltage.

In the hardware section, a laboratory prototype is constructed where the controller and power circuits are assembled to function as three levels charger, similar to the one that is modeled in MATLAB/Simulink. In the experimental work, for safety purposes and due to limitations of available resources, the maximum input supply voltage for the battery charger is set to be 180 Vrms (line to line). Meanwhile, a high performance digital signal processor (DSP) is programmed to perform all the control algorithms of the battery charger. In the experiment work, Levels 1 and 2 chargers are tested with resistor load ranging from 20 Ω to 70 Ω . Meanwhile, for validating performance of Level 3 charger, 15 cells 12 V lead-acid batteries are applied.

1.5 Thesis Layout

This thesis is organized into five chapters. Chapter 1 provides an overview of the research work which includes research background, related study, main problems to be solved, aim and objectives, and scope and limitations of the work.

Chapter 2 provides a comprehensive review on the technology of Electric Vehicle Supply Equipment (EVSE). A survey on the charger requirements for different vehicles and classification based on charging times are also provided. Next, a comprehensive review on the power converters and the existing control method is presented. Lastly, the related works on electric vehicle charger are highlighted.

Chapter 3 describes the design and development of the electric vehicle (EV) charger, detailing its operating principle and design considerations. Moreover, the newly proposed control algorithms are clearly described. This chapter also provides complete details on simulation model and laboratory setup of the proposed EV charger as well as implementation of the proposed control algorithms in a high performance DSP.

Chapter 4 presents the findings and results obtained in simulation and experimental works. In the simulation, the findings are presented according to the level of charger which includes Levels 1, 2, and 3. Meanwhile, in the experimental work, the findings are presented according to power rating which include low and medium powers.

Chapter 5 concludes the work, significant contributions of the work and recommends possible future works.



REFERENCES

- [1] The State Council, "Energy saving and new energy automobile industry development plan," Beijing, China, Jun, 2012. [Online]. Available: http://www.nea.gov.cn/2012-07/10/c_131705726.htm.
- [2] The State Council, "Guidance on accelerating the popularization and application of new energy vehicles," Beijing, China, Jul, 2014. [Online]. Available: http://www.gov.cn/zhengce/content/2014-07/21/content_8936.htm.
- [3] S. Habib, M. Kamran, and U. Rashid, "Impact analysis of vehicle to grid technology and charging strategies of electric vehicles on distribution networks A review," *J. Power Syst.*, vol. 277, pp. 205-214, March. 2015.
- [4] R. C. Green II, L. Wang, and M. Alam, "The impact of plug-in hybrid electric vehicles on distribution networks: a review and outlook," *Renew. Sustain. Energy Rev.*, vol. 15, no. 1, pp. 544-553, January 2011.
- [5] M. K. Gary, and W. G. Morsi, "Power quality assessment in distribution systems embedded with plug-in hybrid and battery electric vehicles," *IEEE Trans. Power Syst.*,vol. 30, no. 2, pp. 663-671, July 2014.
- [6] C. H. Dharmakeerthi, N. Mithulananthan, and T. K. Saha, "Impact of electric vehicle fast charging on power system voltage stability," *Int. J. Elect. Power Energy Syst.*, vol. 57, pp. 241-249, May 2014.
- [7] F. Mwasilu, J. J. Justo, E. K. Kim, T. D. Do, and J. W. Jung, "Electric vehicles and smart grid interaction: A review on vehicle to grid and renewable energy sources integration," *Renew. Sustain. Energy Rev.*, vol. 34, pp. 501-516, June 2014.
- [8] Y. Yao, B.C. Chen, and C.H. Tian, "EHV Magnetically Controlled Reactor for Suppressing Interior Over- voltage and Secondary Arc Current," *Journal* of Jilin University (Engineering and Technology Edition), vol.38, pp. 201-208, February 2008.
- [9] H. Wang, Y.L. Li, and B. Li, "Secondary Arc Extinction Methods for 750kV and UHV Transmission Lines," *Electric Power*, vol. 38, pp. 8-10, December 2005.
- [10] L.Q. Shang and W. Shi, "Study of the secondary arc extinction at EHV double circuit transmission lines," *Automation of Electric Power System*, vol. 29, pp. 60-63, May 2005.
- [11] G.H. Fox, "Getting ready for electric vehicle charging stations," in IEEE Industry Applications Society Annual Meeting (IAS), pp.1-7, 9-13 October 2011.

- [12] N. Kawamura, and M. Muta, "Development of solar charging system for plug-in hybrid electric vehicles and electric vehicles," in Proceedings of International Conference Renewable Energy Research and Applications (ICRERA), pp. 1-5, 11-14 November 2012.
- [13] A. Arancibia and K. Strunz "Modeling of an electric vehicle charging station for fast DC charging," in Proceedings of IEEE International Electric Vehicle Conference (IEVC), pp.1-6, 4-8 March 2012.
- [14] G.F. Reed, B.M. Grainger, A.R. Sparacino, R.J. Kerestes, and M.J. Korytowski, "Advancements in medium voltage DC architecture development with applications for powering electric vehicle charging stations," in Proceedings of IEEE Energytech, pp.1-8, 29-31 May 2012.
- [15] M. Yilmaz and P. T. Krein, "Review of Battery Charger Topologies, Charging Power Levels, and Infrastructure for Plug-In Electric and Hybrid Vehicles," *IEEE Trans. Power Electron.*, vol. 28, no. 5, pp. 2151–2169, May 2013.
- [16] P. Bauer, Yi Zhou, J. Doppler, N. Stembridge, and Y. Zhou, "Charging of electric vehicles and impact on the grid," in Proceedings of 13th International Symposium on Mechatronics, MECHATRONIKA 2010, 2010, pp. 121–127.
- [17] SAE Standard J1772, "SAE Electric Vehicle and Plug-in Hybrid Electric Vehicle Conductive Charge Coupler," 2010.
- [18] SAE Hybrid Committee, "SAE Charging Configurations and Ratings Terminology," 2011.
- [19] "Standard IEC 62196 Plugs, socket-outlets, vehicle connectors and vehicle inlets Conductive charging of electric vehicles Part 1, 2, 3," 2014.
- [20] "Standard IEC 61851 Electric vehicle conductive charging system Part 1, 21, 22, 23, 24," 2014.
- [21] www.teslamotors.com, "Tesla EV charging and supercharger technology."
- [22] A comprehensive guide to plug-in hybrid vehicles, Hybrid Cars, Available online: http://www.hybridcars.com/plug-in-hybrid-cars/battery, 2011.
- [23] TESLA Motors, Available online: http://www.teslamotors.com/models.
- [24] M.F. Shaaban, M. Ismail, E. F. El-Saadany, and W. Zhuang, "Real-time PEV charging/discharging coordination in smart distribution systems," *IEEE Trans. Smart Grid*, vol. 5, no. 4, pp. 1797-1807, July 2014.
- [25] Electric Power Research Institute, Available online: http://www.epri.com/Pages/Default.aspx.

- [26] I. S. Bayram, M. Ismail, M. Abdallah, K. Qaraqe, E. Serpedin, "A pricingbased load shifting framework for EV fast charging stations, *IEEE Smart*, pp. 2385-2392, November 2012.
- [27] I. S. Bayram, G. Michailidis, M. Devetsikiotis, and F. Granelli, "Electric power allocation in a network of fast charging stations," *IEEE Journal Selected Areas Commun.*, vol. 31, no. 7, pp. 1235-1246, July 2013.
- [28] H. Liang, I. Sharma, W. Zhuang, and K. Bhattacharya, "Plug-in electric vehicle charging demand estimation based on queueing network analysis," in Proceedings of IEEE GM'14, July 2014.
- [29] I.S. Bayram, G. Michailidis, I. Papapanagiotou, and M. Devetsikiotis, "Decentralized control of electric vehicles in a network of fast charging stations," in Proceedings of IEEE JGC'13, pp. 2785-2790, December 2013.
- [30] L. Gan, U. Topcu, and S. Low, "Optimal decentralized protocol for electric vehicle charging," in Proceedings of IEEE CDC-ECC'11, pp. 5798-5804, December 2011.
- [31] D. Callaway and I. Hiskens, "Achieving controllability of electric loads," *Proceedings of the IEEE*, vol. 99, no. 1, pp. 184-199, January 2013.
- [32] L. Feng, S. Ge, H. Liu, L. Wang, and Y. Feng, "The planning of charging stations on the urban trunk road," in Proceedings of IEEE ISGT'12, pp. 1-4, May 2012.
- [33] W. Zhenpo, L. Peng, and X. Tao, "Optimizing the quantity of off-broad charger for whole vehicle charging station," in Proceedings of ICOIP'10, pp. 93-96, November 2010.
- [33] SAE Electric Vehicle and Plug-in Hybrid Electric Vehicle Conductive Charge Coupler, SAE Standard J1772, January 2010.
- [34] *Electric Vehicle Infrastructure Installation Guide*, Pacific Gas and Electric Company, San Francisco, CA, USA, March 1999.
- [35] SAE Electric Vehicle Inductive Coupling Recommended Practice, SAE 5-1773, 1 February 1995.
- [36] L. De-Sousa, B. Silvestre, and B. Bouchez, "A combined multiphase electric drive and fast battery charger for electric vehicles," in Proceedings of IEEE Veh. Power and Propulsion Conf., pp. 1–6, September 2010.
- [37] K. Morrowa, D. Karnerb, and J. Francfort, "Plug-in hybrid electric vehicle charging infrastructure review," U.S. Dep. Energy Veh. Technol. Program, Final Rep., 58517, Washington, DC, November 2008.

- [38] M. Rawson and S. Kateley, "Electric vehicle charging equipment design and health and safety codes," California Energy Commission Rep., 31 August 1998.
- [39] D. P. Tuttle and R. Baldick, "The evolution of plug-in electric vehiclegrid interactions," *IEEE Trans. Smart Grid*, vol. 3, no. 1, pp. 500–505, Mar. 2012.
- [40] K. Morrowa, D. Karnerb, and J. Francfort, "Plug-in hybrid electric vehicle charging infrastructure review," U.S. Dep. Energy Veh. Technol. Program, Final Rep., 58517, Washington, DC, Nov. 2008.
- [41] Tesla Motors. (2009). "Tesla roadster spec sheet," [Online]. Available: http://www.teslamotors.com/display_data/teslaroadster_specsheet.pdf.
- [42] Vehicle Technologies Program, U.S. Dept. Energy, Office of Energy and Renewable Energy and the National Renewable Energy Lab, 2011.
- [43] CHAdeMO, "What is CHAdeMO?" (2010). [Online]. Available: http://chademo.com/01_What_is_CHAdeMO.html
- [44] M. Thomason, "Plug-in recharge," (2011). Online]. Available: http://www1.eere.energy.gov/vehiclesandfuels/avta/light_duty/fsev/fsev_batt ery.chargers
- [45] Electrification of the Transportation System, MIT Energy Initiative, Cambridge, MA, April 2010.
- [46] T. Brown, J. Mikulin, N. Rhazi, J. Seel, and M. Zimring, "Bay area electrified vehicle charging infrastructure: Options for accelerating consumer," Renewable and Appropriate Energy Laboratory (RAEL), Univ. of California, Berkeley, June 2010.
- [47] A. Mathoy, "Definition and implementation of a global EV charging infrastructure, Final Rep.," Brusa Elektronik, Sennwald, Switzerland, 2008.
- [48] S. Mehta, "Electric plug-in vehicle/electric vehicle, Status Report," Aug. 2010.
- [49] C. B. Toepher, "Charge! EVs power up for the long haul," *IEEE Spectrum*, vol. 35, no. 11, pp. 41–47, November 1998.
- [50] C. Weiller, "Plug-in hybrid electric vehicle impacts on hourly electricity demand in the US," *Energy Policy*, vol. 39, no. 6, pp. 3766–3778, 2011.
- [51] Illinois Commerce Commission, "Initiative on Plug-in Electric Vehicles, Commonwealth Edison Company, Initial Assessment of the Impact of the Introduction of Plug-in Electric Vehicles on the Distribution System," 15 December 2010.

- [52] M. Etezadi-Amoli, K. Choma, and J. Stefani, "Rapid-charge electric vehicle stations," *IEEE Trans. Power Del.*, vol. 25, no. 3, pp. 1883–1887, June 2010.
- [53] J. Mullan, D. Harries, T. Braunl, and S. Whitely, "Modelling the impacts of electric vehicle recharging on the Western Australian electricity supply system," *Energy Policy*, vol. 39, pp. 4349–4359, May 2011.
- [54] S. Bae and A. Kwasinski, "Spatial and temporal model of electric vehicle charging demand," *IEEE Trans. Smart Grid*, vol. 3, no. 1, pp. 394–403, March 2012.
- [55] Su, W. Zeng, and M. Y. Chow, "A digital testbed for a PHEV/PEV enabled parking lot in a smart grid environment," in Proceedings of IEEE Innovative Smart Grid Tech. Conf., pp. 1–7, January 2012.
- [56] http://batteryuniversity.com/learn/article/lithium_based_batteries.
- [57] K. T. Chau and Y. S. Wong, —Overview of power management in hybrid electric vehicles, Energy Conversion and Management, vol. 43, no. 15, pp. 1953-1968, 2002.
- [58] Pesaran, Battery Requirements for Plug-In Hybrid Electric Vehicles Analysis and Rationall, presented in Sustainability: The Future of Transportation, EVS, December 2007.
- [59] L. Siguang, Z. Chengning, and X. Shaobo, —Research on Fast Charge Method for Lead-acid Electric Vehicle Batteries, in Proceedings of IEEE ISA'09, pp. 1-5, May 2009,
- [60] R. Redl, Batteries for Beginners in Proceedings of APEC, 5-9 February 2012.
- [61] M.C. Kisacikoglu, B. Ozpineci, L.M. Tolbert, Reactive power operation analysis of a singlephase EV/PHEV bidirectional battery charger, in Proceedings of IEEE 8th International Conference Power Electronics and ECCE Asia (ICPE & ECCE), pp. 585-592, 30 May - 3 June 2011
- [62] G. Glanzer, T. Sivaraman, J.I. Buffalo, M. Kohl, H. Berger, "Cost-efficient integration of electric vehicles with the power grid by means of smart charging strategies and integrated onboard chargers," in Proceedings of 10th International Conference on Environment and Electrical Engineering (EEEIC), pp. 1-4, 8-11 May 2011
- [63] C.B. Toepfer, —Charge! EVs power up for the long haul, I Spectrum, IEEE, vol.35, no.11, pp. 41-47, November 1998.
- [64] Erb, D.C.; Onar, O.C.; Khaligh, A.; , "Bi-directional charging topologies for plug-in hybrid electric vehicles," in Proceedings of 25th Annual IEEE

Applied Power Electronics Conference and Exposition (APEC), pp. 2066-2072, 21-25 February 2010.

- [65] J. Francfort, Electric Vehicle Charging Levels and Requirements Overview, Clean Cities December 2010 Webinar, Available online: http://www1.eere.energy.gov.
- [66] C.H. Dharmakeerthi, N. Mithulananthan , and T.K. Saha, "Overview of the Impacts of Plug-in Electric Vehicles on the Power Grid," in Proceedings of Innovative Smart Grid Technologies (ISGT) Asia Conference, Perth, 2011.
- [67] M. El Chehaly, O. Saadeh, C. Martinez, and G. Joos, "Advantages and applications of vehicle to grid mode of operation in plug-in hybrid electric vehicles," in Proceedings of IEEE Electrical Power & Energy Conference (EPEC), pp. 1-6, 2009.
- [68] http://standards.sae.org/j2836/2_201109/
- [70] M.H. Rashid, *Power electronics handbook: devices, circuits and applications.* 2010: Academic press.
- [71] R.W. Erickson and D. Maksimovic, *Fundamentals of power electronics*. 2007: Springer Science & Business Media.
- [72] F. Blaabjerg, Z. Chen, and S.B. Kjaer, *Power electronics as efficient interface in dispersed power generation systems. IEEE Trans. Power Electron.*, vol. 19, no. 5, pp. 1184-1194, 2004.
- [73] C. Albea-Sanchez, Control Design for Electronic Power Converters. Citeseer, 2010.
- [74] O. Gutfleisch, et al., Magnetic materials and devices for the 21st century: stronger, lighter, and more energy efficient. Advanced materials, vol. 23, no. 7, pp. 821-842, 2011.
- [75] G. Eirea, *Estimation and control techniques in power converters*. University of California, Berkeley, 2006.
- [76] N. Mohan, and T.M. Undeland, *Power electronics: converters, applications, and design.* John Wiley & Sons, 2007.
- [77] B. Bird, and K.G. King, *An introduction to power electronics*. 1983.
- [78] R.D. Middlebrook, and S. Cuk, Advances in switched mode power conversion. 1981.
- [79] F. Bordry, Power converters: definitions, classifications and converter topologies.CASCERN Accelerator School and CLRC Daresbury Laboratory: Specialised CAS Course on Power Converters, pp. 13-42, 2004:

- [80] J.A. Rossiter, *Model-based predictive control: a practical approach*. CRC press, 2013.
- [81] A.L. Fradkov, I.V. Miroshnik, and V.O. Nikiforov, "Nonlinear and adaptive control of complex systems", *Springer Science & Business Media*, vol. 491. 2013.
- [82] K.K.-S. Leung, and H.S.-H. Chung, "Dynamic hysteresis band control of the buck converter with fast transient response", *IEEE Trans. Circuits Syst. II: Express Briefs*, vol. 52, no. 7, pp. 398-402, 2005.
- [83] L. Malesani, P. Mattavelli, and P. Tomasin, "Improved constant-frequency hysteresis current control of VSI inverters with simple feedforward bandwidth prediction". *IEEE Trans. Ind. Appl.*, vol. 33, no. 5, pp. 1194-1202, 1997.
- [84] H.İ. Okumuş, and M. Aktaş, "Adaptive hysteresis band control for constant switching frequency in DTC induction machine drives", *Turkish Journal of Electrical Engineering & Computer Sciences*, vol. 18, no. 1, pp. 59-72, 2010.
- [85] M. Malinowski, M.P. Kazmierkowski, and A.M. Trzynadlowski, "A comparative study of control techniques for PWM rectifiers in AC adjustable speed drives", *IEEE Trans. Power Electron.*, vol. 18, no. 6, pp. 1390-1396, 2003.
- [86] B.K. Bose, "An adaptive hysteresis-band current control technique of a voltage-fed PWM inverter for machine drive system". *IEEE Trans. Ind. Electron.*, vol. 37, no. 5, pp. 402-408, 1990.
- [87] L., Dalessandro, et al. A novel hysteresis current control for three-phase three-level PWM rectifiers. in Proceedings of 20th Annual IEEE Applied Power Electronics Conference and Exposition, *APEC 2005*.
- [88] M., Bobrowska-Rafał, et al., "Control of PWM rectifier under grid voltage dips", *Bulletin of the Polish Academy of Sciences: Technical Sciences*, vol. 57, no. 4, pp. 337-343, 2009.
- [89] Y. Zhang, and C. Qu, "Model Predictive Direct Power Control of PWM Rectifiers Under Unbalanced Network Conditions", *IEEE Trans. Ind. Electron.*, vol. 62, no. 7, pp. 4011-4022, 2015.
- [90] E. Ozkop, and H.I. Okumus. "Direct torque control of induction motor using space vector modulation (SVM-DTC)", in Proceedings of 12th IEEE International Middle-East.Power System Conference (MEPCON), 2008.
- [91] M.Z.R., Zuber, et al., "Improved Torque Control Performance in Direct Torque Control using Optimal Switching Vectors", *International Journal of Power Electronics and Drive Systems*, vol. 5, no. 3, pp. 441, 2015.

- [92] J., Liu, X. You, and T.Q. Zheng. "Sliding-mode variable structure current controller for field oriented controlled linear induction motor drive", in Proceedings of 6th IEEE International Power Electronics and Motion Control Conference IPEMC'09. 2009.
- [93] X. Rain, M. Hilairet, and R. Talj. "Second order sliding mode current controller for the switched reluctance machine", in Proceedings of *36th IEEE Annual Conference on Industrial Electronics Society (IECON)*, 2010.
- [94] S.-C. Tan, Y. Lai, and C.K. Tse, "Indirect sliding mode control of power converters via double integral sliding surface", *IEEE Trans. Power Electron.*, vol. 23, no. 2, pp. 600-611, 2008.
- [95] M. Dal and R. Teodorescu, "Sliding mode controller gain adaptation and chattering reduction techniques for DSP-based PM DC motor drives", *Turkish Journal of Electrical Engineering & Computer Sciences*, vol. 19, no. 4, pp. 531-549, 2011.
- [96] J. Chen and P.-C. Tang, "A sliding mode current control scheme for PWM brushless DC motor drives", *IEEE Trans.Power Electron.*, vol. 14, no. 3, pp. 541-551, 1999.
- [97] P. Mattavelli, "An improved deadbeat control for UPS using disturbance observers", *IEEE Trans. Ind. Electron.*, vol. 52, no. 1, pp. 206-212, 2005.
- [98] M. Arnold, and G. Andersson. "Model predictive control of energy storage including uncertain forecasts", in Proceedings of Power Systems Computation Conference (PSCC), Stockholm, Sweden. 2011.
- [99] A.M. Almaktoof, A. Raji, and M. Kahn, "Modelling and Simulation of Three-Phase Voltage Source Inverter Using a Model Predictive Current Control", J. of Innovation, Manage. and Technol, vol. 5, no. 1, pp. 9-13, 2004.
- [100] S., Vazquez, et al., "Model predictive control: A review of its applications in power electronics", IEEE Industrial Electronics Magazine, vol. 8, no. 1, pp. 16-31, 2014.
- [101] E. El-Kholy, "Generalized predictive controller for a boost AC to DC converter fed DC motor", in Proceedigns of IEEE International Conference on Power Electronics and Drives Systems, (PEDS), 2005.
- [103] S. Zhang, et al., "Research on the Three-phase Voltage Aviation Rectifier Based on Neural Network PID Control", *Sensors & Transducers*, vol. 171, no. 5, pp. 25, 2014.
- [104] S. Haghbin, K. Khan, S. Lundmark, M. Alak["]ula, O. Carlson, M. Leksell, and O. Wallmark, "Integrated chargers for EV's and PHEV's: Examples and new

solutions," in Proceedings of International Conference on Electrical Machines, pp. 1–6, 2010.

- [105] W. E. Rippel, "Integrated traction inverter and battery charger apparatus," U.S. Patent 4 920 475, April 1990.
- [106] D. G. Woo, G. Y. Choe, J. S. Kim, B. K. Lee, J. Hur, and G. B. Kang, "Comparison of integrated battery chargers for plug-in electric vehicles: Topology and control," in Proceedings of Electric Mach. Drives Conf., pp. 1294–1299, 2011.
- [107] G. Pellegrino, E. Armando, and P.Guglielmi, "An integral battery charger with power factor correction for electric scooter," *IEEE Trans. Power Electron.*, vol. 25, no. 3, pp. 751–759, March 2010.
- [108] L. Shi, A. Meintz, and M. Ferdowsi, "Single-phase bidirectional ac-dc converters for plug-in hybrid electric vehicle applications," in Proceedings of IEEE Veh. Power Propulsion Conf., pp. 1–5, September 2008.
- [109] L. Tang and G. J. Su, "A low-cost, digitally-controlled charger for plug-in hybrid electric vehicles," in Proceedings of IEEE Energy Convers. Congr. Expo.
- [110] S M. Grenier, M. H. Aghdam, and T. Thiringer, "Design of on-board charger for plug-in hybrid electric vehicle," in Proceedings of Power Electronics, Machine and Drives, pp. 1–6, 2010.
- [111] H. C. Chang and C. M. Liaw, "Development of a compact switched reluctance motor drive for EV propulsion with voltage-boosting and PFC charging capabilities," *IEEE Trans. Veh. Technol.*, vol. 58, no. 7, pp. 3198– 3215, September 2009.
- [112] W. E. Rippel and A. G. Cocconi, "Integrated motor drive and recharge system," U.S. Patent 5099186, March 1992.
- [113] A. G. Cocconi, "Combined motor drive and battery charger system," U.S. Patent 5 341 075, August 1994.
- [114] S. Haghbin, S. Lundmark, M. Alakula, and O. Carlson, "An isolated high-power integrated charger in electrified vehicle applications," *IEEE Trans. Veh. Technol.*, vol. 60, no. 9, pp. 4115–4126, November 2011.
- [115] W. E. Rippel, "Integrated traction inverter and battery charger apparatus," U.S. Patent 4 920 475, April 1990.
- [116] L. Solero, "Nonconventional on-board charger for electric vehicle propulsion batteries," *IEEE Trans. Veh. Technol.*, vol. 50, no. 1, pp. 144–149, January 2001.

- [117] S.-K. Sul and S.-J. Lee, "An integral battery charger for four-wheel drive electric vehicle," *IEEE Trans. Ind. Appl.*, vol. 31, no. 5, pp. 1096–1099, September/October 1995.
- [118] F. J. Perez-Pinal and I. Cervantes, "Multi-reconfigurable power system for EV applications," in *Proc. Int. Conf. EPE Power Electron. Motion Control*, pp. 491–495, 2006,
- [119] F. Lacressonniere and B. Cassoret, "Converter used as a battery charger and a motor speed controller in an industrial truck," in *Proc. EPE*, pp. 1–7, 2005.
- [120] L. De-Sousa, B. Silvestre, and B. Bouchez, "A combined multiphase electric drive and fast battery charger for electric vehicles," in *Proc. IEEE Veh. Power and Propulsion Conf.*, pp. 1–6, September 2010.
- [121] S. Lacroix, E. Laboure, and M. Hilairet, "An integrated fast battery charger for electric vehicle," in *Proc. IEEE Veh. Power Propulsion Conf.*, pp. 1–6, September 2010.
- [122] S. Haghbin, M. Alakula, K. Khan, S. Lundmark, M. Leksell, O. Wallmark, and O. Carlson, "An integrated charger for plug-in hybrid electric vehicles based on a special interior permanent magnet motor," in *Proc. IEEE Veh. Power Propulsion Conf.*, pp. 1–6, September 2010.
- [123] L. De-Sousa and B. Bouchez, "Method and electric combined device for powering and charging with compensation means," Int. Patent WO 2010/057893A1, 2010.
- [124] A. Bruy'ere, L. De Sousa, B. Bouchez, P. Sandulescu, X. Kestelyn, and E. Semail, "A Multiphase traction/fast-battery-charger drive for electric or plugin hybrid vehicles," in *Proc. IEEE Veh. Power Propulsion Conf.*, pp. 1–7, September 2010.
- [125] S. Haghbin, S. Lundmark, M. Alakula, and O. Carlson, "An isolated highpower integrated charger in electrified vehicle applications," *IEEE Trans. Veh. Technol.*, vol. 60, no. 9, pp. 4115–4126, November 2011.
- [126] M. Budhia, G. A. Covic, J. T. Boys, and C. Y. Huang, "Development and evaluation of single sided flux couplers for contactless electric vehicle charging," in *Proc. IEEE Energy Conversion Congr. Expo.*, pp. 614–621, September 2011,
- [127] J. G. Hayes, M. Egan, J. D. Murphy, S. Schulz, and J. Hall, "Wide load resonant converter supplying the SAE J-1773 electric vehicle inductive charging interface," *IEEE Trans. Ind. Appl.*, vol. 35, no. 4, pp. 884–895, August 1999.
- [128] G. Y. Choe, J. S. Kim, B. K. Lee, C. Y. Won, and T. W. Lee, "A bidirectional battery charger for electric vehicles using photovoltaic PCS

systems," in Proc. IEEE Veh. Power Propulsion Conf., pp. 1-6, September 2010,

- [129] I. Husain, "Electric and hybrid vehicles: design fundamentals,"CRC Press, 2nd Edition, chap. I, 2011.
- [130] C. C. Chan, A. Bouscayrol, and K. Chen, "Electric, hybrid, and fuel-cell vehicles: architectures and modeling," *IEEE Trans. Vehicular Tech.*, Vol. 59, No. 2, pp. 589-598, February 2010.
- [131] O. Onar and A. Khaligh, "Grid interactions and stability analysis of a distribution network with plug-in hybrid electric vehicle (PHEV) loads," in Proceedings of IEEE-2010 Applied Power Electronics Conference and Exposition (APEC2010), pp. 1755–1762, February 2010.
- [132] M. Yilmaz and P. T. Krein, "Review of the impact of vehicle-to-grid technologies on distribution systems and utility interfaces," *IEEE Trans. Power Electron.*, vol. 28, no. 12, pp. 5673–5689, December 2013.
- [133] J. C. Gomez and M. M. Morcos, "Impact of EV battery chargers on the power quality of distribution systems," *IEEE Trans. Power Delivery*, vol. 18, no. 3, pp. 975–981, July 2003.
- [134] C. L. Rui, W. S. Lih, S. D. Tswen, and C. T. Rong, "Sinusoidal ripple current charging strategy and optimal charging frequency study for li-ion batteries," *IEEE Trans. Ind. Electron.*, vol. 60, no. 1, pp. 88–97, January 2013.
- [135] S. J. Huang, B. G. Huang, and F. S. Pai, "Fast charge strategy based on the characterization and evaluation of LiFePO batteries," *IEEE Trans. Power Electron.*, vol. 28, no. 4, pp. 1555–1562, April 2013.
- [136] D. Jackson, A. Schultz, S. B. Leeb, A. Mitwalli, G. Verghese, and S. R. Shaw, "A multirate digital controller for a 1.5-kW electric vehicle battery charger," *IEEE Trans. Power Electron.*, vol. 12, no. 6, pp. 1000 –1006, Novmber 1997.
- [137] B. Singh, B. N. Singh, A. Chandra, K. Al-Haddad, A. Pandey, and D. P. Kothari, "A review of three-phase improved power quality ac-dc converters," *IEEE Trans. Ind. Electron.*, vol. 51, no. 3, pp. 641–660, June 2004.
- [138] M. A. Fasugba and P. T. Krein, "Gaining vehicle-to-grid benefits with unidirectional electric and plug-in hybrid vehicle chargers," *in Proc. IEEE Veh. Power and Propulsion Conf.*, pp. 1–6, September 2011.
- [139] Y. Lee, A. Khaligh, and A. Emadi, "Advanced integrated bi-directional AC/DC and DC/DC converter for plug-in hybrid electric vehicles," *IEEE Trans. Veh. Technol.*, vol. 58, no. 3, pp. 3970–3980, October 2009.

- [140] Y. Du, S. Lukic, B. Jacobson, and A. Huang, "Review of high power isolated bi-directional DC-DC converters for PHEV/EV DC charging infrastructure," in Proc. IEEE Energy Conversion Congr. Expo., pp. 553–560, September 2011,
- [141] X. Zhou, S. Lukic, S. Bhattacharya, and A. Huang, "Design and control of grid-connected converter in Bi-directional battery charger for plugin hybrid electric vehicle application," in Proc. IEEE Veh. Power and Propulsion Conf., pp. 1716–1721, September 2009.
- [142] X. Zhou, G. Wang, S. Lukic, S. Bhattacharya, and A. Huang, "Multifunction bi-directional battery charger for plug-in hybrid electric vehicle application," in Proc. IEEE Energy Conversion Congr. Expo., pp. 3930–3936, September 2009.
- [143] S. Haghbin, K. Khan, S. Lundmark, M. Alak["]ula, O. Carlson, M. Leksell, and O. Wallmark, "Integrated chargers for EV's and PHEV's: Examples and new solutions," in Proc. Int. Conf. Electrical Machines, pp. 1–6, 2010,
- [144] M. Grenier, M. H. Aghdam, and T. Thiringer, "Design of on-board charger for plug-in hybrid electric vehicle," in Proc. Power Electronics, Machine and Drives, pp. 1–6, 2010,
- [145] D. Thimmesch, "An SCR inverter with an integral battery charger for electric vehicles," *IEEE Trans. Ind. Appl.*, vol. 21, no. 4, pp. 1023–1029, August 1985.
- [146] W. E. Rippel, "Integrated traction inverter and battery charger apparatus," U.S. Patent 4 920 475, April 1990.
- [147] H. C. Chang and C. M. Liaw, "Development of a compact switched reluctance motor drive for EV propulsion with voltage-boosting and PFC charging capabilities," *IEEE Trans. Veh. Technol.*, vol. 58, no. 7, pp. 3198– 3215, September 2009.
- [148] SAE Electric Vehicle and Plug-in Hybrid Electric Vehicle Conductive Charge Coupler, SAE Standard J1772, Jan. 2010.
- [149] M. Budhia, G. A. Covic, J. T. Boys, and C. Y. Huang, "Development and evaluation of single sided flux couplers for contactless electric vehicle charging," in Proc. IEEE Energy Conversion Congr. Expo., pp. 614–621, September 2011.
- [150] K.W. Klontz, D. M. Divan, D.W. Novotny, and R. D. Lorenz, "Contactless battery charging system," U.S. Patent 5 157 319, September 1991.
- [151] K.W. Klontz, A. Esse, P. J.Wolfs, and D. M. Divan, "Converter selection for electric vehicle charger systems with a high-frequency high-power link," in

Proc. Rec.24th Annu. IEEE Power Electron. Spec. Conf., pp. 855–861, June 1993.

- [152] K. Throngnumchai, T. Kai, and Y. Minagawa, "A study on receiver circuit topology of a cordless battery charger for electric vehicles," in Proc. IEEE Energy Conversion Congr. Expo., Sep. 2011, pp. 843–850.
- [153] A. W. Green and J. T. Boys, "10 kHz inductively coupled power transfer concept and control," in IEE Proc. Power Electron. Variable-Speed Drives, pp. 694–699, October 1994.
- [154] J. T. Boys, G. A. Covic, and A. W. Green, "Stability and control of inductively coupled power transfer systems," in Proc. IEE Electric Power Appl., pp. 37–43, January 2000.
- [155] P. Sergeant and A. Van den Bossche, "Inductive coupler for contactless power transmission," *IET Elect. Power Appl.*, vol. 2, no. 1, pp. 1–7, January 2008.
- [156] S. R. Taddeo, and L. Beach, "Multi-Mode electric vehicle charger station" United States Patent Application Publication, Pub. No.: US 2013/0020993 A1, 2012.
- [157] J.H. Janh and Seal "Interval charger integrated device and method for controlling the same United States Patent Application Publication, Pub. No.: US 8,736,203 B2, 2012.
- [158] Stephen R. Taddeo, and Long Beach, "Multi-Mode electric vehicle charger station" United States, Patent Application Publication, Pub. No.: US 2013/0020993 A, 2012.
- [159] Z. Zhang, H. Zhao, S. Fu, J. Shi, and X. He, "Voltage and power balance control strategy for three-phase modular cascaded solid stated transformer," in Proc. 2016 IEEE Appl. Power Electron. Conf. Expo., pp. 1475–1480, 20– 24 March 2016.
- [160] Y. Shen, X. Sun, W. Li, X. Wu, and B. Wang, "A modified dual active bridge converter with hybrid phase-shift control for wide input voltage range," *IEEE Trans. Power Electron.*, vol. 31, no. 10, pp. 6884–6900, October 2016.
- [161] W. Choi, K. M. Rho, and B. H. Cho, "Fundamental duty modulation of dualactive-bridge converter for wide-range operation," *IEEE Trans. Power Electron.*, vol. 31, no. 6, pp. 4048–4064, Jun. 2016.
- [162] D. Sha, Q. Lin, F. You, X. Wang, and G. Xu, "A ZVS bidirectional threelevel DC–DC converter with direct current slew rate control of leakage inductance current," *IEEE Trans. Ind. Appl.*, vol. 52, no. 3, pp. 2368–2377, 2016.

- [163] X. Sun, X. Wu, Y. Shen, X. Li, and Z. Lu, "A current-fed isolated bidirectional DC–DC converter," *IEEE Trans. Power Electron.*, vol. 32, no. 9, pp. 6882–6895, 2017
- [164] A.S. Al-Ogaili, I. Aris, M.L. Othman, and N. Azis "Three Levels Hybrid Universal Electric Vehicle Charger" 2017, Filing for Patent IP
- [165] R. Ottersten, "On control of back-to-back converters and sensorless induction machine drives ", Department of Electric Power Engineering, Chalmers University of Technology, Goteborg, Sweden, 2003.

